US 20150213792A1

(19) **United States**

(12) **Patent Application Publication**

PERRY

(10) **Pub. No.: US 2015/0213792 A1**

(43) **Pub. Date: Jul. 30, 2015**

(54) **SUB-APERTURES FOR WIRELESS POWER TRANSFER**

(71) Applicant: **uBeam, Inc.**, Santa Monica, CA (US)

(72) Inventor: **Meredith PERRY**, Marina del Rey, CA (US)

(21) Appl. No.: **14/680,511**

(22) Filed: **Apr. 7, 2015**

Related U.S. Application Data

(63) Continuation of application No. 14/635,861, filed on Mar. 2, 2015, which is a continuation of application No. 13/477,551, filed on May 22, 2012, now Pat. No. 9,001,622.

(60) Provisional application No. 61/490,988, filed on May 27, 2011.

Publication Classification

(51) **Int. Cl.**


G10K 11/34	(2006.01)
H02J 7/00	(2006.01)
H04B 11/00	(2006.01)

(52) **U.S. Cl.**

CPC ***G10K 11/341*** (2013.01); ***H04B 11/00*** (2013.01); ***H02J 7/0052*** (2013.01)

(57) **ABSTRACT**

A signal generator generates an electrical signal that is sent to an amplifier, which increases the power of the signal using power from a power source. The amplified signal is fed to a sender transducer to generate ultrasonic waves that can be focused and sent to a receiver. The receiver transducer converts the ultrasonic waves back into electrical energy and stores it in an energy storage device, such as a battery, or uses the electrical energy to power a device. In this way, a device can be remotely charged or powered without having to be tethered to an electrical outlet.





TRANSMITTER 101
105
CONTROLLER
102
114
POWER SOURCE
103
SIGNAL GENERATOR
104
AMPLIFIER
106
SENDING TRANSDUCER
107
112
113
108 RECEIVER
115
PROCESSOR
ENERGY 110 STORAGE DEVICE
109
RECEIVING TRANSDUCER
111
CONTROLLER

FIGURE 1




FIGURE 2




FIGURE 3

SUB-APERTURES FOR WIRELESS POWER TRANSFER

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application claims the benefit of U.S. patent application Ser. No. 14/635,861, filed on Mar. 2, 2015, which claims the benefit of U.S. patent application Ser. No. 13/477,551, filed on May 22, 2012, which claims the benefit of U.S. Provisional Patent Application No. 61/490,988, filed May 27, 2011, all of which are herein incorporated herein by reference in its entirety. This application is also related to U.S. patent application Ser. No. 13/477,452, entitled, "Sender Communications for Wireless Power Transfer"; U.S. patent application Ser. No. 13/477,551, entitled "Receiver Communications for Wireless Power Transfer"; U.S. patent application Ser. No. 13/477,555, entitled "Sender Transducer for Wireless Power Transfer"; U.S. patent application Ser. No. 13/477,557, entitled, "Receiver Transducer for Wireless Power Transfer"; U.S. patent application Ser. No. 13/477,565, entitled, "Sender Controller for Wireless Power Transfer"; and U.S. patent application Ser. No. 13/477,574, entitled, "Receiver Controller for Wireless Power Transfer"; all of which were filed on May 22, 2012, and each and every one of which is incorporated herein in its entirety.

BACKGROUND

[0002] Devices that require energy to operate can be plugged into a power source using a wire. This can restrict the movement of the device and limit its operation to within a certain maximum distance from the power source. Even most battery-powered devices must periodically be tethered to a power source using a cord, which can be inconvenient and restrictive.

BRIEF SUMMARY

[0003] According to an embodiment of the disclosed subject matter, a system comprising at least one first transducer adapted and configured to convert electrical energy to ultrasonic energy in the form of ultrasonic waves. The first transducer is in communication with a first controller, and the first controller is in communication with a first communication device.

[0004] In another embodiment of the disclosed subject matter, a system comprises at least one second transducer adapted and configured to convert ultrasonic energy in the form of ultrasonic waves to electrical energy. The second transducer is in communication with a second controller, and the second controller is in communication with a second communication device.

[0005] Additional features, advantages, and embodiments of the disclosed subject matter may be set forth or apparent from consideration of the following detailed description, drawings, and claims. Moreover, it is to be understood that both the foregoing summary and the following detailed description are exemplary and are intended to provide further explanation without limiting the scope of the claims.

BRIEF DESCRIPTION OF THE DRAWINGS

[0006] The accompanying drawings, which are included to provide a further understanding of the disclosed subject matter, are incorporated in and constitute a part of this specification. The drawings also illustrate embodiments of the disclosed subject matter and together with the detailed description serve to explain the principles of embodiments of the disclosed subject matter. No attempt is made to show structural details in more detail than may be necessary for a fundamental understanding of the disclosed subject matter and various ways in which it may be practiced.

[0007] FIG. **1** shows a system in accordance with an embodiment of the invention.

[0008] FIG. **2** shows a system in accordance with an embodiment of the invention.

[0009] FIG. **3** shows a system in accordance with an embodiment of the invention.

DETAILED DESCRIPTION

[0010] Embodiments of the disclosed subject matter can convert electrical energy into acoustic energy, which can be beamed to a device where it is converted back into electrical energy. The converted electrical energy can be used to power the device and to charge one or more energy storage components of the device, such as a battery, a capacitor, etc. This can obviate the need for constant or periodic tethering to a power source using a cord. Embodiments can transfer energy to several devices at once, in rotation or in any suitable sequence, with dwell times of any suitable duration.

[0011] FIG. **1** shows a system in accordance with the disclosed subject matter. Transmitter **101** can receive electrical energy from power source **102** (such as an electrical outlet or a battery) as input. Signal generator **103** can generate a signal that can be amplified by amplifier **104**. This can be done under the control of controller **105**. The amplified signal can be sent to sending transducer **106**, and the ultrasonic energy in the form of ultrasound waves **107** can be transmitted through a medium such as the air. Receiver **108** can includes receiving transducer **109**, which receives ultrasonic energy in the form of ultrasonic waves and converts it to electrical energy, which can be used to charge energy storage device **110** or power processor **111**. Examples of energy storage device **110** can include a battery, a capacitor, an induction circuit, etc. Examples of device **105** can include a smartphone (such as an Android mobile device, an iPhone, a mobile device having a Microsoft operating system), a portable computer (such as an Apple laptop, a laptop having a Microsoft operating system, etc.), an electronic content reader, (such as the Amazon Kindle, the Apple iPad, etc.) and so on. Controller **111** can control the receiving transducer **109** and/or energy storage device **110**.

[0012] Controller **105** can be coupled to antenna **112** and controller **111** can be coupled to antenna **113**. As described below, the transmitter controller **105** and receiver controller **111** can communicate through antennas **112** and **113**.

[0013] Sending transducer **106** can comprise a plurality of transducers arranged in an array that can produce a focused beam of ultrasonic energy. Sending transducer **106** may include at least one Capacitive Micro machined Ultrasonic Transducer (CMUT), a Capacitive Ultrasonic Transducer (CUT), an electrostatic transducer or any other transducer suitable for converting electrical energy into acoustic energy. To generate focused ultrasonic energy via a phased array, sending transducer **106** can include a timed delay transducer or a parametric array transducer, or a bowl-shaped transducer array. Transmitter **101** can operate for example between about 20 to about 120 kHz for transmission of ultrasonic energy through air, and up to about 155 dB, for example. For ultrasonic transmission through other medium, transmitter **101**

can operate at frequencies greater than or equal to 1 MHz, for example. Sending transducer **106** may have a high electro-mechanical conversion, for example an efficiency of about 40%, corresponding to about a 3 dB loss.

[0014] Transmitter controller **105** can cause the sending transducer **106** to emit ultrasonic waves based on the proximity of the sending transducer **106** (or transmitter **101** in general) to receiving transducer **109**. Receiving transducer **109** can convert ultrasonic energy received from sending transducer **106** to electrical energy. As used herein, proximity can be the actual or effective distance between the sending transducer **106** or the like and receiving transducer **109** or the like. Effective distance can be based on the efficiency of energy transmission between sending transducer **106** and receiving transducer **109** based on various factors that can include, without limitation, their relative locations; the characteristics of the conductive medium (e.g., the air, tissue, etc.) between transmitter and receiver; the relative orientation of the transmitter and receiver; obstructions that may exist between the transmitter and receiver; relative movement between transmitter and receiver; etc. In some cases, a first transmitter/receiver pair may have a higher proximity than a second transmitter/receiver pair, even though the first pair is separated by a greater absolute distance than the second pair.

[0015] Transmitter controller **105** may cause a beam of ultrasonic energy to be directed toward receiver transducer **109**. Further, transmitter controller **105** can cause sending transducer **105** to emit ultrasonic waves having at least one frequency and at least one amplitude. Transmitter controller **105** can cause the sending transducer **106** to change the frequency and/or amplitude of at least some of the ultrasonic waves based on the proximity and/or location of sending transducer **106** to receiving transducer **109**. Additionally, transmitter controller **105** can cause sending transducer **105** to change the amplitude of at least some of the ultrasonic waves based on the frequency of the ultrasonic energy emitted by sending transducer or based on information regarding the receipt of ultrasonic energy as determined by receiving controller **111**.

[0016] Sending controller **105** and receiving controller **111** can communicate through antennas **112** and **113**. In this way, receiving controller can essentially control the character and amplitude of the energy generated by sending transducer **106** by sending commands to sending controller **105**. Also, sending controller **105** can control the characteristics of sending transducer **106** based upon data and/or commands received from receiving controller **111**. Likewise, sending controller can control the characteristics of the energy sent by sending transducer **106** independently of input from receiving controller **111**.

[0017] Transmitter controller **105** can include a transmitter communications device (not shown) that can send an interrogation signal to detect receiving transducer **109**. The transmitter communications device can send a control signal to a receiver communications device (not shown) coupled to receiver controller **111**. Receiver controller **111** can control receiver transducer **109**. The control signal may include the frequency and/or amplitude of the ultrasonic energy emitted by sending transducer **106**. The control signal can be used to determine the proximity and/or orientation of sending transducer **106** to receiving transducer **109**. Additionally, the control signal may include an instruction to be executed by receiving controller **109** and may also include information about the impedance of sending transducer **106**.

[0018] The sender communication device can receive a control signal from the receiver communication device, which can be in communication with receiver controller **111**. The control signal may include a desired power level, the frequency and/or amplitude of ultrasonic energy received from the sender transducer **106**. Additionally, the control signal may include the impedance of the receiving transducer **109**, a request for power, and/or an instruction to be executed by the transmitter controller **105**. The control signal may be used to determine the proximity of the sender transducer to the receiver transducer and/or the relative orientation of the sender transducer to the receiver transducer. Further, the control signal may also indicate a power status. Such a power status can indicate, for example, the amount of power available to the receiver **108**, e.g., percent remaining, percent expended, amount of joules or equivalent left in the receiver energy storage device **110**. The control signal may be transmitted by modulating at least some of the ultrasonic waves and/or may be transmitted out-of-band, e.g., using a separate radio frequency transmitter, or by sending a signal through a cellular telephone network or via a Wi-Fi network. For example, the signal may be transmitted by text, instant message, email, etc.

[0019] Transmitter **101** can further include a signal generator **103**, variously known as a function generator, pitch generator, arbitrary waveform generator, or digital pattern generator, which can generate one or more waveforms of ultrasonic waves. A controller **105** can itself include an oscillator, an amplifier, a processor, memory, etc., (not shown.) The processor of the controller can also execute instructions stored in memory to produce specific waveforms using the signal generator **103**. The waveforms produced by the signal generator **103** can be amplified by the amplifier **104**. The controller **105** can regulate how and when the transducer **106** can be activated.

[0020] The electrical power source **102** for transmitter **101** may be an AC or DC power source. Where an AC power source is used, transmitter **101** may include a power processor **114** that is electrically connected with the signal generator **103**. The power processor **114** can receive AC power from the power source **102** to generate DC power.

[0021] Transmitted ultrasound beams **107** can undergo constructive interference and generate a narrow main lobe and low-level side lobes to help focus and/or direct the ultrasonic energy. The ultrasonic energy generated by transmitter **101** may also be focused using techniques such as geometric focusing, time reversal methods, beam forming via phase lags, or through the use of an electronically controlled array.

[0022] The transmitter **101** may scan an area for receivers, may sense location of a receiver within a room, may track a receiver, and may steer an ultrasonic beam toward the receiver. Transmitter **101** may optionally not emit ultrasonic energy unless a receiver **108** is determined to be within a given range.

[0023] Transmitter **101** may be mechanically and/or electronically oriented towards a receiver **108**. For example, in some embodiments, the transmitter can be tilted in the XY-direction using a motor and the beam can be steered electronically in the Z-direction. The transmitter **101** may transmit ultrasonic energy to the receiver **108** via line of sight transmission or by spreading the ultrasound pulse equally in all directions. For line of sight transmission, the transmitter **101** and receiver **108** may be physically oriented toward each other: the transmitter **101** can physically or electronically (or

both) be aimed at the receiver **108** or the receiver **108** can be so aimed at the transmitter **101**. The transmitter **101** may transmit signals, such as an ultrasonic, radio, or other such signal, to be sensed by the receiver **108** for the purpose of detecting orientation, location, communication, or other purposes, or vice versa. One or both of the transmitter **101** and receiver **108** can include a signal receiver such as antennas **112** and **113**, respectively, that can receive signals from the receiver **108** or transmitter **101**, respectively. Likewise, signals may be transmitted from transmitter **101** to receiver **108** using the ultrasonic waves themselves.

[0024] The transmitter **101** can be thermo regulated by managing the duty cycles of the signal generator and other components. Thermoregulation can also be achieved by attaching heat sinks to the transmitting transducer **106**, using fans, and/or running a coolant through the transmitter, and other thermoregulation methods.

[0025] Receiver **108** can include a receiver transducer **109** that can convert ultrasonic energy in the form of ultrasonic waves to electrical energy. Receiver transducer **109** may include one or more transducers arranged in an array that can receive unfocused or a focused beam of ultrasonic energy. Receiver transducer **108** may include at least one Capacitive Micromachined Ultrasonic Transducer (CMUT), a Capacitive Ultrasonic Transducer (CUT), or an electrostatic transducer, or a piezoelectric-type transducer described below, a combination thereof or any other type or types of transducer that can convert ultrasound into electrical energy. For receiving focused ultrasonic energy via a phased array, receiver transducer **109** may include a timed delay transducer or a parametric transducer. Receiver **108** can operate for example between about 20 to about 120 kHz for receipt of ultrasonic energy through air, and up to about 155 dB, for example. For receiving ultrasonic energy through other medium, receiver **108** can operate at frequencies greater than or equal to 1 MHz, for example. Receiver transducer **109** can have a high electromechanical conversion efficiency, for example of about 40%, corresponding to about a 3 dB loss.

[0026] Receiver transducer **109** may supply electrical energy to an energy storage device **110** and/or a processor **115**. Examples of an energy storage device **110** can include, but are not limited to, a battery, a capacitive storage device, an electrostatic storage device, etc. Examples of a processor can include, but not limited to, a processor or chipset for a smartphone (such as an Android mobile device, an iPhone, a mobile device having a Microsoft operating system), a portable computer (such as an Apple laptop, a laptop having a Microsoft operating system, etc.), an electronic content reader, (such as the Amazon Kindle, the Apple iPad, etc.) and so on.

[0027] In accordance with various embodiments, receiver **108** can include a receiver transducer **109** that can be one or more of a piezoelectrically actuated flexural mode transducer, a flextensional transducer, a flexural mode piezoelectric transducer, and/or a Bimorph-type piezoelectric transducer ("PZT") such as flexing type piezoelectric element of the kind manufactured by Morgan Electro Ceramics. These can be attached to a metal membrane and the structure can resonate in a flexing mode rather than in a brick mode. In embodiments, the structure can be clamped around the rim by an attachment to the transducer housing. The PZT slab can be electrically matched to the rectifier electronics. This can be a high Q resonator (it can resonate at a single frequency) that can be held by very low impedance material.

[0028] Receiver **108** can further include a receiver controller **111** in communication with the receiver transducer **109**. Receiver controller **109** can cause the receiver transducer **109** to receive ultrasonic waves based on the proximity of the receiver transducer **109** to a sender transducer **106**. Receiver transducer **109** can convert ultrasonic energy received from a sender transducer **106** to electrical energy. Proximity can be the actual or effective distance between the receiver transducer **109** and sender transducer **106**. Effective distance can be based on the efficiency of energy transmission between receiver transducer **109** and sender transducer **106** based on various factors that can include, without limitation, their relative locations; the characteristics of the conductive medium (e.g., the air, tissue, etc.) between transmitter and receiver; the relative orientation of the transmitter and receiver; obstructions that may exist between the transmitter and receiver; relative movement between transmitter and receiver; etc. In some cases, a first transmitter/receiver pair may have a higher proximity than a second transmitter/receiver pair, even though the first pair is separated by a greater distance than the second pair.

[0029] Receiver controller **109** may cause a beam of ultrasonic energy to be received from sender transducer **106**. Further, receiver controller **109** can cause the sender transducer **106** to receive ultrasonic waves having at least one frequency and at least one amplitude.

[0030] Receiver **108** can further include a communication device (not shown) that can send an interrogation signal through antenna **113** to detect transmitter **101** and help to determine characteristics of transmitter **101**, including sending transducer **106**. The receiver communication device can send a control signal to a sender communication device, which can be in communication with sender controller **105**. Sender controller **105** can control sender transducer **106**. The control signal may include the frequency and/or amplitude of the ultrasonic waves received by receiver transducer **109**. The control signal may be used to determine the proximity and/or relative orientation of receiver transducer **109** to sender transducer **106**. Additionally, the control signal may include, without limitation, an instruction to be executed by sender controller **105**; the impedance of receiver transducer **109**; a desired power level; a desired frequency, etc.

[0031] The receiver communications device may receive a control signal from a sender communications device that can be in communication with sender controller **105**. The control signal may include the frequency and/or amplitude of ultrasonic energy emitted by sender transducer **106**. Additionally, the control signal may include an instruction to be executed by receiver controller **111** and may also include an interrogation signal to detect a power status from receiver transducer **109**. The control signal may be used to determine the proximity and/or relative orientation of receiver transducer **109** to sender transducer **106**.

[0032] A communications device can send a signal by modulating the ultrasonic waves generated by the transducer for in-band communications. The communication device can also be used to modulate an out-of-band signal, such as a radio signal, for communication to another communication device. The radio signal can be generated by a separate radio transmitter that may use an antenna.

[0033] The system may include communication between receiver and transmitter to, for example, adjust frequency to optimize performance in terms of electro acoustical conversion, modulate ultrasonic power output to match power

demand at a device coupled to the receiver, etc. For example, if it is determined that the ultrasound waves received by the receiver **108** are too weak, a signal can be sent through the communications devices to the transmitter **101** to increase output power. Sender controller **105** can then cause sending transducer **106** to increase the power of the ultrasonic waves being generated. In the same way, the frequency, duration, and directional characteristics (such as the degree of focus) of the ultrasonic waves may be adjusted accordingly.

[0034] Thus, in accordance with embodiments of the disclosed subject matter, the transmitter **101** and receiver **108** can communicate to coordinate the transmission and receipt of ultrasonic energy. Communications between the transmitter **101** and receiver **108** can occur in-band (e.g., using the ultrasonic waves that are used to convey power from the transmitter to the receiver to also carry communications signals) and/or out-of-band (e.g., using separate ultrasonic waves from those used to carry power or, for example, radio waves based on a transmitter or transceiver at the transmitter and receiver.) In an embodiment, a range detection system (not shown) can be included at the transmitter **101**, at the receiver **108** or both. The range detection system at the transmitter can use echolocation based on the ultrasound waves sent to the receiver, the Bluetooth wireless communications protocol or any other wireless communications technology suitable for determining the range between a device and one or more other devices. For example, the strength of a Bluetooth or Wi-Fi signal can be used to estimate actual or effective range between devices. For example, the weaker the signal, the more actual or effective distance can be determined to exist between the two devices. Likewise, the failure of a device to establish a communications link with another device (e.g., using a Bluetooth or Wi-Fi (e.g., 802.11) signal with another device can establish that the other device is beyond a certain distance or range of distances from a first device. Also, a fraction of the waves can reflect back to the transmitter from the receiver. The delay between transmission and receipt of the echo can help the transmitter to determine the distance to the receiver. The receiver can likewise have a similar echolocation system that uses sound waves to assess the distance between the receiver and the transmitter.

[0035] In an embodiment of the presently disclosed subject matter, impedance of the first **106** and second **109** transducers may be the same and/or may be synchronized. In this regard, for example, both transducers **106** and **109** may operate at the same frequency range and intensity range, and have the same sensitivity factor and beam width.

[0036] Communications between transmitter **101** and receiver **108** can also be used to exchange impedance information to help match the impedance of the system. Impedance information can include any information that is relevant to determining and/or matching the impedance of the transmitter and/or receiver, which can be useful in optimizing the efficiency of energy transfer. For example, a receiver **108** can send impedance information via a communication signal (e.g., a "control signal") that includes a frequency or a range of frequencies that the receiver **108** is adapted to receive. The frequency or range of frequencies may be the optimal frequencies for reception. Impedance information can also include amplitude data from the receiver **108**, e.g., the optimal amplitude or amplitudes at which a receiver **108** can receive ultrasound waves. In an embodiment, an amplitude is associated with a frequency to identify to the transmitter **101** the optimal amplitude for receiving ultrasound at the receiver **108** at the specified frequency. In an embodiment, impedance information can include a set of frequencies and associated amplitudes at which the receiver **108** optimally can receive the ultrasound waves and/or at which the transmitter **101** can optimally transmit the ultrasound. Impedance information can also include information about the sensitivity of the transmitter **101** and/or receiver **108**, beam width, intensity, etc. The sensitivity may be tuned in some embodiments by changing the bias voltage, at least for embodiments using CMUT technology.

[0037] Communications can also include signals for determining location information for the transmitter **101** and/or the receiver **108**. In accordance with embodiments of the disclosed subject matter, location information for receivers **108** can be associated with receiver identifiers (e.g., Electronic Identification Numbers, phone numbers, Internet Protocol, Ethernet or other network addresses, device identifiers, etc.) This can be used to establish a profile of the devices at or near a given location at one time or over one or more time ranges. This information can be provided to third parties. For example, embodiments of the system may determine a set of device identifiers that are proximate to a given location and to each other. The fact that they are proximate; the location at which they are proximate; information about each device (e.g., a device's position relative to one or other device, a device's absolute location, power information about a device, etc.) can be shared with a third party, such as an third party application that would find such information useful. Further, similar such information can be imported into embodiments of the present invention from third party sources and applications.

[0038] Embodiments of communications protocols between transmitter **101** and receivers **108** can be used to dynamically tune the beam characteristics and/or device characteristics to enable and/or to optimize the transmission of power from transmitter **101** to receiver **108**. For example, at a given distance, it may be optimal to operate at a given frequency and intensity. A transmitter **101** may server several different devices by, for example, steering and tuning the beam for each receiver device **108**, e.g., in a round-robin or random fashion. Thus, the beam for a device A may be at 40 kHz and 145 dB, device B may be at 60 kHz and 130 dB and device C at 75 kHz and 150 dB. The transmitter can tune itself to transmit an optimally shaped beam to each of these dynamically, changing beam characteristics as the transmitter shifts from one device to another. Further, dwell time on each receiver device **108** can be modulated to achieve particular power transfer objectives.

[0039] In an embodiment, a transmitter **101** can receive a signal (one or more control signals) from a receiver **108** indicating one or more of the receiver's distance, orientation, optimal frequencies, amplitudes, sensitivity, beam width, etc. For example, optimal frequency when a receiver is less than 1 foot away from a transmitter may be 110 kHz with a 1.7 dB/ft attenuation rate, and optimal frequency when a receiver is farther than 1 foot away from a transmitter may be 50 kHz with a 0.4 dB/foot attenuation rate. The receiver can detect the distance and provide a signal to the transmitter to change its frequency accordingly. In response, the transmitter can tune itself to transmit the best beam possible to transfer the most power in the most reliable fashion to the receiver. These parameters can be dynamically adjusted during the transmission of ultrasonic energy from the transmitter to the receiver,

e.g., to account for changes in the relative positions of the transmitter and receiver, changes in the transmission medium, etc.

[0040] Likewise, a receiver **108** may configure itself in response to signals received from a transmitter **101**. For example, a receiver **108** may tune to a given frequency and adjust its sensitivity to most efficiently receive and convert ultrasound waves from the transmitter **101** to electrical energy.

[0041] Dwell time of a transmitter **101** on a receiver **108** can also be adjusted to optimize the energy delivered by a transmitter to several receivers around the same time. For example, the transmitter **101** may receive power requirements information from each of five receivers. It may dwell on the neediest receiver for a longer time interval than a less needy receiver as it services (e.g., sends ultrasound waves to) each receiver, e.g., in round-robin fashion.

[0042] Embodiments of the present invention include a system that can include a sender transducer coupled to the amplifier. The sender transducer can be a capacitive micromachined ultrasound transducer, another type of capacitive ultrasound transducer, an electrostatic ultrasound transducer, a piezoelectric type ultrasound transducer, etc. A capacitive transducer includes any transducer that converts any capacitively-stored energy into ultrasonic energy. An electrostatic transducer is one that uses any electrostatically-stored energy into ultrasound energy. A piezoelectric-type transducer is one that generates ultrasonic energy based on subjecting dielectric crystals to mechanical stress.

[0043] The transducer can be configured as an array of transducers and/or apertures. This can be used to produce a beam of ultrasonic energy. The transducer can be controlled by the sender controller to produce one or more ultrasonic beams and can produce each such beam or combination of beams with a given shape, direction, focal length and any other focal property of the beam. The transducer can include one or more steering components, including one or more electronic steering components, e.g., one or more configurations or patterns or array elements and/or apertures. One or more of the apertures can be convex to help control beam properties such as focal length. A transducer can have a mechanical steering component that works alone or in combination with one or more electronic steering components to control focal properties of one or more ultrasonic beams.

[0044] In accordance with embodiments of the present invention, a system can include a sender that has a first value of a configuration parameter. A configuration parameter can be used to describe an actual or potential state or condition of a sender or a receiver and can include, for example, an amplitude, a frequency, a steering parameter, an instruction, a power status, a transmitter characteristic and a receiver characteristic. A sender characteristic can describe an actual or potential condition of the sender or receiver. For example, a sender characteristic can relate to the power state of the sending transducer and have the values ON (emitting ultrasound to be converted into electrical energy by a receiver) or OFF. Another power configuration parameter can relate to the power level of the emitted ultrasonic energy in various units, such as watts per square inch, decibels, etc.

[0045] A characteristic can describe an actual or potential condition of the sender or receiver that can be fixed. For example, a characteristic can be a telephone number, Electronic Serial Number (ESN), Mobile Equipment Identifier (MEID), IP address, MAC address, etc., or a mobile or stationary device that can be a sender or receiver. A characteristic can be a fixed impedance or other electronic property (e.g., transducer type, software/firmware version, etc.) of a device.

[0046] In accordance with embodiments of the present invention, a device has a first configuration parameter. Based on input received through the sender communications device, the sender can change its configuration parameter value to a second configuration parameter value and thereby change its state and/or behavior. Mechanisms for changing the sender configuration parameter can include receiving a new configuration parameter value through the communications device. The new configuration parameter value can originate from a receiver to which the sender is or intends to transmit ultrasonic energy. For example, a sender can be transmitting ultrasonic energy at a first power level and a receiver can send a message to the sender requesting that the energy be transmitted at a second power level. For example, a receiver can send a request asking that the power of transmitted ultrasound be boosted from 120 dB to 140 dB. The sender can then change its power level configuration parameter from 120 dB to 140 dB.

[0047] Another mechanism is to change a first configuration parameter based on input received through the communications device, even when that input does not specify a new (second) value for the configuration parameter. For example, input can be received at the sender communications device from a receiver that includes a request to increase the power of the transmitted ultrasonic energy. In response, the sender can change the value of the power configuration parameter from the first value to a second value, e.g., from 120 dB to 140 dB. Likewise, one or more configuration parameters can be changed based on a combinations of inputs from one or more receivers or third parties. For example, a beam shape can be changed based upon a receiver characteristic, such as the type of receiver transducer at the receiver.

[0048] A configuration parameter can be or include one or more steering parameters. Examples of steering parameters include a steering angle, such as the angle at which a mechanical tilt device has disposed or can disposed one or more elements of a transducer; a dispersion angle, such as the angle at which a threshold power occurs in an ultrasonic beam (e.g., the beam width expressed as an angle); a focal length, such as a distance in centimeters at which an ultrasonic beam becomes most focused; a transmitter location, such as the angle and distance of a receiver from a transmitter, or the distance of a transmitter from a receiver, or the absolute position (e.g., from a given reference point) of a sender or receiver; and a relative orientation of a sender and receiver, such as the difference in the relative orientation of a sender transducer and a receiver transducer, expressed in the degrees from parallel. For example, when one transducer is parallel to another, they can be said to have a zero degree offset. When one is perpendicular in orientation to another, they can have a ninety degree offset, etc.

[0049] Another mechanism is to change a first steering parameter in order to adjust and/or improve the efficiency of the transmission of ultrasonic energy to a receiver. The steering parameter can be changed based on input received through the communications device, even when that input does not specify a new (second) value for the steering parameter. For example, input can be received at the sender communications device from a receiver that includes an amount of the transmitted ultrasonic energy being received, e.g., 120 dB.

In response, the sender can change the value of the steering parameter, e.g., relative orientation, from the first value to a second value, e.g., from a ninety degree offset to a zero degree offset. As a result of changing/adjusting the steering parameter, the efficiency of the transmission of ultrasonic energy to the receiver may improve, and the amount of the transmitted ultrasonic energy being received may increase, e.g., from 120 dB to 140 dB. For example, the amount of power at the receiver can be monitored by the receiver and used as a basis for generating an input to be sent to the sender to adjust one or more of its configuration parameters. This can change the way in which ultrasonic energy is transmitted by the sender to the receiver, e.g., by changing the tilt of a mechanical steering mechanism for the sender transducer, by changing the power level of the transmitted ultrasonic energy, by changing the electronic steering and beam shaping of the ultrasonic energy at the sender, etc. In this way, the receiver can provide real-time or near-real-time feedback to the sender so that the sender can tune the way in which it sends ultrasonic energy to the receiver to improve the rate at which energy is transferred (e.g., power), the continuity of energy transfer, the duration of energy transfer, etc.

[0050] Beam steering and focusing can be achieved by causing the controller to modulate (control) the phase of the electrical signal sent to the sending transducer or to various elements of the sending transducer. For wide-angle steering, elements of size $\lambda/2$ can be used, e.g., having a size of around 4 mm. Some semiconductor companies (Supertex, Maxim, Clare, etc.) manufacture high voltage switch chips that can allow a few high-power oscillator circuits to take the place of thousands of transmitters. An example of a useful design can have four oscillators with phases of 0, $\pi/2$, π and $3\pi/2$. Switches can be arranged so that each transmit element can be connected to any of the four phases. The pitch of the switch-matrix can then be smaller than the pitch of the transducer array, which can facilitate interconnection. A small amount of memory can store the entire set of switch arrangements needed for an arbitrary number of steering and focusing positions. A simple microcontroller (e.g., an ARM microcontroller) can manage the steering/focusing computation.

[0051] Beam steering and focusing can be made more manageable in various ways. An electronic steering mechanism can be combined with a mechanical tilt mechanism in a direction orthogonal to that of the electronic steering mechanism to steer and focus the beam. For example, the transmitter can be relatively fixed in azimuth (horizontal dimension) but mechanically steerable in elevation (vertical dimension). Tracking vertically can be achieved by a mechanical tilt, driven by the signaling from the receiver, or from a transmitter, either directly or through the receiver, or with input from both and/or a third party, such as a power-tracking server. Electronic steering and focusing can be used for the azimuthal (horizontal) beam.

[0052] Some embodiments can tilt in both azimuth and elevation. In such cases, a two dimensional array with certain elements (e.g., a 15×15 array of 2λ elements) can perform focusing and steering. In some embodiments, the element size can grow from $\lambda/2$ to 2λ or larger. In some embodiments, the electronically steered array can be embedded in a mechanically focused transducer. A smaller matrix array can be positioned at the center of curved transducer. The curvature can create a focus in a given direction and at a certain average depth, e.g., one meter. The electronically focusing portion in the center can further adjust the focusing characteristics of the beam.

[0053] In some embodiments, the output can be split asymmetrically between azimuth and elevation, allowing for sophisticated beam control. In various embodiments, the aperture can be divided into several sub-apertures. Some or all of the sub-apertures can have different steering capabilities, enabling such an arrangement to produce a plurality of foci, which may be adjacent to each other. FIG. **2** shows a divided aperture apparatus in accordance with embodiments of the present invention. Source aperture **201** of can be divided into separate sub-apertures **202**, **203** and **204**. Each sub-aperture **202**, **203** and **204** has its own target focus **205**, **206** and **207**, respectively. The phase of each of the three sources shown in FIG. **2** can be altered to change the focal length of the elevation aperture. The beam steering can be mechanical, electronic, or a combination of the two. This arrangement can also be focused by changing the phase between the sources. The efficiency of the transmitter can be maintained for targets over a range of depths around the mechanical foci established by the curvature of the sources.

[0054] FIG. **3** shows another focusing apparatus that uses azimuth aperture division to allow for an extended focus range over the target. Source targets **301**, **302**, **303** and **304** have respective target foci **305**, **306**, **307** and **308**. Steering and focusing can be accomplished electronically, mechanically, or a combination thereof. In the embodiment shown in FIG. **3**, the element size can be made small enough to avoid the need for aperture curvature and/or mechanical tilt. Dividing the array into segments can increase the size of the focal spots and allow them to be juxtaposed. The foci can move around on the surface of the receiver, e.g., to optimize the overall power transfer.

[0055] A mobile device application (e.g., an iPhone or Android application) may be associated with an embodiment of the present system to aid the user. The associated mobile application may locate an ultrasonic power system, in accordance with an embodiment of the disclosed subject matter, near or within range of the user's location. The mobile application may pinpoint the user's exact location and compare it to the strongest power signal location in the room, and direct the user to that power location. The mobile application may communicate with corresponding applications on other mobile devices, e.g., to share location information, transmitter and/or receiver information, data about the transmissivity of a given medium, etc.

[0056] In accordance with embodiments of the present invention, a given device may act as essentially as a relay between an initial transmitter and a terminal receiver device. Such a device (a "relay device" or an "intermediate device") may receive power from a first device, convert at least a part of the received power to electrical energy, re-convert it to acoustic energy and then beam that acoustic energy to the terminal receiver device. This can be useful when the terminal device may be out of range of the initial transmitter device, especially when the initial transmitter device stores a substantial amount of energy or is connected to a larger source of energy, such as an electrical outlet or a large external battery. This can also be used to arrange for a transfer energy from a device that has sufficient or an excess amount of stored energy to a device in need of energy, even when the latter may be out of range of the former without a relay or intermediate device.

[0057] The mobile application may also inform the user of how quickly its mobile application device is being charged and how much more power and/or time the device requires until it's fully charged. Additionally, the mobile application can indicate the user's "burn rate" based on the amount of data being used on the device at a given time based on a variety of factors, for example, how many programs/applications are open and can indicate that the device will need to charge again in a given time period. The mobile application may tell the user when the device is using power from the device battery or power from the wireless power system. For example, the mobile application may have a hard or soft switch to signal the transmitter when the device battery is less than 20% full, thereby reducing the use of dirty energy and allowing the system to supply the most power to those who need it to the most. Additionally, the user may have the ability to turn off their ultrasonic receptor and/or transmitter using the mobile application.

[0058] At least part of the receiver **108** may be in the shape of a protective case, cover, or backing for a device, such as a cell phone, that may be inside or outside the physical device. An energy storage device, such as a rechargeable battery, may be embedded within the receiver case. The receiver **108** may also be used in other devices such as a laptop, tablet, or digital reader, for example in a case or backing therefor. The receiver **108** may be embedded within the electronic housing or can be a physical attachment. The receiver **108** can be any shape or size and can function as an isolated power receiver or be connected to a number of devices to power them simultaneously or otherwise.

[0059] In an embodiment of the disclosed subject matter, the receiver **108** can be a medical device such as an implant, for example a pacemaker, or drug delivery system. The implant can be powered, or the storage device can be charged, using an ultrasonic transmitter **101**. The characteristics of the transmitter **101** and/or receiver **108** can be tuned taking into account the power needs of the device, the conduction parameters of the tissue between the transmitter **101** and receiver **108**, and the needs of the patient. For ultrasonic power transmission through animal or plant tissue, the receiver **108** can be embedded in a medical device and/or tissue to power or charge a chemical deliver or medical device such as an implanted device. For example, a transmitter **101** could be programmed to emit ultrasound waves at a given time to a receiver **108** located within a pacemaker device implanted in the body of a patient.

[0060] Certain embodiments of the present invention can be designed to deliver a relatively uniform pressure to a rectangle such as a surface of, on or in a mobile device. For example, an embodiment can be designed to deliver acoustic energy to a mobile device such as a smartphone of size 115× 58 mm at a distance of one meter from the transmitter with a transmit frequency in the range of 40-60 kHz (i.e. the wavelength can be 5.7 to 8.5 mm.)

[0061] The maximum power in some embodiments from transmitter to receiver can be 316 $W \cdot m^{-2}$, while the normalized amplitude or "gain" can be characterized as the pressure created from 1 Pa at the surface of the transmitter. A gain of less than one could mean that the energy transfer is less than ideal. A gain above one could mean that the power density at the transmitter should be reduced, e.g., for regulatory compliance, which may also be less than ideal. A design could create a gain of one, constant over the receiver area, and a gain less than one everywhere else. The system can track the motion of the phone and limit power loss in the face of relative motion and/or position change of the transmitter in relation to the receiver and/or vice versa.

[0062] Phase change across the phone can be minimized, even in view of changes in the angle between the plane of the transmitter and receiver, which can be facilitated by using separate receiver patches on the phone and/or with a multi-element transmitter, which can also raise the overall efficiency through better control of the acoustic field. Steering and focusing can be achieved electronically by varying the phase of the transmitter wave across the elements. Different steering angles and focus depths can have different values of phase at each element.

[0063] Various embodiments of the present invention can track the relative position and orientation of a transmitter and receiver, e.g., through an iOS or Android application and a wireless protocol such as Bluetooth or 802.11. Closed-loop communication between transmitter and receiver can permit the transmit beam to track the mobile device to minimize the phase changes of the beam across an element on or in the receiver.

[0064] When a receiver arrives within range of a transmitter, a two-way communication can be initiated. The receiver can signal its location and request transmission of acoustic power. As charging takes place, the phone can updates the transmitter about its location, the amount of power received and the distribution of acoustic energy at the receiver. An alert can be sent if the receiver is positioned in an orientation or location where the power transfer is inefficient. The foregoing description, for purpose of explanation, has been described with reference to specific embodiments. However, the illustrative discussions above are not intended to be exhaustive or to limit embodiments of the disclosed subject matter to the precise forms disclosed. Many modifications and variations are possible in view of the above teachings. The embodiments were chosen and described in order to explain the principles of embodiments of the disclosed subject matter and their practical applications, to thereby enable others skilled in the art to utilize those embodiments as well as various embodiments with various modifications as may be suited to the particular use contemplated.

1. A system, comprising:

a sender comprising:

a first signal generator;

a first amplifier coupled to the first signal generator, said first amplifier configured to receive power from a power source and to generate an electrical transmission signal adapted to be used to generate ultrasonic waves;

a sender transducer coupled to the first amplifier, the sender transducer adapted and configured to generate ultrasonic waves based on the electrical transmission signal received from the amplifier, the sender transducer comprising transmit elements adapted and configured to generate the ultrasonic waves and divided among two or more sub-apertures;

a sender controller coupled to at least one of the first signal generator, the first amplifier and the sender transducer, the sender controller adapted and configured steer the ultrasonic waves generated by the transmit elements of each of the two or more sub-apertures independently for each sub-aperture; and

a sender communications device adapted to communicate with a receiver communications device; and

the receiver comprising:

a receiver transducer adapted and configured to receive ultrasonic waves generated by the sender transducer, to generate a receiver electrical signal based on the received ultrasonic waves, and to connect to a receiver electrical storage device adapted and configured to store electrical energy based on the receiver electrical signal generated by the receiver transducer;

a receiver communications device adapted and configured to send input to the sender communications device; and

a receiver controller coupled to at least one of the receiver transducer and the receiver electrical storage device.

2. The system of claim **1**, wherein the receiver further comprises:

a receiver electrical storage device adapted and configured to store electrical energy based on the receiver electrical signal generated by the receiver transducer.

3. A system, comprising:

a signal generator;

an amplifier coupled to the signal generator, said amplifier configured to receive power from a power source and to generate an electrical transmission signal adapted to be used to generate ultrasonic waves;

a sender transducer coupled to the amplifier, the sender transducer adapted and configured to generate ultrasonic waves based on the electrical transmission signal received from the amplifier, the sender transducer comprising transmit elements adapted and configured to generate the ultrasonic waves and divided among two or more sub-apertures;

a sender controller coupled to at least one of the signal generator, the amplifier and the sender transducer, the sender controller adapted and configured steer the ultrasonic waves generated by the transmit elements of each of the two or more sub-apertures independently for each sub-aperture; and

a sender communications device adapted to communicate with a receiver.

4. The system of claim **3**, wherein the sender controller is further adapted and configured to target the ultrasonic waves from a first of the two or more sub-apertures at the receiver and the ultrasonic waves from a second of the two or more sub-apertures at a second receiver.

5. The system of claim **3**, wherein the sender controller is further adapted and configured to change the phase of the ultrasonic waves from a first of the two or more sub-apertures and change the phase of the ultrasonic waves from a second of the one or more-sub-apertures independently.

6. The system of claim **3**, wherein the sender controller is further adapted and configured to target the ultrasonic waves from a first of the two or more sub-apertures and the ultrasonic waves from a second of the two or more sub-apertures so that the foci of the ultrasonic waves from the first of the two or more sub-apertures overlaps with the foci of the ultrasonic waves from the second of the two or more sub-apertures.

7. The system of claim **3**, wherein the two or more sub-apertures are arranged horizontally on the sender transducer.

8. The system of claim **3**, wherein each of the two or more sub-apertures is curved.

9. The system of claim **3**, wherein each of the two or more sub-apertures is flat.

10. A method comprising:

emitting ultrasonic energy from transmit elements of a first sub-aperture of a sender transducer;

emitting ultrasonic energy from transmit elements of a second sub-aperture of the sender transducer;

steering the ultrasonic energy emitted from the transmit elements of the first sub-aperture to a first receiver; and

steering the ultrasonic energy emitted from the transmit elements of the second sub-aperture to a second receiver independently of the steering of the ultrasonic energy emitted from the transmit elements of the first sub-aperture.

11. The method of claim **10**, further comprising:

changing the phase of the ultrasonic energy emitted from the transmit elements of the first sub-aperture; and

changing the phase of the ultrasonic energy emitted from the transmit elements of the second sub-aperture independently of changing the phase of the ultrasonic energy emitted from the transmit elements of the first sub-aperture.

12. The method of claim **10**, further comprising:

steering the ultrasonic energy emitted from the transmit elements of one or both of the first sub-aperture or the second sub-aperture such that the foci of the ultrasonic energy emitted from the transmit elements of first sub-aperture overlaps the foci of the ultrasonic energy emitted from the transmit elements of the second sub-aperture.

* * * * *