US009298310B2

(12) **United States Patent**
Westerman et al.

(10) **Patent No.: US 9,298,310 B2**
(45) **Date of Patent: Mar. 29, 2016**

(54) **TOUCH SENSOR CONTACT INFORMATION**

(71) Applicant: **Apple Inc.**, Cupertino, CA (US)

(72) Inventors: **Wayne Carl Westerman**, Burlingame, CA (US); **John Greer Elias**, Townsend, DE (US)

(73) Assignee: **Apple Inc.**, Cupertino, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **14/476,545**

(22) Filed: **Sep. 3, 2014**

(65) **Prior Publication Data**

US 2015/0029152 A1 Jan. 29, 2015

Related U.S. Application Data

(60) Continuation of application No. 14/163,929, filed on Jan. 24, 2014, now Pat. No. 9,001,068, which is a continuation of application No. 11/830,793, filed on Jul. 30, 2007, now Pat. No. 8,698,755, which is a continuation of application No. 11/015,434, filed on Dec. 17, 2004, now Pat. No. 7,339,580, which is a continuation of application No. 09/919,266, filed on Jul. 31, 2001, now Pat. No. 6,888,536, which is a division of application No. 09/236,513, filed on Jan. 25, 1999, now Pat. No. 6,323,846.

(60) Provisional application No. 60/072,509, filed on Jan. 26, 1998.

(51) **Int. Cl.**
G06F 3/045 (2006.01)
G06F 3/041 (2006.01)
(Continued)

(52) **U.S. Cl.**
CPC ***G06F 3/0416*** (2013.01); ***G06F 3/0235*** (2013.01); ***G06F 3/041*** (2013.01); ***G06F 3/044*** (2013.01); ***G06F 3/0412*** (2013.01); ***G06F 3/0485*** (2013.01); ***G06F 3/0488*** (2013.01); ***G06F 3/04815*** (2013.01); ***G06F 3/04845*** (2013.01); ***G06F 3/04883*** (2013.01); ***G06F 3/04886*** (2013.01); ***G06K 9/00375*** (2013.01); ***G06K 9/6272*** (2013.01); ***G06K 9/6878*** (2013.01); ***H03K 17/9622*** (2013.01); *G06F 2203/04101* (2013.01); *G06F 2203/04104* (2013.01); *G06F 2203/04106* (2013.01); *G06F 2203/04808* (2013.01); *H03K 2217/960725* (2013.01)

(58) **Field of Classification Search**
USPC 345/156–184; 178/18.01–20.04
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,333,160 A 7/1967 Gorski
3,541,541 A 11/1970 Engelhart
(Continued)

FOREIGN PATENT DOCUMENTS

AU 2007286532 A1 4/2008
CA 1243096 10/1988
(Continued)

OTHER PUBLICATIONS

Final Office Action mailed Mar. 24, 2015, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 16 pages.
(Continued)

Primary Examiner — Jason Olson
Assistant Examiner — Sosina Abebe
(74) *Attorney, Agent, or Firm* — Morrison & Foerster LLP

(57) **ABSTRACT**

Apparatus and methods are disclosed for simultaneously tracking multiple finger and palm contacts as hands approach, touch, and slide across a proximity-sensing, multi-touch surface. Identification and classification of intuitive hand configurations and motions enables unprecedented integration of typing, resting, pointing, scrolling, 3D manipulation, and handwriting into a versatile, ergonomic computer input device.

33 Claims, 45 Drawing Sheets



(51) **Int. Cl.**

G06F 3/023	(2006.01)
G06F 3/044	(2006.01)
G06F 3/0481	(2013.01)
G06F 3/0484	(2013.01)
G06F 3/0485	(2013.01)
G06F 3/0488	(2013.01)
G06K 9/00	(2006.01)
H03K 17/96	(2006.01)
G06K 9/62	(2006.01)
G06K 9/68	(2006.01)

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,662,105 A 5/1972 Hurst et al.
3,798,370 A 3/1974 Hurst
4,017,848 A 4/1977 Tannas, Jr.
4,056,754 A 11/1977 Bailey et al.
4,219,847 A 8/1980 Pinkney et al.
4,220,815 A 9/1980 Gibson et al.
4,237,421 A 12/1980 Waldron
4,246,452 A 1/1981 Chandler
4,266,144 A 5/1981 Bristol
4,290,061 A 9/1981 Serrano
4,291,303 A 9/1981 Cutler et al.
4,340,911 A 7/1982 Kato et al.
4,526,043 A 7/1985 Boie et al.
4,550,221 A 10/1985 Mabusth
4,561,002 A 12/1985 Chiu
4,598,420 A 7/1986 Harvey
4,617,563 A 10/1986 Fujiwara et al.
4,618,989 A 10/1986 Tsukune et al.
4,658,428 A 4/1987 Bedros et al.
4,672,364 A 6/1987 Lucas
4,672,558 A 6/1987 Beckes et al.
4,686,332 A 8/1987 Greanias et al.
4,692,809 A 9/1987 Beining et al.
4,695,827 A 9/1987 Beining et al.
4,720,607 A 1/1988 De Moncuit
4,733,222 A 3/1988 Evans
4,734,685 A 3/1988 Watanabe
4,736,191 A 4/1988 Matzke et al.
4,743,895 A 5/1988 Alexander
4,746,770 A 5/1988 McAvinney
4,758,830 A 7/1988 Levien et al.
4,771,276 A 9/1988 Parks
4,775,765 A 10/1988 Kimura et al.
4,788,384 A 11/1988 Bruere-Dawson et al.
4,798,919 A 1/1989 Miessler et al.
4,806,846 A 2/1989 Kerber
4,812,833 A 3/1989 Shimauchi
4,831,218 A 5/1989 Wright
4,850,677 A 7/1989 Okumura
4,896,363 A 1/1990 Taylor et al.
4,898,555 A 2/1990 Sampson
4,906,983 A 3/1990 Parker
4,914,624 A 4/1990 Dunthorn
4,952,932 A 8/1990 Sugino et al.
4,962,463 A 10/1990 Crossno et al.
4,963,702 A 10/1990 Yaniger et al.
4,968,877 A 11/1990 McAvinney et al.
4,988,982 A 1/1991 Rayner et al.
5,003,519 A 3/1991 Noirjean
5,012,524 A 4/1991 LeBeau
5,016,008 A 5/1991 Gruaz et al.
5,017,030 A 5/1991 Crews
5,053,757 A 10/1991 Meadows
5,072,384 A 12/1991 Doi et al.
5,073,950 A 12/1991 Colbert et al.
5,113,041 A 5/1992 Blonder et al.
5,150,105 A 9/1992 Perbet et al.
5,155,813 A 10/1992 Donoghue et al.
5,168,531 A 12/1992 Sigel
5,178,477 A 1/1993 Gambaro
5,189,403 A 2/1993 Franz et al.
5,189,416 A 2/1993 Estes
5,189,711 A 2/1993 Weiss et al.
5,194,862 A 3/1993 Edwards
5,214,414 A 5/1993 Levine et al.
5,224,861 A 7/1993 Glass et al.
5,231,381 A 7/1993 Duwaer
5,241,139 A 8/1993 Gungl et al.
5,241,308 A 8/1993 Young
5,252,951 A 10/1993 Tannenbaum et al.
5,270,711 A 12/1993 Knapp
5,276,787 A 1/1994 Searby
5,281,966 A 1/1994 Walsh
5,293,430 A 3/1994 Shiau et al.
5,305,017 A 4/1994 Gerpheide
5,309,374 A 5/1994 Misra et al.
5,311,175 A 5/1994 Waldman
5,327,161 A 7/1994 Logan et al.
5,335,557 A 8/1994 Yasutake
5,341,133 A 8/1994 Savoy et al.
5,345,543 A 9/1994 Capps et al.
5,347,295 A 9/1994 Agulnick et al.
5,369,228 A 11/1994 Faust
5,374,787 A 12/1994 Miller et al.
5,376,948 A 12/1994 Roberts
5,379,057 A 1/1995 Clough et al.
5,389,951 A 2/1995 Baker
5,398,310 A 3/1995 Tchao et al.
5,402,151 A 3/1995 Duwaer
5,414,227 A 5/1995 Schubert et al.
5,420,607 A 5/1995 Miller et al.
5,420,936 A 5/1995 Fitzpatrick et al.
5,422,831 A 6/1995 Misra et al.
5,436,639 A 7/1995 Arai et al.
5,442,742 A 8/1995 Greyson et al.
5,459,463 A 10/1995 Gruaz et al.
5,463,388 A 10/1995 Boie et al.
5,463,696 A 10/1995 Beernink et al.
5,469,194 A 11/1995 Clark et al.
5,471,578 A 11/1995 Moran et al.
5,473,742 A 12/1995 Polyakov et al.
5,479,528 A 12/1995 Speeter
5,483,261 A 1/1996 Yasutake
5,488,204 A 1/1996 Mead et al.
5,495,077 A 2/1996 Miller et al.
5,505,072 A 4/1996 Oreper
5,513,309 A 4/1996 Meier et al.
5,515,738 A 5/1996 Tamori
5,521,986 A 5/1996 Curtin, II et al.
5,523,775 A 6/1996 Capps
5,530,455 A 6/1996 Gillick et al.
5,537,608 A 7/1996 Beatty et al.
5,541,372 A 7/1996 Baller et al.
5,543,588 A 8/1996 Bisset et al.
5,543,590 A 8/1996 Gillespie et al.
5,543,591 A 8/1996 Gillespie et al.
5,546,475 A 8/1996 Bolle et al.
5,548,667 A 8/1996 Tu
5,552,787 A 9/1996 Schuler et al.
5,563,632 A 10/1996 Roberts
5,563,996 A 10/1996 Tchao
5,565,658 A 10/1996 Gerpheide et al.
5,572,717 A 11/1996 Pedersen
5,579,036 A 11/1996 Yates, IV
5,581,276 A 12/1996 Cipolla et al.
5,581,484 A 12/1996 Prince
5,581,681 A 12/1996 Tchao et al.
5,583,946 A 12/1996 Gourdol
5,588,098 A 12/1996 Chen et al.
5,589,856 A 12/1996 Stein et al.
5,590,219 A 12/1996 Gourdol
5,592,566 A 1/1997 Pagallo et al.
5,594,469 A 1/1997 Freeman
5,594,806 A 1/1997 Colbert
5,594,810 A 1/1997 Gourdol
5,596,694 A 1/1997 Capps
5,600,735 A 2/1997 Seybold
5,600,781 A 2/1997 Root et al.
5,612,719 A 3/1997 Beernink et al.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,625,715 A 4/1997 Trew et al.
5,627,567 A 5/1997 Davidson
5,631,805 A 5/1997 Bonsall
5,631,976 A 5/1997 Bolle et al.
5,633,955 A 5/1997 Bozinovic et al.
5,634,102 A 5/1997 Capps
5,636,101 A 6/1997 Bonsall et al.
5,638,093 A 6/1997 Takahashi et al.
5,642,108 A 6/1997 Gopher et al.
5,644,653 A 7/1997 Sunakawa et al.
5,644,657 A 7/1997 Capps et al.
5,648,642 A 7/1997 Miller et al.
5,649,070 A 7/1997 Connell et al.
5,666,113 A 9/1997 Logan
5,666,502 A 9/1997 Capps
5,666,552 A 9/1997 Greyson et al.
5,675,361 A 10/1997 Santilli
5,675,362 A 10/1997 Clough et al.
5,677,710 A 10/1997 Thompson-Rohrlich
5,680,160 A 10/1997 LaPointe
5,686,705 A 11/1997 Conroy et al.
5,689,253 A 11/1997 Hargreaves et al.
5,710,844 A 1/1998 Capps et al.
5,717,777 A 2/1998 Wong et al.
5,729,249 A 3/1998 Yasutake
5,729,250 A 3/1998 Bishop et al.
5,730,165 A 3/1998 Philipp
5,732,227 A 3/1998 Kuzunuki et al.
5,732,230 A 3/1998 Cullen et al.
5,734,742 A 3/1998 Asaeda et al.
5,734,751 A 3/1998 Saito
5,736,976 A * 4/1998 Cheung 345/168
5,741,990 A 4/1998 Davies
5,745,116 A 4/1998 Pisutha-Amond
5,745,591 A 4/1998 Feldman
5,745,716 A 4/1998 Tchao et al.
5,746,818 A 5/1998 Yatake
5,748,184 A 5/1998 Shieh
5,748,269 A 5/1998 Harris et al.
5,751,851 A 5/1998 Guzik et al.
5,757,478 A 5/1998 Ma
5,764,218 A 6/1998 Bona et al.
5,764,222 A 6/1998 Shieh
5,767,457 A 6/1998 Gerpheide et al.
5,767,842 A * 6/1998 Korth 345/168
5,771,342 A 6/1998 Todd
5,790,104 A 8/1998 Shieh
5,790,107 A 8/1998 Kasser et al.
5,796,389 A 8/1998 Bertram et al.
5,797,396 A 8/1998 Geiser et al.
5,801,681 A 9/1998 Sayag
5,802,516 A 9/1998 Shwarts et al.
5,805,137 A 9/1998 Yasutake
5,805,144 A 9/1998 Scholder et al.
5,805,157 A 9/1998 Bertram et al.
5,808,567 A 9/1998 McCloud
5,808,605 A 9/1998 Shieh
5,809,166 A 9/1998 Huang et al.
5,809,267 A 9/1998 Moran et al.
5,812,118 A 9/1998 Shieh
5,812,698 A 9/1998 Platt et al.
5,821,597 A 10/1998 Nakajima et al.
5,821,690 A 10/1998 Martens et al.
5,821,922 A 10/1998 Sellers
5,821,930 A * 10/1998 Hansen 715/702
5,823,782 A 10/1998 Marcus et al.
5,825,351 A 10/1998 Tam
5,825,352 A 10/1998 Bisset et al.
5,825,675 A 10/1998 Want et al.
5,831,602 A 11/1998 Sato et al.
5,835,079 A 11/1998 Shieh
5,837,947 A 11/1998 Teterwak
5,838,302 A 11/1998 Kuriyama et al.
5,852,434 A 12/1998 Sekendur
5,852,669 A 12/1998 Eleftheriadis et al.
5,854,450 A 12/1998 Kent
5,854,625 A 12/1998 Frisch et al.
5,856,822 A 1/1999 Du et al.
5,856,824 A 1/1999 Shieh
5,862,256 A 1/1999 Zetts et al.
5,864,296 A 1/1999 Upton
5,870,083 A 2/1999 Shieh
5,870,771 A 2/1999 Oberg
5,872,559 A 2/1999 Shieh
5,874,948 A 2/1999 Shieh
5,877,748 A 3/1999 Redlich
5,880,411 A 3/1999 Gillespie et al.
5,883,619 A 3/1999 Ho et al.
5,886,697 A 3/1999 Naughton et al.
5,887,080 A 3/1999 Tsubusaki et al.
5,896,126 A 4/1999 Shieh
5,898,422 A 4/1999 Zetts
5,898,434 A 4/1999 Small et al.
5,905,476 A 5/1999 McLaughlin et al.
5,917,476 A 6/1999 Czerniecki
5,920,309 A 7/1999 Bisset et al.
5,923,319 A 7/1999 Bishop et al.
5,933,134 A 8/1999 Shieh
5,936,615 A 8/1999 Waters
5,940,065 A 8/1999 Babb et al.
5,942,733 A 8/1999 Allen et al.
5,943,043 A 8/1999 Furuhata et al.
5,943,044 A 8/1999 Martinelli et al.
5,945,980 A 8/1999 Moissev et al.
5,956,019 A 9/1999 Bang et al.
5,956,020 A * 9/1999 D'Amico et al. 345/173
5,956,682 A 9/1999 Loudermilk et al.
5,963,190 A 10/1999 Tsuboyama et al.
5,973,676 A 10/1999 Kawakura
5,982,302 A * 11/1999 Ure 341/22
5,982,352 A 11/1999 Pryor
5,987,162 A 11/1999 Nakata
5,990,804 A 11/1999 Koyama
5,990,893 A 11/1999 Numazaki
5,995,081 A 11/1999 Kato
5,995,106 A 11/1999 Naughton et al.
5,995,663 A 11/1999 Itsuzaki et al.
6,002,389 A 12/1999 Kasser
6,002,808 A 12/1999 Freeman
6,005,959 A 12/1999 Mohan et al.
6,005,963 A 12/1999 Bolle et al.
6,008,800 A 12/1999 Pryor
6,016,355 A 1/2000 Dickinson et al.
6,020,878 A 2/2000 Robinson
6,020,881 A 2/2000 Naughton et al.
6,023,313 A 2/2000 Hazama
6,029,214 A 2/2000 Dorfman et al.
6,031,524 A 2/2000 Kunert
6,037,882 A 3/2000 Levy
6,040,824 A 3/2000 Maekawa et al.
6,049,329 A 4/2000 Zetts et al.
6,050,825 A 4/2000 Nichol et al.
6,052,339 A 4/2000 Frenkel et al.
6,061,177 A 5/2000 Fujimoto
6,067,079 A 5/2000 Shieh
6,072,494 A 6/2000 Nguyen
6,075,520 A 6/2000 Inoue et al.
6,084,576 A 7/2000 Leu et al.
6,088,023 A 7/2000 Louis et al.
6,097,371 A 8/2000 Siddiqui et al.
6,107,997 A 8/2000 Ure
6,124,845 A 9/2000 Toda et al.
6,128,003 A 10/2000 Smith et al.
6,131,299 A 10/2000 Raab et al.
6,135,958 A 10/2000 Mikula-Curtis et al.
6,141,463 A 10/2000 Covell et al.
6,144,380 A 11/2000 Shwarts et al.
6,147,680 A 11/2000 Tareev
6,154,209 A 11/2000 Naughton et al.
6,160,551 A 12/2000 Naughton et al.
6,175,644 B1 1/2001 Scola
6,184,926 B1 2/2001 Khosravi et al.
6,188,391 B1 2/2001 Seely et al.
6,198,515 B1 3/2001 Cole

(56) **References Cited**

U.S. PATENT DOCUMENTS

6,204,839 B1 3/2001 Mato, Jr.
6,208,329 B1 3/2001 Ballare
6,222,465 B1 4/2001 Kumar et al.
6,222,508 B1 4/2001 Alvelda et al.
6,239,389 B1 5/2001 Allen et al.
6,239,790 B1 5/2001 Martinelli et al.
6,243,071 B1 6/2001 Shwarts et al.
6,246,395 B1 6/2001 Goyins
6,246,862 B1 6/2001 Grivas et al.
6,249,606 B1 6/2001 Kiraly et al.
6,255,604 B1 7/2001 Tokioka et al.
6,271,860 B1 8/2001 Gross
6,278,443 B1 8/2001 Amro et al.
6,279,170 B1 8/2001 Chu
6,283,858 B1 9/2001 Hayes et al.
6,288,707 B1 9/2001 Philipp
6,289,326 B1 9/2001 LaFleur
6,292,178 B1 9/2001 Bernstein et al.
6,295,052 B1 9/2001 Kato et al.
6,310,610 B1 10/2001 Beaton et al.
6,310,964 B1 10/2001 Mohan et al.
6,323,846 B1 11/2001 Westerman et al.
6,337,681 B1 1/2002 Martin
6,340,979 B1 1/2002 Beaton et al.
6,344,861 B1 2/2002 Naughton et al.
6,347,290 B1 2/2002 Bartlett
6,377,009 B1 4/2002 Philipp
6,380,929 B1 4/2002 Platt
6,380,931 B1 4/2002 Gillespie et al.
6,392,636 B1 5/2002 Ferrari et al.
6,411,287 B1 6/2002 Scharff et al.
6,414,671 B1 7/2002 Gillespie et al.
6,421,234 B1 7/2002 Ricks et al.
6,445,384 B1 9/2002 Atwood et al.
6,452,514 B1 9/2002 Philipp
6,457,355 B1 10/2002 Philipp
6,466,036 B1 10/2002 Philipp
6,515,669 B1 2/2003 Mohri
6,525,749 B1 2/2003 Moran et al.
6,535,200 B2 3/2003 Philipp
6,543,684 B1 4/2003 White et al.
6,543,947 B2 4/2003 Lee
6,567,549 B1 5/2003 Marianetti et al.
6,570,557 B1 5/2003 Westerman et al.
6,593,916 B1 7/2003 Aroyan
6,610,936 B2 8/2003 Gillespie et al.
6,624,833 B1 9/2003 Kumar et al.
6,639,577 B2 10/2003 Eberhard
6,650,319 B1 11/2003 Hurst et al.
6,658,994 B1 12/2003 McMillan
6,670,894 B2 12/2003 Mehring
6,677,932 B1 1/2004 Westerman
6,677,934 B1 1/2004 Blanchard
6,690,387 B2 2/2004 Zimmerman et al.
6,724,366 B2 4/2004 Crawford
6,738,154 B1 5/2004 Venable
6,757,002 B1 6/2004 Oross et al.
6,803,906 B1 10/2004 Morrison et al.
6,842,672 B1 1/2005 Straub et al.
6,856,259 B1 2/2005 Sharp
6,888,536 B2 5/2005 Westerman et al.
6,900,795 B1 5/2005 Knight, III et al.
6,927,761 B2 8/2005 Badaye et al.
6,942,571 B1 9/2005 McAllister et al.
6,965,375 B1 11/2005 Gettemy et al.
6,972,401 B2 12/2005 Akitt et al.
6,977,666 B1 12/2005 Hedrick
6,985,801 B1 1/2006 Straub et al.
6,992,659 B2 1/2006 Gettemy
7,015,894 B2 3/2006 Morohoshi
7,031,228 B2 4/2006 Born et al.
7,038,659 B2 5/2006 Rajkowski
7,084,859 B1 8/2006 Pryor
7,129,416 B1 10/2006 Steinfeld et al.
7,138,983 B2 11/2006 Wakai et al.
7,184,064 B2 2/2007 Zimmerman et al.
7,240,289 B2 7/2007 Naughton et al.
RE40,153 E 3/2008 Westerman et al.
7,339,580 B2 3/2008 Westerman et al.
7,663,607 B2 2/2010 Hotelling et al.
7,764,274 B2 7/2010 Westerman et al.
7,812,828 B2 10/2010 Westerman et al.
7,920,129 B2 4/2011 Hotelling et al.
8,314,775 B2 11/2012 Westerman et al.
8,330,727 B2 12/2012 Westerman et al.
8,334,846 B2 12/2012 Westerman et al.
8,384,675 B2 2/2013 Westerman et al.
8,441,453 B2 5/2013 Westerman et al.
8,466,880 B2 6/2013 Westerman et al.
8,466,881 B2 6/2013 Westerman et al.
8,466,883 B2 6/2013 Westerman et al.
8,479,122 B2 7/2013 Hotelling et al.
8,482,533 B2 7/2013 Westerman et al.
8,514,183 B2 8/2013 Westerman et al.
8,576,177 B2 11/2013 Westerman et al.
8,629,840 B2 1/2014 Westerman et al.
8,633,898 B2 1/2014 Westerman et al.
8,665,240 B2 3/2014 Westerman
8,674,943 B2 3/2014 Westerman et al.
8,698,755 B2 4/2014 Westerman et al.
8,730,177 B2 5/2014 Westerman et al.
8,730,192 B2 5/2014 Westerman et al.
8,736,555 B2 5/2014 Westerman et al.
8,866,752 B2 10/2014 Westerman et al.
8,902,175 B2 12/2014 Westerman et al.
9,001,068 B2 4/2015 Westerman et al.
9,098,142 B2 8/2015 Westerman et al.
2001/0030637 A1 10/2001 Geisow et al.
2002/0008711 A1 1/2002 Karjalainen
2002/0036618 A1 3/2002 Wakai et al.
2002/0118848 A1 8/2002 Karpenstein
2002/0140668 A1 10/2002 Crawford
2003/0006974 A1 1/2003 Clough et al.
2003/0067451 A1 4/2003 Tagg et al.
2003/0076301 A1 4/2003 Tsuk et al.
2003/0076303 A1 4/2003 Huppi
2003/0076306 A1 4/2003 Zadesky et al.
2003/0095095 A1 5/2003 Pihlaja
2003/0095096 A1 5/2003 Robbin et al.
2003/0098858 A1 5/2003 Perski et al.
2003/0132950 A1 7/2003 Surucu et al.
2003/0164820 A1 9/2003 Kent
2003/0206202 A1 11/2003 Moriya
2003/0234768 A1 12/2003 Rekimoto et al.
2004/0146688 A1 7/2004 Treat
2004/0263484 A1 12/2004 Mantysalo et al.
2005/0012723 A1 1/2005 Pallakoff
2005/0052425 A1 3/2005 Zadeski et al.
2005/0104867 A1 5/2005 Westerman et al.
2005/0110768 A1 5/2005 Marriott et al.
2006/0022955 A1 2/2006 Kennedy
2006/0022956 A1 2/2006 Lengeling et al.
2006/0026521 A1 2/2006 Hotelling et al.
2006/0026535 A1 2/2006 Hotelling et al.
2006/0026536 A1 2/2006 Hotelling et al.
2006/0032680 A1 2/2006 Elias et al.
2006/0033724 A1 2/2006 Chaudhri et al.
2006/0053387 A1 3/2006 Ording
2006/0066582 A1 3/2006 Lyon et al.
2006/0085757 A1 4/2006 Andre et al.
2006/0097991 A1 5/2006 Hotelling et al.
2006/0197753 A1 9/2006 Hotelling
2006/0232567 A1 10/2006 Westerman et al.
2006/0238517 A1 10/2006 King et al.
2006/0238518 A1 10/2006 Westerman et al.
2006/0238519 A1 10/2006 Westerman et al.
2006/0238520 A1 10/2006 Westerman et al.
2006/0238521 A1 10/2006 Westerman et al.
2006/0238522 A1 10/2006 Westerman et al.
2007/0070050 A1 3/2007 Westerman et al.
2007/0070051 A1 3/2007 Westerman et al.
2007/0070052 A1 3/2007 Westerman et al.
2007/0078919 A1 4/2007 Westerman et al.
2007/0081726 A1 4/2007 Westerman et al.

(56) **References Cited**

U.S. PATENT DOCUMENTS

2007/0139395	A1	6/2007	Westerman et al.
2007/0229464	A1	10/2007	Hotelling et al.
2007/0236466	A1	10/2007	Hotelling
2007/0247429	A1	10/2007	Westerman
2007/0257890	A1	11/2007	Hotelling et al.
2007/0268273	A1	11/2007	Westerman et al.
2007/0268274	A1	11/2007	Westerman et al.
2007/0268275	A1	11/2007	Westerman et al.
2008/0041639	A1	2/2008	Westerman et al.
2008/0042986	A1	2/2008	Westerman et al.
2008/0042987	A1	2/2008	Westerman et al.
2008/0042988	A1	2/2008	Westerman et al.
2008/0042989	A1	2/2008	Westerman et al.
2008/0128182	A1	6/2008	Westerman et al.
2009/0021489	A1	1/2009	Westerman et al.
2009/0160816	A1	6/2009	Westerman et al.
2009/0244031	A1	10/2009	Westerman et al.
2009/0244032	A1	10/2009	Westerman et al.
2009/0244033	A1	10/2009	Westerman et al.
2009/0249236	A1	10/2009	Westerman et al.
2009/0251435	A1	10/2009	Westerman et al.
2009/0251438	A1	10/2009	Westerman et al.
2009/0251439	A1	10/2009	Westerman et al.
2010/0149092	A1	6/2010	Westerman et al.
2010/0149134	A1	6/2010	Westerman et al.
2012/0293442	A1	11/2012	Westerman et al.
2013/0147761	A1	6/2013	Westerman et al.
2013/0265263	A1	10/2013	Westerman et al.
2014/0160068	A1	6/2014	Westerman et al.
2014/0176499	A1	6/2014	Westerman et al.

FOREIGN PATENT DOCUMENTS

DE	19612949	C1	8/1997
DE	10251296	A1	5/2004
EP	0 397 428	A2	11/1990
EP	0 464 908		1/1992
EP	0 495 595	A2	7/1992
EP	0 546 704	A2	6/1993
EP	0 546 704	A3	6/1993
EP	0 288 692		7/1993
EP	0 622 722		11/1994
EP	0 664 504		1/1995
EP	0 770 971	A2	5/1997
EP	0 770 971	A3	5/1997
EP	0 773 496	A1	5/1997
EP	0 782 090	A2	7/1997
EP	0 782 090	A3	7/1997
EP	0 817 000		1/1998
EP	1 014 295		1/2002
GB	2330670	A	4/1999
JP	59-149537	A	8/1984
JP	64-009488	A	1/1989
JP	01-100622	A	4/1989
JP	02-056017	A	2/1990
JP	02-304613	A	12/1990
JP	03-071219	A	3/1991
JP	03-269717	A	12/1991
JP	04-233619	A	8/1992
JP	06-083523	A	3/1994
JP	06-161661	A	6/1994
JP	06-332620	A	12/1994
JP	07-057103	A	3/1995
JP	07-110741	A	4/1995
JP	07-129312	A	5/1995
JP	07-160428	A	6/1995
JP	07-182101	A	7/1995
JP	7-230352	A	8/1995
JP	07-325655	A	12/1995
JP	08-076926	A	3/1996
JP	08-137608	A	5/1996
JP	08-286830	A	11/1996
JP	09-237175	A	9/1997
JP	2000-163031	A	6/2000
JP	2002-342033	A	11/2002
WO	WO-92/02000		2/1992
WO	WO-94/18664	A1	8/1994
WO	WO-96/07981	A1	3/1996
WO	WO-96/15464	A1	5/1996
WO	WO-97/18547		5/1997
WO	WO-97/23738		7/1997
WO	WO-97/34273	A1	9/1997
WO	WO-97/36225		10/1997
WO	WO-97/40744		11/1997
WO	WO-98/14863		4/1998
WO	WO-99/38149		7/1999
WO	WO-03/088176		10/2003
WO	WO-2006/023569		3/2006

OTHER PUBLICATIONS

Notice of Allowance mailed Mar. 27, 2015, for U.S. Appl. No. 14/089,240, filed Nov. 25, 2013, eight pages.

"4-Wire Resistive Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-4resistive.html generated Aug. 5, 2005.

"5-Wire Resistive Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-resistive.html generated Aug. 5, 2005.

"A Brief Overview of Gesture Recognition" obtained from http://www.dai.ed.ac.uk/Cvonline/LOCA_COPIES/COHEN/gesture_overview.html, generated Apr. 20, 2004.

"Capacitive Position Sensing" obtained from http://www.synaptics.com/technology/cps.cfm generated Aug. 5, 2005.

"Capacitive Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-capacitive.html generated Aug. 5, 2005.

"Comparing Touch Technologies" obtained from http://www.touchscreens.com/intro-touchtypes.html generated Oct. 10, 2004.

"FingerWorks—Gesture Guide—Application Switching," obtained from http://www.fingerworks.com/gesture_guide_apps.html, generated on Aug. 27, 2004, 1-pg.

"FingerWorks—Gesture Guide—Editing," obtained from http://www.fingerworks.com/gesure_guide_editing.html, generated on Aug. 27, 2004, 1-pg.

"FingerWorks—Gesture Guide—File Operations," obtained from http://www.fingerworks.com/gesture_guide_files.html, generated on Aug. 27, 2004, 1-pg.

"FingerWorks—Gesture Guide—Text Manipulation," obtained from http://www.fingerworks.com/gesture_guide_text_manip.html, generated on Aug. 27, 2004, 2-pg.

"FingerWorks—Gesture Guide—Tips and Tricks," obtained from http://www.fingerworks.com/gesture_guide_tips.html, generated Aug. 27, 2004, 2-pgs.

"FingerWorks—Gesture Guide—Web," obtained from http://www.fingerworks.com/gesture_guide_web.html, generated on Aug. 27, 2004, 1-pg.

"FingerWorks—Guide to Hand Gestures for USB Touchpads," obtained from http://www.fingerworks.com/igesture_userguide.html, generated Aug. 27, 2004, 1-pg.

"FingerWorks—iGesture—Technical Details," obtained from http://www.fingerworks.com/igesture_tech.html, generated Aug. 27, 2004, 1-pg.

"FingerWorks—The Only Touchpads with Ergonomic Full-Hand Resting and Relaxation!" obtained from http://www.fingerworks.com/resting.html, Copyright 2001, 1-pg.

"FingerWorks—Tips for Typing on the Mini," obtained from http://www.fingerworks.com/mini_typing.html, generated on Aug. 27, 2004, 2-pgs.

"Gesture Recognition," (2006). Located at http://www.fingerworks.com/gesture_recognition.html>, last visited Jul. 25, 2006, two pages.

"GlidePointe®" obtained from http://www.cirque.com/technology/technology_gp.html generated Aug. 5, 2005.

"How do touchscreen monitors know where you're touching?" obtained from http://www.electronics.howstuffworks.com/question716.html generated Aug. 5, 2005.

"How does a touchscreen work?" obtained from http://www.touchscreens.com/intro-anatomy.html generated Aug. 5, 2005.

(56) **References Cited**

OTHER PUBLICATIONS

"iGesture Pad—the MultiFinger USB TouchPad with Whole-Hand Gestures," obtained from http://www.fingerworks.com/igesture.html, generated Aug. 27, 2004, 2-pgs.
"iGesture Products for Everyone (learn in minutes) Product Overview," (2005). Located at <http://www.fingerworks.com/>, last visited Aug. 30, 2005, six pages.
"Infrared Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-infrared.html generated Aug. 5, 2005.
"Mouse Emulation" FingerWorks obtained from http://www.fingerworks.com/gesture_guide_mouse.html generated Aug. 30, 2005.
"Mouse Gestures in Opera" obtained from http://www.opera.com/products/desktop/mouse/index.dml generated Aug. 30, 2005.
"Mouse Gestures," Optim oz, May 21, 2004.
"MultiTouch Overview" FingerWorks obtained from http://www.fingerworks.com/multoverview.html generated Aug. 30, 2005.
"Near Field Imaging Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-nfi.html generated Aug. 5, 2005.
"PenTouch Capacitive Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-pentouch.html generated Aug. 5, 2005.
"Surface Acoustic Wave Touchscreens" obtained from http://www.touchscreens.com/intro-touchtypes-saw.html generated Aug. 5, 2005.
"Symbol Commander" obtained from http://www.sensiva.com/symbolcomander/, generated Aug. 30, 2005.
"Tips for Typing" FingerWorks http://www.fingerworks.com/mini_typing.html generated Aug. 30, 2005.
"Touch Technologies Overview" 2001, 3M Touch Systems, Massachusetts.
"Wacom Components—Technology" obtained from http://www.wacom-components.com/english/tech.asp generated on Oct. 10, 2004.
"Watershed Algorithm" http://rsb.info.nih.gov/ij/plugins/watershed.html generated Aug. 5, 2005.
Adams, H.G. et al. (Jul. 1985). "Automated Radiographic Report Generation Using Barcode Technology," *American Journal of Roentgenology* 145(1):177-180.
Agrawal, R. et al. (Jul. 1986). "An Overview of Tactile Sensing," Center for Research on Integrated Manufacturing: Robot Systems Division, The University of Michigan, 47 pages.
Anonymous. (1989). "Concorde Version 3.0: Turns a PC into a Graphics Workstation," News and Views: *Tektronix, Inc. Bioinformatics*, 5(1):63-75.
Anonymous. (May 8, 1992). "The Sensor Frame Graphic Manipulator," *NASA Phase II Final Report*, 28 pages.
Bier, et al., "Toolglass and Magic Lenses: The see-through interface" In James Kijiya, editor, Computer Graphics (SIGGRAPH '93 Proceedings), vol. 27, pp. 73-80, Aug. 1993.
Bolle, R.M. et al. (1996) "Veggie Vision: A Produce Recognition System," *IEEE*, pp. 244-251.
Brown, E. et al. (1990). "Windows on Tablets as a Means of Achieving Vitrual Input Devices," *Interact* '90, pp. 675-681.
Buxton, W. (1986). "There's More to Interaction Than Meets the Eye: Some Issues in Manual Input," *User Centered System Design, New Perspectives on Human-Computer Interaction*, pp. 319-337.
Buxton, W. et al. (Jul. 22, 1985). "Issues and Techniques in Touch-Sensitive Tablet Input," *Proceedings ACM Siggraph*, pp. 215-224.
Buxton, W. et al. (1986). "A Study in Two-Handed Input," *Proceedings of CHI '86*, pp. 321-326.
Buxton, W.A.S. (Mar./Apr. 1994). "Two-Handed Document Navigation," *Xerox Disclosure Journal* 19(2):103-108.
Chang, C-C. et al. (Aug. 1, 1993). "A Hashing-Oriented Nearest Neighbor Searching Scheme," Pattern Recognition Letters, 14(8):625-630.
Charlebois, M. et al. (1996). "Curvature Based Shape Estimation Using Tactile Sensing," *Proceedings 1996 IEEE International Conference on Robotics and Automation*, six pages.
Charlebois, M.A. (Dec. 1996). "Exploring the Shape of Objects with Curved Surfaces Using Tactile Sensing," A Thesis Submitted in Partial Fulfillment of the Requirements for the Degree of Master of Applied Science, Simon Fraser University, Burnaby, British Columbia, Canada, 108 pages.
Colosi, J. ed. (Dec. 15, 1984). Computer News, *Hewlett-Packard* 10(4):1-27.
Crowley, J.L. (Mar. 1, 1997). "Vision for Man-Machine Interaction," Robotics and Autonomous Systems, 19(3-4):347-358.
Cui, Y. et al. (1996). "Hand Segmentation Using Learning-Based Prediction and Verification for Hand Sign Recognition," *Proceedings of the 1996 IEEE Computer Society Conference on Computer Vision and Pattern Recognition*, pp. 88-93.
Cutler, L.D. et al. (Apr. 27, 1997). "Two-Handed Direct Manipulation on the Responsive Workbench," *Proceedings of the 1997 Symposium on Interactive 3D Graphics*, Providence, RI, Apr. 27-30, 1997, pp. 107-114.
Dario, P. et al. (1986). "A Sensorised Scenario for Basic Investigation on Active Touch," in *International Trends in Manufacturing Technology:Robot Sensors vol. 2—Tactile and Non-Vision*, Pugh, A. ed., IFS Publications: UK, pp. 237-245.
Davies, E.R. (Aug. 1987). "Lateral Histograms for Efficient Object Location: Speed versus Ambiguity," *Pattern Recognition Letters* 6(3):189-198.
Davies, E.R. (1990). *Machine Vision: Theory, Algorithms, Practicalities*, Academic Press, Inc.: San Diego, CA, pp. xi-xxi (Table of Contents Only.).
Davies, E.R. (1997). "Boundary Pattern Analysis," Chapter 7 in *Machine Vision: Theory Algorithms Practicalities*, 2nd Edition, Academic Press, Inc.: San Diego, CA, pp. 171-191.
Davies, E.R. (1997). "Ellipse Detection," Chapter 11 in *Machine Vision: Theory Algorithms Practicalities*, 2nd Edition, Academic Press, Inc.: San Diego, CA, pp. 271-290.
Davies, E.R. (1997). "Image Acquisition," Chapter 23 in *Machine Vision: Theory Algorithms Practicalities*, 2nd Edition, Academic Press, Inc.: San Diego, CA, pp. 583-601.
Davies, E.R. (1997). *Machine Vision: Theory, Algorithms, Practicalities*, Second Edition, Academic Press, Inc.: San Diego, CA, pp. vii-xx (Table of Contents Only).
Davis, J. et al. (May 2, 1994). "Recognizing Hand Gestures," *European Conference on Computer Vision*, Stockholm, SE, 1:331-340.
Davis, J. et al. (Oct. 31, 1994). "Determining 3-D Hand Motion," *Signals, Systems and Computers, 1994 Conference Record of the 28th Asilomar Conference on Pacific Grove*, CA , Oct. 31-Nov. 2, 1994, Los Alamitos, CA, pp. 1262-1266.
Desai, A. et al. (1994). "On the Localization of Objects Using an FSR Pressure Pad Transducer," *IEEE* pp. 953-957.
Desai, A.M. (Nov. 1994). "Interpretation of Tactile Data From an FSR Pressure Pad Transducer Using Image Processing Techniques," A Thesis Submitted in Partial Fulfillment of the Requirements for the Degree of Master of Applied Science, Simon Fraser University, Burnaby, British Columbia, Canada, 157 pages.
Douglas et al., The Ergonomics of Computer Pointing Devices (1997).
European examination report for European Patent Application No. 06016830.9, mailed Aug. 6, 2008.
European examination report for European Patent Application No. 06016856.4 mailed Sep. 16, 2008.
European examination report for European patent Application No. 99904228.6, mailed Apr. 20, 2006.
European examination report for European Patent Application No. 99904228.6, mailed Mar. 23, 2007.
European search report for European Patent Application No. 06016830.9 mailed Dec. 3, 2007.
European Search Report mailed Dec. 12, 2008, for EP Application No. 06016855.6 filed Jan. 25, 1999, six pages.
European Search Report mailed Dec. 23, 2008, for EP Application No. 06016831.7 filed Jan. 25, 1999, eight pages.
European Search Report mailed Jan. 9, 2009, for EP Application No. 06016832.5 filed Jan. 25, 1999, four pages.
European Search Report mailed Feb. 17, 2010, for EP Application No. 06016857.2, six pages.

(56) **References Cited**

OTHER PUBLICATIONS

European Search Report mailed Feb. 24, 2010, for EP Application No. 06016833.3, nine pages.
European Search Report mailed Nov. 15, 2011, for EP Patent Application No. 10010057.7, filed Jan. 25, 1999, six pages.
European Search Report mailed Nov. 15, 2011, for EP Patent Application No. 10010058.5, filed Jan. 25, 1999, six pages.
European Search Report mailed Dec. 5, 2011, for EP Patent Application No. 10010056.9, filed Jan. 25, 1999, eight pages.
European Search Report received in EP 1 621 989 (@ *Beyer Weaver & Thomas, LLP*) dated Mar. 27, 2006.
European supplementary search report for European Patent Application No. 99904228.6, mailed Feb. 16, 2005.
EVB Elektronik "TSOP6238 IR Receiver Modules for Infrared Remote Control Systems" dated Jan. 2004 1-pg.
Everett, H.R. (1995). *Sensors for Mobile Robots: Theory and Application*, AK Peters, Ltd.: Wellesley, MA, pp. v-x (Table of Contents Only.).
Extended European search report for European Patent Application No. 06016858.0, mailed Dec. 21, 2007.
Extended European search report for European Patent Application No. 06016856.4, mailed Mar. 14, 2008.
Fearing, R.S. (Dec. 1987). "Tactile Sensing, Perception and Shape Interpretation," Thesis (Ph.D.) Stanford University, Department of Electrical Engineering.
Fearing, R.S. (Jun. 1990). "Tactile Sensing Mechanisms," *The International Journal of Robotics Research* 9(3):3-23.
Final Office Action mailed Mar. 19, 2009, for U.S. Appl. No. 11/428,506, filed Jul. 3, 2006, seven pages.
Final Office Action mailed Nov. 19, 2009, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, 14 pages.
Final Office Action mailed Apr. 14, 2010, for U.S. Appl. No. 11/559,736, filed Nov. 14, 2006, 11 pages.
Final Office Action mailed May 12, 2010, for U.S. Appl. No. 11/428,503, filed Jul. 3, 2006, 12 pages.
Final Office Action mailed Jun. 11, 2010, for U.S. Appl. No. 11/559,833, filed Nov. 14, 2006, eight pages.
Final Office Action mailed Jul. 19, 2010, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, seven pages.
Final Office Action mailed Oct. 19, 2010, for U.S. Appl. No. 11/559,799, filed Nov. 14, 2006, eight pages.
Final Office Action mailed Oct. 29, 2010, for U.S. Appl. No. 11/559,763, filed Nov. 14, 2006, 15 pages.
Final Office Action mailed Nov. 23, 2010, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, 13 pages.
Final Office Action mailed Nov. 26, 2010, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, nine pages.
Final Office Action mailed Dec. 2, 2010, for U.S. Appl. No. 11/830,815, filed Jul. 30, 2007, nine pages.
Final Office Action mailed Dec. 3, 2010, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, 15 pages.
Final Office Action mailed Apr. 21, 2011, for U.S. Appl. No. 11/830,808, filed Jul. 30, 2007, 10 pages.
Final Office Action mailed Sep. 27, 2011, for U.S. Appl. No. 11/830,774, filed Jul. 30, 2007, 15 pages.
Final Office Action mailed Sep. 28, 2011, for U.S. Appl. No. 12/479,678, filed Jun. 5, 2009, 13 pages.
Final Office Action mailed Oct. 14, 2011, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, 16 pages.
Final Office Action mailed Oct. 19, 2011, for U.S. Appl. No. 12/479,573, filed Jun. 5, 2009, 13 pages.
Final Office Action mailed Nov. 17, 2011, for U.S. Appl. No. 11/830,781, filed Jul. 30, 2007, 16 pages.
Final Office Action mailed Nov. 17, 2011, for U.S. Appl. No. 12/479,617, filed Jun. 5, 2009, 18 pages.
Final Office Action mailed Dec. 16, 2011, for U.S. Appl. No. 12/422,212, filed Apr. 10, 2009, 20 pages.
Final Office Action mailed Feb. 3, 2012, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 16 pages.
Final Office Action mailed Feb. 17, 2012, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, 14 pages.
Final Office Action mailed Mar. 1, 2012, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, 14 pages.
Final Office Action mailed Apr. 16, 2012, for U.S. Appl. No. 12/422,222, filed Apr. 10, 2009, 14 pages.
Final Office Action mailed Apr. 25, 2012, for U.S. Appl. No. 12/422,197, filed Apr. 10, 2009, 12 pages.
Final Office Action mailed Apr. 27, 2012, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, 13 pages.
Final Office Action mailed May 1, 2012, for U.S. Appl. No. 12/434,439, filed May 1, 2009, 14 pages.
Final Office Action mailed May 8, 2012, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, seven pages.
Final Office Action mailed May 24, 2012, for U.S. Appl. No. 11/830,757, filed Jul. 30, 2007, 19 pages.
Final Office Action mailed Jun. 8, 2012, for U.S. Appl. No. 12/422,225, filed Apr. 10, 2009, 12 pages.
Final Office Action mailed Jul. 6, 2012, for U.S. Appl. No. 11/830,815, filed Jul. 30, 2007, 15 pages.
Final Office Action mailed Jan. 29, 2013, for U.S. Appl. No. 11/830,766, filed Jul. 30, 2007, 16 pages.
Final Office Action mailed Jan. 29, 2013, for U.S. Appl. No. 11/830,774, filed Jul. 30, 2007, 19 pages.
Final Office Action mailed Feb. 15, 2013, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 16 pages.
Final Office Action mailed Mar. 21, 2013, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, 12 pages.
Final Office Action mailed Apr. 12, 2013, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, 15 pages.
Final Office Action mailed Apr. 30, 2013, for U.S. Appl. No. 11/559,833, filed Nov. 14, 2006, 10 pages.
Final Office Action mailed May 9, 2013, for U.S. Appl. No. 13/569,065, filed Aug. 7, 2012, nine pages.
Final Office Action mailed Jul. 11, 2013, for U.S. Appl. No. 13/757,726, filed Feb. 1, 2013, nine pages.
Final Office Action mailed Sep. 12, 2013, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, seven pages.
Final Office Action mailed Oct. 11, 2013, for U.S. Appl. No. 12/422,222, filed Apr. 10, 2009, 16 pages.
Final Office Action mailed Feb. 21, 2014, for U.S. Appl. No. 12/422,197, filed Apr. 10, 2009, 14 pages.
Final Office Action mailed Mar. 21, 2014, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, eight pages.
Fisher et al., "Repetitive Motion Disorders: The Design of Optimal Rate-Rest Profiles," Human Factors, 35(2):283-304 (Jun. 1993).
Fitzgibbon, A. et al. (Jan. 4, 1996). "Direct Least Square Fitting of Ellipses," *IEEE Transactions on Pattern Analysis and Machine Intelligence* 21(5):1-15.
Fukumoto and Yoshinobu Tonomura, "Body Coupled Fingering: Wireless Wearable Keyboard," *CHI 97*, pp. 147-154 (Mar. 1997).
Fukumoto, et al., "ActiveClick: Tactile Feedback for Touch Panels," In CHI 2001 Summary, pp. 121-122, 2001.
Geman, S. et al. (Nov. 1984). "Stochastic Relaxation, Gibbs Distributions, and The Bayesian Restoration of Images," *IEEE Transactions on Pattern Analysis and Machine Intelligence* 6(6):721-741.
Ghani, N. (Oct. 1988). "Visual and Tactile Senses in Collaboration," *Sensor Review: The International Journal of Sensing for Industry* 8(4):210-215.
Golub, G. et al. (1983). "Measuring Vectors, Matrices, Subspaces, and Linear System Sensitivty," Chapter 2 in *Matrix Computation*, Johns Hopkins University Press: Baltimore, MD, pp. 10-30.
Goodisman, A. (May 10, 1991). "A Stylus-Based User Interface for Text: Entry and Editing," Thesis (B.S./M.S.) MIT Department of Electrical Engineering and Computer Science, pp. 1-100.
Hackwood, S. et al. (1986). "Torque-Sensitive Tactile Array for Robotics," *in International Trends in Manufacturing Technology:Robot Sensors vol. 2—Tactile and Non-Vision*, Pugh, A. ed., IFS Publications: UK, pp. 123-131.
Hardy, "Fingerworks" Mar. 7, 2002; BBC World on Line.
Harmon, L.D. (Summer 1982). "Automated Tactile Sensing," *The International Journal of Robotics Research* 1(2):3-32.

(56) **References Cited**

OTHER PUBLICATIONS

Heap, T. et al. (Oct. 14, 1996). "Towards 3D Hand Tracking Using a Deformable Model," *Proceedings of the 2nd International Conference*, Killington, VT, USA, Oct. 14-16, 1996, *Automatic Face and Gesture Recognition, IEEE Comput. Soc.*, pp. 140-145.
Helander, M. ed. (1988). *Handbook of Human-Computer Interaction*, pp. i-xxxiii. (Table of Contents Only.).
Hillier and Gerald J. Lieberman, *Introduction to Operations Research* (1986).
Ho, C-T., et al. (1995). "A Fast Ellipse/Circle Detector Using Geometric Symmetry," *Pattern Recognition* 28(1):117-124.
Holland, S. (Jul. 1989). "Artificial Intelligence, Education and Music: The Use of Artificial Intelligence to Encourage and Facilitate Music Composition by Novices," CITE Report No. 88, *Centre for Information Technology in Education*, 309 pages.
Hurst, M.P. (Jul. 1995). "Configurator: A Configuration Program for Satellite Dish Hardware," Thesis (M.S.) MIT Department of Electrical Engineering and Computer Science, pp. 1-74.
International search report for PCT/US99/01454, mailed May 14, 1999.
International Search Report mailed Dec. 28, 2005, for PCT Application No. PCT/US05/03325, filed Feb. 3, 2005, two pages.
International Search Report received in corresponding PCT application No. PCT/US2006/008349 dated Oct. 6, 2006.
Jacob et al., "Integrality and Separability of Input Devices," *ACM Transactions on Computer-Human Interaction*, 1:3-26 (Mar. 1994).
Jayawant, B.V. et al. (1986). "Robot Tactile Sensing: A New Array Sensor," in *International Trends in Manufacturing Technology:Robot Sensors vol. 2—Tactile and Non-Vision* , Pugh, A. ed., IFS Publications: UK, pp. 199-205.
Kahn, R.E. et al. (Mar. 1988). "An Open Architecture for a Digital Library System and a Plan for Its Development," in The Digital Library Project: The World of Knowbots, Corporation for National Research Initiatives, 1:1-48.
Kinkley et al., "Touch-Sensing Input Devices," in CHI '99 Proceedings, pp. 223-230, 1999.
Kionx "KXP84 Series Summary Data Sheet" copyright 2005, dated Oct. 21, 2005, 4-pgs.
Kirk, D.E. (1970). "Numerical Determination of Optimal Trajectories," Chapter 6 in *Optimal Control Theory: An Introduction*, Prentice Hall, Inc.: Englewood Cliffs, NY. pp. 329-413, with Table of Contents, pp. vii-ix. (90 pages total).
Kjeldsen, F.C.M. (1997). "Visual Interpretation of Hand Gestures as a Practical Interface Modality," Thesis (Ph.D.) Columbia University, Graduate School of Arts, pp. 1-198.
Konrad, J. (1980). "Bayesian Estimation of Motion Fields from Image Sequences," Thesis, McGill University, Department of Electrical Engineering, pp. 1-237.
Krein, P. et al. (May/Jun. 1990). "The Electroquasistatics of the Capacitive Touch Panel," *IEEE Transactions on Industry Applications* 26(3):529-534.
Krueger, M. et al. (Jun. 10, 1988). "Videoplace, Responsive Environment, 1972-1990," located at http://www.youtube.com/watch?v=dmmxVA5xhuo, last visited Aug. 5, 2011, two pages.
Kurtenbach, G.P. (1983). "The Design and Evaluation of Marking Menus," A Thesis Submitted in Conformity with the Requirements of the Degree of Doctor of Philosophy, University of Toronto, Toronto, Canada, 201 pages.
Lee et al., "A Multi-Touch Three Dimensional Touch-Sensitive Tablet," in CHI '85 Proceedings, pp. 121-128, 2000.
Lee, "A Fast Multiple-Touch-Sensitive Input Device," Master's Thesis, University of Toronto (1984).
Lee, S.K. et al. (Apr. 1985). "A Multi-Touch Three Dimensional Touch-Sensitive Tablet," *Proceedings of CHI: ACM Conference on Human Factors in Computing Systems*, pp. 21-25.
Leonard, J.J. et al. (Jun. 1991). "Mobile Robot Localization by Tracking Geometric Beacons," *IEEE Transaction on Robotics and Automation* 7(3):376-382.
Leung, A. et al. (1994). "Application of Adaptive Neural Network to Localization of Objects Using Pressure Array Transducer," *IEEE* pp. 2114-2119.
Liu, H. et al. (Jun. 1993). "Development of a New Kind of Robot Slipping Sensor," *Proceedings of the 1993 American Control Conference*, Jun. 2-4, 1993, San Francisco, CA, pp. 756-757.
Matsushita et al., "HoloWall: Designing a Finger, Hand, Body and Object Sensitive Wall," in Proceedings of UIST '97, Oct. 1997.
Mehta, N. (Oct. 1982). "A Flexible Human Macine Interface," A Thesis Submitted in Conformity with the Requirements for the Degree of Master of Applied Science in the University of Toronto, 81 pages.
Miller, D. et al. (Feb./Mar. 1994). "Combined Source-Channel Vector Quantization Using Deterministic Annealing," *IEEE Transactions on Communications* 42(2/3/4):347-356.
Moghaddam, B. et al. (Jul. 1997). "Probabilistic Visual Learning for Object Representation," *IEEE Transactions on Pattern Analysis and Machine Intelligence* 19(7):696-710.
Moroney, D.T. (Mar. 1992). "Use of an Optical Multichannel Analyzer for Reflectivity Measurements," Submitted in Partial Fulfillment of the Requirements for the Degree of Master of Science in Astronautical Engineering, Naval Postgraduate School, Monterrey, CA, 187 pages.
Mui, L. (Jan. 29, 1996). "A Statistical Multi-Experts Approach to Image Classification and Segmentation," Thesis (B.S./M.Eng.) MIT Department of Electrical Engineering and Computer Science, pp. 1-177.
Nicholls, H.R. et al. (Jun. 1989). "A Survey of Robot Tactile Sensing Technology," *The International Journal of Robotics Research* 8(3):3-30.
Nirei, K. et al. (Aug. 5, 1996). "Human Hand Tracking from Binocular Image Sequences," *Proceedings of the 1996 IEEE IECON 22nd International Conference*, Taipei, Taiwan, Aug. 5-10, 1996, *Industrial Electronics, Control, and Instrumentation* 1(5):297-302.
Non-Final Office Action mailed Sep. 24, 2007, for U.S. Appl. No. 11/428,506, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Sep. 21, 2007, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, seven pages.
Non-Final Office Action mailed Sep. 24, 2007, for U.S. Appl. No. 11/428,521, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Jan. 28, 2008, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, seven pages.
Non-Final Office Action mailed Feb. 4, 2008, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Jul. 9, 2008, for U.S. Appl. No. 11/428,521, filed Jul. 3, 2006, 11 pages.
Non-Final Office Action mailed Sep. 2, 2008, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Sep. 15, 2008, for U.S. Appl. No. 11/428,506, filed Jul. 3, 2006, eight pages.
Non-Final Office Action mailed Oct. 31, 2008, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, seven pages.
Non-Final Office Action mailed Feb. 17, 2009, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Mar. 18, 2009, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, 12 pages.
Non-Final Office Action mailed Apr. 2, 2009, for U.S. Appl. No. 11/428,501, filed Jul. 3, 2006, 11 pages.
Non-Final Office Action mailed Apr. 2, 2009, for U.S. Appl. No. 11/428,503, filed Jul. 3, 2006, 12 pages.
Non-Final Office Action mailed Aug. 25, 2009, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Sep. 2, 2009, for U.S. Appl. No. 11/559,736, filed Nov. 14, 2006, 12 pages.
Non-Final Office Action mailed Oct. 5, 2009, for U.S. Appl. No. 11/559,799, filed Nov. 14, 2006, 14 pages.
Non-Final Office Action mailed Oct. 6, 2009, for U.S. Appl. No. 11/559,763, filed Nov. 14, 2006, 24 pages.
Non-Final Office Action mailed Oct. 14, 2009, for U.S. Appl. No. 11/428,501, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Oct. 29, 2009, for U.S. Appl. No. 11/559,822, filed Nov. 14, 2006, 11 pages.

(56) **References Cited**

OTHER PUBLICATIONS

Non-Final Office Action mailed Oct. 30, 2009, for U.S. Appl. No. 11/428,503, filed Jul. 3, 2006, nine pages.
Non-Final Office Action mailed Dec. 22, 2009, for U.S. Appl. 11/559,833, filed Nov. 14, 2006, six pages.
Non-Final Office Action mailed Dec. 24, 2009, for U.S. Appl. No. 11/677,958, filed Feb. 22, 2007, six pages.
Non-Final Office Action mailed Jan. 27, 2010, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, five pages.
Non-Final Office Action mailed May 11, 2010, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, eight pages.
Non-Final Office Action mailed Jun. 8, 2010, for U.S. Appl. No. 11/830,808, filed Jul. 30, 2007, 13 pages.
Non-Final Office Action mailed Jun. 9, 2010, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, eight pages.
Non-Final Office Action mailed Jun. 10, 2010, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, 10 pages.
Non-Final Office Action mailed Jun. 22, 2010, for U.S. Appl. No. 11/830,815, filed Jul. 30, 2007, 12 pages.
Non-Final Office Action mailed Nov. 23, 2010, for U.S. Appl. No. 11/830,808, filed Jul. 30, 2007, 11 pages.
Non-Final Office Action mailed Jan. 20, 2011, for U.S Appl. No. 11/830,757, filed Jul. 30, 2007, 21 pages.
Non-Final Office Action mailed Feb. 17, 2011, for U.S. Appl. No. 11/830,766, filed Jul. 30, 2007, 20 pages.
Non-Final Office Action mailed Mar. 18, 2011, for U.S. Appl. No. 11/830,774, filed Jul. 30, 2007, 18 pages.
Non-Final Office Action mailed Mar. 21, 2011, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, 11 pages.
Non-Final Office Action mailed Mar. 31, 2011, for U.S. Appl. No. 12/479,573, filed Jun. 5, 2009, 17 pages.
Non-Final Office Action mailed Mar. 31, 2011, for U.S. Appl. No. 12/479,617, filed Jun. 5, 2009, 20 pages.
Non-Final Office Action mailed Mar. 31, 2011, for Appl. No. 12/479,678, filed Jun. 5, 2009, 18 pages.
Non-Final Office Action mailed Apr. 21, 2011, for U.S. Appl. No. 11/559,763, filed Nov. 14, 2006, seven pages.
Non-Final Office Action mailed Apr. 28, 2011, for U.S. Appl. No. 11/830,781, filed Jul. 30, 2007, 16 pages.
Non-Final Office Action mailed Jun. 28, 2011, for U.S. Appl. No. 12/422,197, filed Apr. 10, 2009, 18 pages.
Non-Final Office Action mailed Jun. 28, 2011, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 13 pages.
Non-Final Office Action mailed Jun. 28, 2011, for U.S. Appl. No. 12/422,212, filed Apr. 10, 2009, 16 pages.
Non-Final Office Action mailed Jun. 29, 2011, for U.S. Appl. No. 12/342,027, filed Dec. 22, 2008, 32 pages.
Non-Final Office Action mailed Jul. 20, 2011, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, 12 pages.
Non-Final Office Action mailed Aug. 4, 2011, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, 13 pages.
Non-Final Office Action mailed Aug. 5, 2011, for U.S. Appl. No. 12/422,222, filed Apr. 10, 2009, 15 pages.
Non-Final Office Action mailed Aug. 5, 2011, for U.S. Appl. No. 12/422,225, filed Apr. 10, 2009, 17 pages.
Non-Final Office Action mailed Sep. 1, 2011, for U.S. Appl. No. 11/830,766, filed Jul. 30, 2007, 29 pages.
Non-Final Office Action mailed Sep. 16, 2011, for U.S. Appl. No. 11/830,757, filed Jul. 30, 2007, 26 pages.
Non-Final Office Action mailed Oct. 14, 2011, for U.S. Appl. No. 12/434,439, filed May 1, 2009, nine pages.
Non-Final Office Action mailed Oct. 27, 2011, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, six pages.
Non-Final Office Action mailed Nov. 10, 2011, for U.S. Appl. No. 11/830,815, filed Jul. 30, 2007, 15 pages.
Non-Final Office Action mailed Nov. 23, 2011, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, eight pages.
Non-Final Office Action mailed Jan. 19, 2012, for U.S. Appl. No. 11/830,808, filed Jul. 30, 2007, eight pages.
Non-Final Office Action mailed Jan. 30, 2012, for U.S. Appl. No. 11/428,503, filed Jul. 3, 2006, 15 pages.
Non-Final Office Action mailed Apr. 5, 2012, for U.S. Appl. No. 12/479,678, filed Jun. 5, 2009, 13 pages.
Non-Final Office Action mailed Apr. 16, 2012, 2011, for U.S. Appl. No. 12/422,212, filed Apr. 10, 2009, 20 pages.
Non-Final Office Action mailed May 23, 2012, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, 15 pages.
Non-Final Office Action mailed Jun. 7, 2012, for U.S. Appl. No. 11/830,766, filed Jul. 30, 2007, 14 pages.
Non-Final Office Action mailed Jun. 22, 2012, for U.S. Appl. No. 11/830,774, filed Jul. 30, 2007, 17 pages.
Non-Final Office Action mailed Jun. 25, 2012, for U.S. Appl. No. 11/830,781, filed Jul. 30, 2007, 19 pages.
Non-Final Office Action mailed Jun. 25, 2012, for U.S. Appl. No. 12/479,573, filed Jun. 5, 2009, 11 pages.
Non-Final Office Action mailed Aug. 30, 2012, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, 15 pages.
Non-Final Office Action mailed Sep. 4, 2012, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, 13 pages.
Non-Final Office Action mailed Sep. 6, 2012, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, 14 pages.
Non-Final Office Action mailed Sep. 13, 2012, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 16 pages.
Non-Final Office Action mailed Sep. 25, 2012, for U.S. Appl. No. 11/428,515, filed Jul. 3, 2006, 15 pages.
Non-Final Office Action mailed Oct. 12, 2012, for U.S. Appl. No. 12/422,212, filed Apr. 10, 2009, five pages.
Non-Final Office Action mailed Nov. 8, 2012, for U.S. Appl. No. 12/479,678, filed Jun. 5, 2009, five pages.
Non-Final Office Action mailed Nov. 16, 2012, for U.S. Appl. No. 13/569,065, filed Aug. 7, 2012, eight pages.
Non-Final Office Action mailed Nov. 29, 2012, for U.S. Appl. No. 11/559,833, filed Nov. 14, 2006, 10 pages.
Non-Final Office Action mailed Jan. 4, 2013, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, six pages.
Non-Final Office Action mailed Feb. 21, 2013, for U.S. Appl. No. 12/422,197, filed Apr. 10, 2009, 12 pages.
Non-Final Office Action mailed Mar. 18, 2013, for U.S. Appl. No. 12/422,222, filed Apr. 10, 2009, 15 pages.
Non-Final Office Action mailed Mar. 26, 2013, for U.S. Appl. No. 13/757,726, filed Feb. 1, 2013, eight pages.
Non-Final Office Action mailed Jun. 21, 2013, for U.S. Appl. No. 11/830,774, filed Jul. 30, 2007, 18 pages.
Non-Final Office Action mailed Jul. 18, 2013, for U.S. Appl. No. 11/830,766, filed Jul. 30, 2007, 15 pages.
Non-Final Office Action mailed Aug. 16, 2013, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, 16 pages.
Non-Final Office Action mailed Sep. 12, 2013, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Sep. 13, 2013, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 17 pages.
Non-Final Office Action mailed Sep. 19, 2013, for U.S. Appl. No. 13/895,221, filed May 15, 2013, 15 pages.
Non-Final Office Action mailed Oct. 11, 2013, for U.S. Appl. No. 12/422,197, filed Apr. 10, 2009, 12 pages.
Non-Final Office Action mailed Nov. 25, 2013, for U.S. Appl. No. 13/569,065, filed Aug. 7, 2012, six pages.
Non-Final Office Action mailed Feb. 13, 2014, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, seven pages.
Non-Final Office Action mailed Apr. 10, 2014, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 21 pages.
Non-Final Office Action mailed Jun. 12, 2014, for U.S. Appl. No. 14/089,240, filed Nov. 25, 2013, 11 pages.
Notice of Allowability mailed Feb. 11, 2009, for U.S. Appl. No. 11/428,521, filed Jul. 3, 2006, five pages.
Notice of Allowability mailed Jul. 10, 2009, for U.S. Appl. No. 11/428,521, filed Jul. 3, 2006, four pages.
Notice of Allowability mailed Sep. 2, 2009, for U.S. Appl. No. 11/428,506, filed Jul. 3, 2006, five pages.
Notice of Allowance mailed Apr. 26, 2010, for U.S. Appl. No. 11/559,822, filed Nov. 14, 2006, nine pages.

(56) **References Cited**

OTHER PUBLICATIONS

Notice of Allowability (Supplemental) mailed May 12, 2010, for U.S. Appl. No. 11/559,822, filed Nov. 14, 2006, two pages.
Notice of Allowance mailed Jun. 21, 2010, for U.S. Appl. No. 11/677,958, filed Feb. 22, 2007, eight pages.
Notice of Allowance mailed Aug. 16, 2011, for U.S. Appl. No. 11/559,763, filed Nov. 14, 2006, nine pages.
Notice of Allowance mailed Oct. 26, 2011, for U.S. Appl. No. 11/559,763, filed Nov. 14, 2006, nine pages.
Notice of Allowance mailed Apr. 13, 2012, for U.S. Appl. No. 12/342,027, filed Dec. 22, 2008, 10 pages.
Notice of Allowance mailed Jun. 27, 2012, for U.S. Appl. No. 11/559,736, filed Nov. 14, 2006, 11 pages.
Notice of Allowance mailed Jul. 26, 2012, for U.S.No. 11/428,503, filed Jul. 3, 2006, nine pages.
Notice of Allowance mailed Jan. 15, 2013, for U.S. Appl. No. 12/479,617, filed Jun. 5, 2009, 10 pages.
Notice of Allowance mailed Feb. 8, 2013, for U.S. Appl. No. 11/830,801, filed Jul. 30, 2007, seven pages.
Notice of Allowance mailed Feb. 15, 2013, for U.S. Appl. No. 11/559,799, filed Nov. 14, 2006, 13 pages.
Notice of Allowance mailed Feb. 19, 2013, for U.S. Appl. No. 12/422,212, filed Apr. 10, 2009, nine pages.
Notice of Allowance mailed Feb. 21, 2013, for U.S. Appl. No. 12/342,027, filed Dec. 22, 2008, 10 pages.
Notice of Allowance mailed Mar. 5, 2013, for U.S. Appl. No. 12/434,439, filed May 1, 2009, nine pages.
Notice of Allowance mailed Apr. 2, 2013, for U.S. Appl. No. 12/479,678, filed Jun. 5, 2009, 11 pages.
Notice of Allowance mailed Aug. 21, 2013, for U.S. Appl. No. 13/757,726, filed Feb. 1, 2013, six pages.
Notice of Allowance mailed Sep. 17, 2013, for U.S. Appl. No. 11/830,757, filed Jul. 30, 2007, 10 pages.
Notice of Allowance mailed Oct. 8, 2013, for U.S. Appl. No. 11/830,774, filed Jul. 30, 2007, 11 pages.
Notice of Allowance mailed Oct. 17, 2013, for U.S. Appl. No. 11/559,833, filed Nov. 14, 2006, 12 pages.
Notice of Allowance mailed Nov. 1, 2013, for U.S. Appl. No. 13/895,221, filed May 15, 2013, 12 pages.
Notice of Allowance mailed Jan. 2, 2014, for U.S. Appl. No. 11/830,766, filed Jul. 30, 2007, 10 pages.
Notice of Allowance mailed Jan. 6, 2014, for U.S. Appl. No. 11/830,788, filed Jul. 30, 2007, 13 pages.
Notice of Allowance mailed Jan. 6, 2014, for U.S. Appl. No. 11/830,793, filed Jul. 30, 2007, 12 pages.
Notice of Allowance mailed Jan. 10, 2014, for U.S. Appl. No. 13/569,065, filed Aug. 7, 2012, eight pages.
Notice of Allowance mailed Mar. 14, 2014, for U.S. Appl. No. 12/422,222, filed Apr. 10, 2009, nine pages.
Notice of Allowance mailed Aug. 4, 2014, for U.S. Appl. No. 12/422,197, filed Apr. 10, 2009, 10 pages.
Notice of Allowance mailed Jun. 9, 2014, for U.S. Appl. No. 14/163,929, filed Jan. 24, 2014, seven pages.
Nowlin, W.C. (Apr. 1991). "Experimental Results on Bayesian Algorithms for Interpreting Compliant Tactile Sensing Data," *Proceedings of the 1991 IEEE International Conference on Robotics and Automation*, Sacramento, CA, pp. 378-383.
Ogawa, H. et al. (1979). "Preprocssing for Chinese Character Recognition and Global Clsssification of Handwritten Chinese Characters," *Pattern Recognition* 11:1-7.
Pavlovic, V.I. et al. (Jul. 1997). "Visual Interpretation of Hand Gestures for Human-Computer Interaction: A Review," *IEEE Transactions on Pattern Analysis and Machine Intelligence* 19(7):677-695.
Poggio, T. et al. (1990). "The MIT Vision Machine," Chapter 42 *in Artificial Intelligence*, MIT Press: Cambridge, MA, pp. 493-529.
Potter, R.L. (1993). "Improving the Accuracy of Touchscreens: An Experimental Evaluation of Three Strategies," Chapter 4.1 in *Sparks of Innovation in Human-Computer Interaction*, Shneiderman, B., Ed., Ablex Publications: Norwood, N.J., pp. 157-167.
Pugh, A. ed. (1986). *International Trends in Manufacturing Technology: Robot Sensors vol. 2—Tactile and Non-Vision*, 3 pages (Table of Contents Only).
Quantum Research Group "QT510 / QWheel™ Touch Slider IC" copyright 2004-2005, 14-pgs.
Quantum Research Group Ltd.(1997). QT9701B2 Datasheet, 30 pages.
Quek, F.K.H. (Dec. 1, 1996). "Unencumbered Gestural Interaction," *IEEE Multimedia*, 3(4):36-47.
Radwin, "Activation Force and Travel Effects on Overexertion in Repetitive Key Tapping," *Human Factors*, 39(1):130-140 (Mar. 1997).
Rebman, J. et al. (1986). "A Tactile Sensor with Electrooptical Transduction," in *International Trends in Manufacturing Technology:Robot Sensors vol. 2—Tactile and Non-Vision*, Pugh, A. ed., IFS Publications: UK, pp. 145-155.
Rekimoto "SmartSkin: An Infrastructure for Freehand Manipulation on Interactive Surfaces" CHI 2002, Apr. 20-25, 2002.
Rekimoto et al., "ToolStone: Effective Use of the Physical Manipulation Vocabularies of Input Devices," In Proc. of UIST 2000.
Robertson, B.E. et al. (1986). "Tactile Sensor System for Robotics," in *International Trends in Manufacturing Technology: Robot Sensors vol. 2—Tactile and Non-Vision*, Pugh, A. ed., IFS Publications: UK, pp. 89-97.
Rubine et al., "Programmable Finger-Tracking Instrument Controllers," *Computer Music Journal*, vol. 14, No. 1 (Spring 1990).
Rubine, D. (Jul. 1991). "Specifying Gestures by Example," *ACM SIGGRAPH Computer Graphics* 25(4):329-337.
Rubine, D. (May 1992). "Combining Gestures and Direct Manipulation," CHI '92, pp. 659-660.
Rubine, D. et al. (1988). "The VideoHarp," *Proceedings of the 14th International Computer Music Conference*, Cologne, W. Germany, Sep. 20-25, 1988, pp. 49-55.
Rubine, D.H. (Dec. 1991). "The Automatic Recognition of Gestures," CMU-CS-91-202, Submitted in Partial Fulfillment of the Requirements of the Degree of Doctor of Philosophy in Computer Science at Carnegie Mellon University, 285 pages.
Rusaw, S. et al. (May 1998). "Determining Polygon Orientation Using Model Based Force Interpretation," *Proceedings of the 1998 IEEE International Conference on Robotics and Automation*, Leuven, Belgium, pp. 544-549.
Rutledge et al., "Force-To-Motion Functions for Pointing," Human-Computer Interaction—Interact (1990).
Sato, N. et al. (1986). "A Method for Three-Dimensional Part Identification by Tactile Transducer," in *International Trends in Manufacturing Technology: Robot Sensors vol. 2—Tactile and Non-Vision*, Pugh, A. ed., IFS Publications: UK, pp. 133-143.
Sears, A. et al. (Jan. 23, 1989). "High Precision Touchscreens: Design Strategies and Comparisons With a Mouse," Human-Computer Interaction Laboratory, University of MD, pp. 1-23.
Sethi, M. (1997). "Generating Clouds in Computer Graphics," A Thesis Submitted in Partial Fulfillment of the Requirements for the Degree of M.Sc. in Computer Science, 154 pgs.
Siegel, D.M. et al. (1987). "Performance Analysis of a Tactile Sensor," *IEEE*, pp. 1493-1499.
Simigian, S. et al. (1989). "Image: Modified for Use on a Microcomputer-Based System," *Computers & Geosciences* 15(3):237-254.
Son, J.S. et al. (1996). "Comparison of Contact Sensor Localization Abilities During Manipulation," *Robotics and Autonomous System 17* pp. 217-233.
Speeter, T.H. (Nov. 1988). "Flexible, Piezoresitive Touch Sensing Array," Optics Illumination and Imaging Sensing for Machine Vision III, *SPIE* 1005:31-43.
Stansfield, S.A. (Mar. 1990). "Haptic Perception With an Articulated, Sensate Robot Hand," *SANDIA Report*: SAND90—0085—UC-406, 37 pages.
Stap, J.W. (Jun. 29, 1992). "Automatic 3-D Measurement of Workpieces on a Ship Repair Yard," M.Sc. Thesis, 132 pages.
Stauffer, R.N. ed. (Jun. 1983). "Progress in Tactile Sensor Development," *Robotics Today* pp. 43-49.
Subatai Ahmad, "A Usable Real-Time 3D Hand Tracker," Proceedings of the 28th Asilomar Conference on Signals, Systems and Computers—Part 2 (of2), vol. 2 (Oct. 1994).

(56) **References Cited**

OTHER PUBLICATIONS

Sugiyama, S. et al. (Mar. 1990). "Tactile Image Detection Using a 1k-element Silicon Pressure Sensor Array," *Sensors and Actuators* A21-A23 (1-3):397-400.
Sun Microsystems. (1992). "The Star7 PDA Prototype," located at <http://www.youtube.com/watch?v=Ahg8OBYixL0, last visited Jan. 15, 2010, seven pages.
Supplementary European search report for U.S. patent Application No. 99904228.6, mailed Jul. 8, 2005.
Texas Instruments "TSC2003 / I2C Touch Screen Controller" Data Sheet SBAS 162, dated Oct. 2001, 20-pgs.
Tomita, A. Jr. et al. (Nov. 9, 1997). "An Image Processing Method for Use in a GUI for the Visually Impaired," *Proceedings of the IECON '97: 23rd International Conference on Industrial Electronics, Control and Instrumentation*, New Orleans, LA, Nov. 9-14, 1997, pp. 264-268.
U.S. Appl. No. 10/654,108, filed Sep. 2, 2003 entitled "Ambidextrous Mouse."
U.S. Appl. No. 10/789,676, filed Feb. 27, 2004 entitled "Shape Detecting Input Device."
U.S. Appl. No. 11/332,861, filed Jan. 13, 2006 which is a Reissue of 6,677,932 listed above.
Van Brussel, H. et al. (Jun. 1986). "A High Resolution Tactile Sensor for Part Recognition," *Proceedings of the 6th International Conference on Robot Vision and Sensory Controls*, Paris, France, Jun. 3-5, 1986, pp. 49-59.
Velasco, V.B. Jr. (Aug. 1997). "A Methodology for Computer-Assisted Gripper Customization Using Rapid Prototyping Technology," Thesis Submitted in Partial Fulfillment of the Requirements for the Degree of Ph.D., 199 pages.
Want, R. et al. (Mar. 1995). "The ParcTab Ubiquitous Computing Experiment," Technical Report CSL-95-1, *Xerox*, 44 pages.
Wellner, "The Digital Desk Calculators: Tangible Manipulation on a Desk Top Display" in ACM UIST '91 Proceedings, pp. 27-34, Nov. 1991.
Westerman, W. (Jan. 1, 1999). "Hand Tracking, Finger Identification, and Chordic Manipulation on a Multi-Touch Surface," Dissertation, University of Delaware, pp. 1-333.
Williams, "Applications for a Switched-Capacitor Instrumentation Building Block" Linear Technology Application Note 3, Jul. 1985, pp. 1-16.
Wolfeld, J.A. (Aug. 1981). "Real Time Control of a Robot Tactile Sensor," Thesis Presented in Partial Fulfillment of the Requirements for the Degree of Master of Science in Engineering for Graduate Work in Computer and Information Science, 68 pages.
Yamada et al., "A Switched-Capacitor Interface for Capacitive Pressure Sensors" IEEE Transactions on Instrumentation and Measurement, vol. 41, No. 1, Feb. 1992, pp. 81-86.
Yaniger, S.L. (Apr. 1991). "Force Sensing Resisotrs: A Review of the Technology," *Elector International Conference Record*, Apr. 16-18, 1991, New York, NY pp. 666-668.
Yeh et al., "Switched Capacitor Interface Circuit for Capacitive Transducers" 1985 IEEE.
Yuen, H. K. et al. (Feb. 1, 1989). "Detecting Partially Occluded Ellipses Using the Hough Transform," *Image and Vision Computing* 7(1): 31-37.
Zhai et al., "Dual Stream Input for Pointing and Scrolling," *Proceedings of CHI '97 Extended Abstracts* (1997).
Zimmerman et al., "Applying Electric Field Sensing to Human-Computer Interfaces," In CHI '85 Proceedings, pp. 280-287, 1995.
Final Office Action mailed Sep. 19, 2014, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, seven pages.
Final Office Action mailed Sep. 24, 2014, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 17 pages.
Non-Final Office Action mailed Jun. 2, 2015, for U.S. Appl. No. 11/428,522, filed Jul. 3, 2006, six pages.
Non-Final Office Action mailed Sep. 17, 2015, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 16 pages.
Final Office Action mailed Dec. 3, 2014, for U.S. Appl. No. 14/089,240, filed Nov. 25, 2013, 12 pages.
Non-Final Office Action mailed Dec. 4, 2014, for U.S. Appl. No. 12/422,205, filed Apr. 10, 2009, 16 pages.
Non-Final Office Action mailed Oct. 8, 2015, for U.S. Appl. No. 12/139,411, filed Jun. 13, 2008, seven pages.
Non-Final Office Action mailed Dec. 3, 2015, for U.S. Appl. No. 11/830,781, filed Jul. 30, 2007, 18 pages.

* cited by examiner


4
2
ELECTRODE SCANNING HARDWARE
6
CALIBRATION AND PROXIMITY IMAGE FORMATION
8
CONTACT TRACKING AND IDENTIFICATION
10
12
TYPING RECOGNIZER
14
FINGER SYNCHRONIZATION DETECTOR
HAND MOTION COMPONENT EXTRACTION
16
PENGRIP DETECTOR
17
CHORD MOTION RECOGNIZER
18
22
24
DISPLAY
HOST COMPUTER SYSTEM
HOST COMMUNICATION INTERFACE
20

FIG. 1



FIG. 2


38
32
33
39
40
46
45
58
34
V
48
30
31
41

FIG. 3A


38
32
33
69
39
46
45
58
34
V
48
30
31
41

FIG. 3B



FIG. 4A



FIG. 4B



FIG. 5A



FIG. 5B


58
35
37
36
55
45
51
44h
44g
44f
44e
44d
44c
44b
44a
47
46
43h
43g
43f
43e
43d
43c
43b
43a
50
34
V

FIG. 6


58
70
M
63
8
61
65
66
60
K
69
68
64

FIG. 7A


71
S
58a-h
N
62
67
65
66
70
M
63
8
61
60
K
69
68
64

FIG. 7B


58h
58g
58f
58e
58d
58c
58b
58a
35
37
36
55
45h
45g
45f
45e
45d
45c
45b
45a
44h
44g
44f
44e
44d
44c
44b
44a
81
47
78
77
75
76
46
43
34

FIG. 8



FIG. 9A



FIG. 9B



FIG. 10



FIG. 11



FIG. 12


VERTICAL POSITION ON SURFACE (Y AXIS cm)
HORIZONTAL POSITION ON SURFACE (X AXIS cm)
14
12
10
8
6
4
2
0
-2
-4
-6
0
2
4
6
8
10
12
14
16
18
201
202
203
204
205
206
207
208
208
209

FIG. 13


VERTICAL POSITION ON SURFACE (Y AXIS cm)
14
12
10
8
6
4
2
0
-2
-4
-6
0
2
4
6
8
10
12
14
16
18
HORIZONTAL POSITION ON SURFACE (X AXIS cm)
202
203
204
205
201
210
210
210
207
206
210

FIG. 14


VERTICAL POSITION ON SURFACE (Y AXIS cm)
14
12
10
8
6
4
2
0
-2
-4
-6
0
2
4
6
8
10
12
14
16
18
HORIZONTAL POSITION ON SURFACE (X AXIS cm)
201
202
203
204
205
206
207

FIG. 15


CURRENT PROXIMITY IMAGE
240
IMAGE SEGMENTATION
241
PATHS FROM PREVIOUS IMAGES
243
PARAMETERIZED ELECTRODE GROUPS
242
CONTACT PATH TRACKING
245
NEW PATHS & UPDATED PATH PARAMETERS
246
HAND IDENTIFICATION
247
FINGER & PALM IDENTIFICATION
248
IDENTIFIED CONTACT PATHS
250
HAND POSITION ESTIMATION
251
ESTIMATED HAND & FINGER OFFSETS
252

FIG. 16


START
GET HAND'S IDENTIFIED PATHS
250
COMPUTE OFFSETS BETWEEN EACH FINGER'S MEASURED AND DEFAULT POSITIONS
254
COMPUTE AVERAGE OF OFFSETS WEIGHTED BY CONTACT PROXIMITY
255
ADJUST FILTER POLE TO CURRENT IDENTIFICATION CONFIDENCE
256
COMPUTE WEIGHTED AVERAGE OF HAND CONTACT VELOCITIES
257
AUTOREGRESSIVELY UPDATE HAND OFFSET ESTIMATES FROM MEASURED OFFSETS AND VELOCITIES
258
UPDATE FINGER OFFSET ESTIMATES
259
CONVERT ESTIMATED OFFSETS TO ABSOLUTE POSITIONS
260
END

FIG. 17


CURRENT PROXIMITY IMAGE
240
DIFFUSE CURRENT IMAGE
262
SMOOTHED PROXIMITY IMAGE
263
SEARCH FOR SIGNIFICANT LOCAL MAXIMA
264
LOCAL MAXIMUM PIXELS
265
FLATTENED FINGERTIP FEEDBACK
267
ESTIMATED HAND POSITION OFFSETS
252
DEFINE SEGMENTATION STRICTNESS REGIONS
266
CONSTRUCT ELECTRODE GROUPS AROUND LOCAL MAXIMUM PIXELS
268
COMBINE OVERLAPPING GROUPS
270
FIT ELLIPSES TO COMBINED GROUPS
272
PARAMETERIZED ELECTRODE GROUPS
242

FIG. 18



FIG. 19



FIG. 20A



FIG. 20B



FIG. 20C


START
300
GET NEXT ELECTRODE IN DIRECTION OF SEARCH
A
290
RAW PROXIMITY > BACKGROUND?
N
REACHED BACKGROUND LEVEL EDGE
END
304
Y
A
N
292
IN STRICT SEGMENTATION REGION?
Y
306
SEARCHING HORIZONTAL ?
N
VERTICAL MINIMUM ?
N
Y
310
Y
294
SEARCHING HORIZONTAL ?
N
REACHED EDGE BETWEEN FINGERTIP AND THUMB OR PALM
312
Y
END
296
HORIZ. DIST. TO LOCAL MAX > 2cm ?
N
308
HORIZ. OR DIAGONAL MINIMUM ?
Y
Y
N
298
TALL HORIZONTAL MINIMUM ?
N
REACHED EDGE BETWEEN FINGERS
314
Y
A
END
REACHED EDGE BETWEEN PALM HEELS
300
END

FIG. 21


START
PREDICT CURRENT POSITIONS OF EXISTING PATHS
320
FOR EACH GROUP FIND CLOSEST PATH
322
FOR EACH PATH, FIND CLOSEST GROUP WITHIN TRACKING RADIUS
324
FORM GROUP-PATH PAIRS IF GROUP & ACTIVE PATH ARE CLOSEST TO ONE ANOTHER
326
ATTEMPT TO PAIR REMAINING GROUPS WITH RECENTLY DEACTIVATED PATHS
334
ALLOCATE NEW PATHS FOR ANY REMAINING UNPAIRED GROUPS
336
DEACTIVATE ANY REMAINING UNPAIRED PATHS
344
UPDATE PATH PARAMETERS
346
END

FIG. 22


START
DEFINE IDENTITY ATTRACTORS AT DEFAULT CONTACT POSITIONS
350
TRANSLATE ATTRACTOR TEMPLATE BY ESTIMATED HAND OFFSET
352
COMPUTE MATRIX OF DISTANCES FROM EACH PATH TO EACH ATTRACTOR
354
COMPUTE ATTRACTOR WEIGHTING FACTORS FROM FEATURES OF EACH PATH
356
FIND ASSIGNMENT BETWEEN PATHS AND ATTRACTORS WHICH MINIMIZES SUM OF WEIGHTED DISTANCES
358
HAND ASSIGNMENTS TENTATIVE ?
360
N
Y
FINGER ATTRACTORS ASSIGNED > 1 OR < 5 ?
362
Y
N
VERIFY THUMB ASSIGNMENT
368
UPDATE FINGER COUNTS AND SUBSETS
364
END

FIG. 23


VERTICAL SURFACE POSITION (cm)
HORIZONTAL SURFACE POSITION (cm)
12
10
8
6
4
2
0
-2
-4
-6
0
2
4
6
8
10
12
14
16
18
20
380
373
374
372
375
380
371
380
380
380
377
376

FIG. 24



FIG. 25A



FIG. 25B



FIG. 25C



FIG. 25D


START
COMPUTE INTER-PATH THUMB FACTORS
400
COMBINE WITH THUMB SIZE & ORIENTATION FACTORS OF INNERMOST AND NEXT INNERMOST CONTACT
402
404
combined_thumb_fact > is_thumb_thresh?
N
Y
412
INNERMOST ASSIGNED TO THUMB?
N
Y
406
combined_thumb_fact < not_thumb_thresh?
N
Y
SHIFT INNERMOST PATH TO THUMB ATTRACTOR
414
408
INNERMOST ASSIGNED TO THUMB?
N
Y
413
EXISTING ASSIGNMENTS OK
SHIFT INNERMOST PATHS AWAY FROM THUMB ATTRACTOR
410
END

FIG. 26


START
GET ALL PATHS ASSIGNED TO THE GIVEN HAND
430
COMPUTE DISTANCES FROM EACH PATH TO OTHER PATHS
432
FIND SHORTEST RING CONNECTING ALL PATHS AND PASSING THROUGH EACH ONCE
434
COMPUTE THUMB & PALM WEIGHTING FACTORS FOR EACH PATH
436
PICK INNERMOST PATH IN RING
438
440
INNERMOST PATH THUMB ?
N
Y
442
INNERMOST PATH A PALM HEEL?
N
Y
PATHS ABOVE THIS VERTICAL LEVEL ARE FINGERTIPS, BELOW ARE PALMS
444
446
PATHS AT THIS VERTICAL LEVEL ARE PALMS
448
PATHS AT THIS VERTICAL LEVEL ARE FINGERTIPS
END

FIG. 27


START
485
INNER & OUTER HAND PARTS TOUCHING ?
N
Y
486
PENGRIP PREVIOUSLY DETECTED ?
N
END
Y
GET ESTIMATED FINGER & PALM POSITIONS FOR LIFTED HAND PARTS
487
GET MEASURED POSITIONS & SIZES OF TOUCHING FINGERS & PALM HEELS
488
COMPUTE KNUCKLE FACTOR FOR OUTER FINGERS
489
COMPUTE INDEX JUTTING FACTOR FOR INNER FINGERS
490
COMBINE FACTORS & FILTER WITH OLD COMBINED FACTORS
491
492
FILTERED FACTOR > PENGRIP THRESH ?
Y
N
493
INNER FINGERS TOUCHING ?
Y
N
494
SEND STYLUS LIFT SIGNAL TO HANDWRITING RECOGNIZER & KNUCKLE/PALM MOTION TO CURSOR
END
495
SEND PARAMETERS OF INNER FINGER PATHS TO HANDWRITING RECOGNIZER
END

FIG. 28


START
450
CONTACT PROXIMITIES STABILIZED ?
Y
N
452
RETAIN PREVIOUS IDENTIFICATIONS VIA PATH EXTENSION
END
DEFINE & TRANSLATE LEFT & RIGHT ATTRACTOR TEMPLATES
453
456
PICK FIRST CONTOUR
GENERATE PARTITIONING CONTOURS
454
TENTATIVELY DIVIDE HAND IDENTITIES ACROSS CONTOUR
458
TENTATIVELY ASSIGN FINGER IDENTITIES WITHIN EACH HAND
460
EVALUATE BIOMECHANICAL COHERENCE OF PARTITION
462
PICK NEXT CONTOUR
470
464
COST LOWEST SO FAR ?
Y
N
466
RECORD PARTITION AS LOWEST COST
N
472
LAST CONTOUR ?
Y
473
CHOOSE LOWEST COST HAND PARTITION
474
ASSIGN FINAL CONTACT IDENTITIES WITHIN EACH HAND
END

FIG. 29



FIG. 30A



FIG. 30B



FIG. 30C



FIG. 31A



FIG. 31B



FIG. 31C


RIGHT INNER
ANGLE FACTOR
1
0
−150
−100
−50
0
50
100
150
ANGLE BETWEEN INNERMOST AND
NEXT INNERMOST FINGER CONTACTS (degrees)

FIG. 32


INTER-HAND
SEPARATION FACTOR
1
0
−6
−4
−2
0
2
4
6
8
10
12
ESTIMATED HORIZONTAL
SEPARATION BETWEEN THUMBS (cm)

FIG. 33


START
GET HAND'S CURRENT PATH PARAMETERS & ID'S
500
SUPPRESSIVE FINGER VELOCITY FILTERING
502
MEASURE HAND'S POLAR VELOCITY COMPONENTS
504
MEASURE HAND'S TRANSLATIONAL VELOCITY COMPONENTS
506
MEASURE HAND'S DIFFERENTIAL TILT PRESSURE COMPONENTS
508
DOWNSCALE WEAKER COMPONENTS
510
DEAD-ZONE FILTER ALL COMPONENTS BY FRACTION OF FASTEST COMPONENT
512
END

FIG. 34



FIG. 35


START
522
AT LEAST 2 FINGERS DOWN ?
N
524
SET RADIAL AND ANGULAR VELOCITY TO ZERO
END
Y
GET CURRENT AND PREVIOUS POSITIONS OF INNERMOST AND OUTERMOST TOUCHING FINGERS
526
COMPUTE RADIAL VELOCITY FROM CHANGE IN SEPARATION BETWEEN INNERMOST AND OUTERMOST
528
COMPUTE ROTATIONAL VELOCITY FROM SEPARATION AND CHANGE IN ANGLE BETWEEN INNERMOST AND OUTERMOST
530
COMBINE WITH ROTATION AND SCALING ABOUT A FIXED POINT BETWEEN THUMB AND OTHER FINGERS
531
532
AVERAGE PROXIMITY DROPPING ?
N
534
CHECK FOR RADIAL OR ROTATIONAL DECELERATION
Y
END

FIG. 36


START
540
INIT TRANSLATION WEIGHTINGS TO FINGER PROXIMITIES
544
DECREASE TRANSLATION WEIGHTING OF RELATIVELY SLOW FINGERS
546
DECREASE TRANSLATION WEIGHTING OF CENTRAL FINGERS AS POLAR COMPONENT SPEEDS INCREASE
548
COMPUTE TRANSLATION VELOCITY AS WEIGHTED AVERAGE OF FINGER VELOCITIES
550
AVERAGE PROXIMITY DROPPING ?
N
Y
551
ACCEL RATIO = CURRENT SPEED/ PAST AVERAGE
552
ACCEL RATIO > THRESH NEAR ONE ?
N
Y
554
TRANSLATION DIRECTION CLOSE TO PAST AVERAGE ?
N
Y
556
SET TRANSLATION DECELERATION FLAG
CLEAR TRANSLATION DECELERATION FLAG
558
UPDATE MOVING WINDOW AVERAGE OF TRANSLATION VELOCITIES
560
END

FIG. 37


START
HAND FLATTENED ?
562
N
Y
SET TILT & ROLL COMPONENTS TO ZERO
564
END
ALL PATH PROXIMITIES STABILIZED ?
566
N
Y
STORE CURRENT PATH PROXIMITIES AS REFERENCE PROXIMITIES
568
COMPUTE UNWEIGHTED AVERAGE OF PATH POSITIONS
570
COMPUTE RATIOS OF CURRENT PROXIMITY TO REFERENCE PROXIMITY FOR EACH PATH
572
SET RATIOS LESS THAN ONE TO ONE
574
COMPUTE AVERAGE OF PATH POSITIONS WEIGHTED BY PROXIMITY RATIOS
576
COMPUTE TILT & ROLL COMPONENTS FROM DIFFERENCE VECTOR BETWEEN WEIGHTED AND UNWEIGHTED AVERAGES
578
END

FIG. 38


GET HAND'S CURRENT PATH PARAMETERS & ID'S
600
A
SEARCH FOR FINGER SUBSETS PRESSED OR RELEASED SIMULTANEOUSLY
603
DELETE ASSOCIATED KEYPRESS QUEUE ELEMENTS
601
N
SYNC MARKER PENDING ?
602
N
ANY PRESSES SYNCED ?
604
N
FINGER RELEASES SYNCED > 2 ?
Y
605
Y
Y
SET SYNC TIME MARKER
606
FINGER PRESSES SYNCED > 2 ?
N
608
Y
PAUSE SENDING OF ASSOCIATED KEYPRESS QUEUE ELEMS
610
A
624
CLEAR SYNC MARKER
DELETE ASSOCIATED KEY QUEUE ELEMS
612
C
TOUCHING OR HALTED TOO LONG ?
Y
DELETE ASSOCIATED KEY QUEUE ELEMENTS
614
615
N
RESUME KEY QUEUE SENDING
622
N
SYNCED FINGERS LIFTING ?
616
N
Y
LIFTING SIMULTANEOUSLY ?
Y
B
618

FIG. 39A


B
DELETE ASSOCIATED KEYPRESS QUEUE ELEMENTS
620
SYNCED FINGERS DOWN BRIEFLY ?
626
N
Y
SIGNIFICANT LATERAL MOTION ?
628
Y
C
N
LOOKUP CHORD FROM SYNCED FINGER ID'S
630
CHORD HAS TAP EVENTS ?
632
N
RESTING CHORD: NO EVENTS GENERATED
634
Y
APPEND CHORD TAP EVENTS TO COMM QUEUE
636
C

FIG. 39B


GET HAND'S EXTRACTED MOTION & IDENTIFIED PATHS
650
A
CHORD SLIDE ONGOING ?
652
N
FINGERS TOUCHING > 2 ?
654
N
Y
SYNCED SUBSET OR ALL FINGERS SLIDING ?
656
N
Y
SELECT SLIDE CHORD FROM SYNCED SUBSET OR COMBINATION OF FINGERS TOUCHING
658
DISABLE KEY & CHORD TAPS FOR THIS HAND
660
B
FINGER SUBSET LIFTED ?
664
Y
N
PRE-LIFTOFF DECELERATION FLAG SET ?
666
Y
N
LEAVE CHORD SLIDE MODE
668
A
SET CURRENT VELOCITY COMPONENTS TO PRE-LIFTOFF AVERAGE
667
B
NEW SUBSET PRESSED IN SYNC ?
670
Y
N
WHOLE SUBSET SLIDING ?
673
N
Y
B
SELECT NEW SLIDE CHORD FROM NEW SYNCED SUBSET
674
B

FIG. 40A


B
PICK FIRST SLICE DEFINED FOR SELECTED CHORD
675
APPLY SLICE'S VELOCITY GAIN FUNCTION TO MOTION COMPONENTS
676
PROJECT VELOCITY COMPONENTS INTO SLICE'S SPEED AND DIRECTION RANGE
677
INTEGRATE PROJECTED VELOCITY COMPONENTS OVER TIME
678
UNITS OF MOTION >= 1 ?
680
N
Y
LOOKUP SLICE'S KEY/MOUSE/3D EVENTS
682
APPEND EVENTS W/ # MOTION UNITS TO COMM QUEUE
684
REMOVE INTEGER # MOTION UNITS FROM INTEGRATORS
686
RESET OTHER SLICES' INTEGRATORS
688
ONE-SHOT SLICE ?
689
N
Y
DISABLE FURTHER EVENTS FROM ONE-SHOT SLICE
690
LAST SLICE FOR CHORD ?
692
N
Y
A
PICK NEXT SLICE
694

FIG. 40B


START
RETRIEVE KEY LAYOUT REGIONS AND SYMBOLS
700
GET CURRENT IDENTIFIED PATHS FOR BOTH HANDS
702
5 FINGERS ON SAME HAND PRESSED IN SYNC?
704
Y
N
TRANSLATE HAND'S KEY REGIONS BY MEASURED HAND OFFSETS
706
FINGERS PARTIALLY CLOSED ?
708
Y
N
NOTHING TOUCHING SURFACE FOR AWHILE?
714
Y
N
RESET KEY LAYOUT OFFSETS TO ZERO
716
ADJUST REGIONS IN EACH FINGER'S COLUMN BY FINGER OFFSETS
710
UPDATE DISPLAYED POSITIONS OF KEY SYMBOLS
712
PROCESS FINGER TAPS ON MORPHED KEY LAYOUT
718

FIG. 41


START
GET ANY PATH RECENTLY CREATED BY HAND PART TOUCHDOWN
750
PATH PROXIMITY JUST CROSSED KEYPRESS THRESH ?
752
N
Y
PATH IDENTIFIED AS FINGER NOT PALM?
754
N
Y
PATH'S HAND SLIDING/ WRITING ?
756
Y
N
DEBOUNCE OK ?
757
Y
N
FIND CLOSEST KEY REGION
760
ANY KEY REGION NEARBY ?
762
N
Y
CREATE KEYPRESS QUEUE ELEMENT CONTAINING PATH ID, CLOSEST KEY & PRESS TIMESTAMP
764
APPEND KEYPRESS QUEUE ELEMENT TO TAIL OF FIFO KEYPRESS QUEUE
766

FIG. 42


START
A
DELETE CURRENT ELEMENT FROM KEYPRESS QUEUE
B
PICK ELEMENT AT HEAD OF KEYPRESS QUEUE
770
778
C
ELEMENT PATH STILL IDENTIFIED AS FINGER ?
772
PATH IN A SYNCHRONIZED SUBSET ?
774
FINGER SLID TOO FAR ?
776
Y
N
782
TIME SINCE PRESS < TAP TIMEOUT
780
FINGER LIFTED ?
B
784
APPEND PRECEDING MODIFIERS & ELEMENT'S KEY REGION SYMBOL TO HOST COMM QUEUE
788
SKIP TO NEXT ELEMENT IN QUEUE
C
786
KEY REGION A MODIFIER ?
792
PATH PROXIMITY PROFILE IMPULSIVE ?
790
MOST FINGERS TOUCHING ?
D

FIG. 43A


D
B
798
794
796
TYPEMATIC STARTED FOR ELEMENT ?
FINGER TOUCHDOWN MOST RECENT?
TIME SINCE FINGER PRESS > TAP TIMEOUT ?
Y
N
N
Y
Y
N
N
A
B
805
800
802
ANOTHER ASYNCHRONOUS TAP ?
FINGER DOWN > .5s AND < 1s ?
HAND'S OTHER FINGERS LIFTED > .5s ?
Y
Y
N
N
Y
A
COMPUTE REPEAT INTERVAL FROM CURRENT FINGER PROXIMITY
806
804
INITIALIZE TYPEMATIC MODE FOR ELEMENT
808
TIME SINCE LAST SEND > REPEAT INTERVAL ?
Y
N
810
APPEND PRECEDING MODIFIERS & ELEMENT'S KEY REGION SYMBOL TO HOST COMM QUEUE
812
UPDATE LAST TYPEMATIC SEND TIMESTAMP
A

FIG. 43B

TOUCH SENSOR CONTACT INFORMATION

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a continuation of Ser. No. 14/163,929, entitled "Touch Sensor Contact Information" (now Pub. No. US2014-0176499) filed Jan. 24, 2014, which is a continuation of Ser. No. 11/830,793, entitled "Touch Sensor Contact Information" (now U.S. Pat. No. 8,698,755) filed Jul. 30, 2007, which is a continuation of Ser. No. 11/015,434, entitled "Method and Apparatus for Integrating Manual Input" (now U.S. Pat. No. 7,339,580) filed Dec. 17, 2004, which is a continuation of Ser. No. 09/919,266, entitled "Method And Apparatus For Integrating Manual Input" (now U.S. Pat. No. 6,888,536) filed Jul. 31, 2001, which is a division of application Ser. No. 09/236,513 (now U.S. Pat. No. 6,323,846) filed Jan. 25, 1999, which claims the benefit of provisional application 60/072,509, filed Jan. 26, 1998, each of which is hereby incorporated by reference in its entirety.

BACKGROUND OF THE INVENTION

A. Field of the Invention

The present invention relates generally to methods and apparatus for data input, and, more particularly, to a method and apparatus for integrating manual input.

B. Description of the Related Art

Many methods for manual input of data and commands to computers are in use today, but each is most efficient and easy to use for particular types of data input. For example, drawing tablets with pens or pucks excel at drafting, sketching, and quick command gestures. Handwriting with a stylus is convenient for filling out forms which require signatures, special symbols, or small amounts of text, but handwriting is slow compared to typing and voice input for long documents. Mice, finger-sticks and touchpads excel at cursor pointing and graphical object manipulations such as drag and drop. Rollers, thumbwheels and trackballs excel at panning and scrolling. The diversity of tasks that many computer users encounter in a single day call for all of these techniques, but few users will pay for a multitude of input devices, and the separate devices are often incompatible in a usability and an ergonomic sense. For instance, drawing tablets are a must for graphics professionals, but switching between drawing and typing is inconvenient because the pen must be put down or held awkwardly between the fingers while typing. Thus, there is a long-felt need in the art for a manual input device which is cheap yet offers convenient integration of common manual input techniques.

Speech recognition is an exciting new technology which promises to relieve some of the input burden on user hands. However, voice is not appropriate for inputting all types of data either. Currently, voice input is best-suited for dictation of long text documents. Until natural language recognition matures sufficiently that very high level voice commands can be understood by the computer, voice will have little advantage over keyboard hot-keys and mouse menus for command and control. Furthermore, precise pointing, drawing, and manipulation of graphical objects is difficult with voice commands, no matter how well speech is understood. Thus, there will always be a need in the art for multi-function manual input devices which supplement voice input.

A generic manual input device which combines the typing, pointing, scrolling, and handwriting capabilities of the standard input device collection must have ergonomic, economic, and productivity advantages which outweigh the unavoidable

sacrifices of abandoning device specialization. The generic device must tightly integrate yet clearly distinguish the different types of input. It should therefore appear modeless to the user in the sense that the user should not need to provide explicit mode switch signals such as button presses, arm relocations, or stylus pickups before switching from one input activity to another. Epidemiological studies suggest that repetition and force multiply in causing repetitive strain injuries. Awkward postures, device activation force, wasted motion, and repetition should be minimized to improve ergonomics. Furthermore, the workload should be spread evenly over all available muscle groups to avoid repetitive strain.

Repetition can be minimized by allocating to several graphical manipulation channels those tasks which require complex mouse pointer motion sequences. Common graphical user interface operations such as finding and manipulating a scroll bar or slider control are much less efficient than specialized finger motions which cause scrolling directly, without the step of repositioning the cursor over an on-screen control. Preferably the graphical manipulation channels should be distributed amongst many finger and hand motion combinations to spread the workload. Touchpads and mice with auxilliary scrolling controls such as the Cirque®™ Smartcat touchpad with edge scrolling, the IBM®™ ScrollPoint™ mouse with embedded pointing stick, and the Roller Mouse described in U.S. Pat. No. 5,530,455 to Gillick et al. represent small improvements in this area, but still do not provide enough direct manipulation channels to eliminate many often-used cursor motion sequences. Furthermore, as S. Zhai et al. found in "Dual Stream Input for Pointing and Scrolling," Proceedings of CHI '97 Extended Abstracts (1997), manipulation of more than two degrees of freedom at a time is very difficult with these devices, preventing simultaneous panning, zooming and rotating.

Another common method for reducing excess motion and repetition is to automatically continue pointing or scrolling movement signals once the user has stopped moving or lifts the finger. Related art methods can be distinguished by the conditions under which such motion continuation is enabled. In U.S. Pat. No. 4,734,685, Watanabe continues image panning when the distance and velocity of pointing device movement exceed thresholds. Automatic panning is, stopped by moving the pointing device back in the opposite direction, so stopping requires additional precise movements. In U.S. Pat. No. 5,543,591 to Gillespie et al., motion continuation occurs when the finger enters an edge border region around a small touchpad. Continued motion speed is fixed and the direction corresponds to the direction from the center of the touchpad to the finger at the edge. Continuation mode ends when the finger leaves the border region or lifts off the pad. Disadvantageously, users sometimes pause at the edge of the pad without intending for cursor motion to continue, and the unexpected motion continuation becomes annoying. U.S. Pat. No. 5,327,161 to Logan et al. describes motion continuation when the finger enters a border area as well, but in an alternative trackball emulation mode, motion continuation can be a function solely of lateral finger velocity and direction at liftoff. Motion continuation decays due to a friction factor or can be stopped by a subsequent touchdown on the surface. Disadvantageously, touch velocity at liftoff is not a reliable indicator of the user's desire for motion continuation since when approaching a large target on a display at high speeds the user may not stop the pointer completely before liftoff. Thus it would be an advance in the art to provide a motion continuation method which does not become activated unexpectedly when the user really intended to stop pointer move-

ment at a target but happens to be on a border or happens to be moving at significant speed during liftoff.

Many attempts have been made to embed pointing devices in a keyboard so the hands do not have to leave typing position to access the pointing device. These include the integrated pointing key described in U.S. Pat. No. 5,189,403 to Franz et al., the integrated pointing stick disclosed by J. Rutledge and T. Selker in "Force-to-Motion Functions for Pointing," Human-Computer Interaction—INTERACT '90, pp. 701-06 (1990), and the position sensing keys described in U.S. Pat. No. 5,675,361 to Santilli. Nevertheless, the limited movement range and resolution of these devices, leads to poorer pointing speed and accuracy than a mouse, and they add mechanical complexity to keyboard construction. Thus there exists a need in the art for pointing methods with higher resolution, larger movement range, and more degrees of freedom yet which are easily accessible from typing hand positions.

Touch screens and touchpads often distinguish pointing motions from emulated button clicks or keypresses by assuming very little lateral fingertip motion will occur during taps on the touch surface which are intended as clicks. Inherent in these methods is the assumption that tapping will usually be straight down from the suspended finger position, minimizing those components of finger motion tangential to the surface. This is a valid assumption if the surface is not finely divided into distinct key areas or if the user does a slow, "hunt and peck" visual search for each key before striking. For example, in U.S. Pat. No. 5,543,591 to Gillespie et al., a touchpad sends all lateral motions to the host computer as cursor movements. However, if the finger is lifted soon enough after touchdown to count as a tap and if the accumulated lateral motions are not excessive, any sent motions are undone and a mouse button click is sent instead. This method only works for mouse commands such as pointing which can safely be undone, not for dragging or other manipulations. In U.S. Pat. No. 5,666,113 to Logan, taps with less than about 1/16" lateral motion activate keys on a small keypad while lateral motion in excess of 1/16" activates cursor control mode. In both patents cursor mode is invoked by default when a finger stays on the surface a long time.

However, fast touch typing on a surface divided into a large array of key regions tends to produce more tangential motions along the surface than related art filtering techniques can tolerate. Such an array contains keys in multiple rows and columns which may not be directly under the fingers, so the user must reach with the hand or flex or extend fingers to touch many of the key regions. Quick reaching and extending imparts significant lateral finger motion while the finger is in the air which may still be present when the finger contacts the surface. Glancing taps with as much as 1/4" lateral motion measured at the surface can easily result. Attempting to filter or suppress this much motion would make the cursor seem sluggish and unresponsive. Furthermore, it may be desirable to enter a typematic or automatic key repeat mode instead of pointing mode when the finger is held in one place on the surface. Any lateral shifting by the fingertip during a prolonged finger press would also be picked up as cursor jitter without heavy filtering. Thus, there is a need in the art for a method to distinguish keying from pointing on the same surface via more robust hand configuration cues than lateral motion of a single finger.

An ergonomic typing system should require minimal key tapping force, easily distinguish finger taps from resting hands, and cushion the fingers from the jarring force of surface impact. Mechanical and membrane keyboards rely on the spring force in the keyswitches to prevent activation when the hands are resting on the keys. This causes an irreconcilable tradeoff between the ergonomic desires to reduce the fatigue from key activating force and to relax the full weight of the hands onto the keys during rest periods. Force minimization on touch surfaces is possible with capacitive or active optical sensing, which do not rely on finger pressure, rather than resistive-membrane or surface-acoustic-wave sensing techniques. The related art touch devices discussed below will become confused if a whole hand including its four fingertips a thumb and possibly palm heels, rests on the surface. Thus, there exists a long felt need in the art for a multi-touch surface typing system based on zero-force capacitive sensing which can tolerate resting hands and a surface cushion.

An ergonomic typing system should also adapt to individual hand sizes tolerate variations in typing style, and support a range of healthy hand postures. Though many ergonomic keyboards have been proposed, mechanical keyswitches can only be repositioned at great cost. For example, the keyboard with concave keywells described by Hargreaves et al. in U.S. Pat. No. 5,689,253 fits most hands well but also tends to lock the arms in a single position. A touch surface key layout could easily be morphed, translated, or arbitrarily reconfigured as long as the changes did not confuse the user. However, touch surfaces may not provide as much laterally orienting tactile feedback as the edges of mechanical keyswitches. Thus, there exists a need in the art for a surface typing recognizer which can adapt a key layout to fit individual hand postures and which can sustain typing accuracy if the hands drift due to limited tactile feedback.

Handwriting on smooth touch surfaces using a stylus is well-known in the art, but it typically does not integrate well with typing and pointing because the stylus must be put down somewhere or held awkwardly during other input activities. Also, it may be difficult to distinguish the handwriting activity of the stylus from pointing motions of a fingertip. Thus there exists a need in the art for a method to capture coarse handwriting gestures without a stylus and without confusing them with pointing motions.

Many of the input differentiation needs cited above could be met with a touch sensing technology which distinguishes a variety of hand configurations and motions such as sliding finger chords and grips. Many mechanical chord keyboards have been designed to detect simultaneous downward activity from multiple fingers, but they do not detect lateral finger motion over a large range. Related art shows several examples of capacitive touchpads which emulate a mouse or keyboard by tracking a single finger. These typically measure the capacitance of or between elongated wires which are laid out in rows and columns. A thin dielectric is interposed between the row and column layers. Presence of a finger perturbs the self or mutual capacitance for nearby electrodes. Since most of these technologies use projective row and column sensors which integrate on one electrode the proximity of all objects in a particular row or column, they cannot uniquely determine the positions of two or more objects as discussed in S. Lee, "A Fast Multiple-Touch-Sensitive Input Device," University of Toronto Masters Thesis (1984). The best they can do is count fingertips which happen to lie in a straight row, and even that will fail if a thumb or palm is introduced in the same column as a fingertip.

In U.S. Pat. Nos. 5,565,658 and 5,305,017, Gerpheide et al. measure the mutual capacitance between row and column electrodes by driving one set of electrodes at some clock frequency and sensing how much of that frequency is coupled onto a second electrode set. Such synchronous measurements are very prone to noise at the driving frequency, so to increase

signal-to-noise ratio they form virtual electrodes comprised of multiple rows or multiple columns, instead of a single row and column, and scan through electrode combinations until the various mutual capacitances are nulled or balanced. The coupled signal increases with the product of the rows and columns in each virtual electrodes, but the noise only increases with the sum, giving a net gain in signal-to-noise ratio for virtual electrodes consisting of more than two rows and two columns. However, to uniquely distinguish multiple objects, virtual electrode sizes would have to be reduced so the intersection of the row and column virtual electrodes would be no larger than a finger tip, i.e., about two rows and two columns, which will degrade the signal-to-noise ratio. Also, the signal-to-noise ratio drops as row and column lengths increase to cover a large area.

In U.S. Pat. Nos. 5,543,591, 5,543,590, and U.S. Pat. No. 5,495,077, Gillespie et al measure the electrode-finger self-capacitance for row and column electrodes independently. Total electrode capacitance is estimated by measuring the electrode voltage change caused by injecting or removing a known amount of charge in a known time. All electrodes can be measured simultaneously if each electrode has its own drive/sense circuit. The centroid calculated from all row and column electrode signals establishes an interpolated vertical and horizontal position for a single object. This method may in general have higher signal-to-noise ratio than synchronous methods, but the signal-to-noise ratio is still degraded as row and column lengths increase. Signal-to-noise ratio is especially important for accurately locating objects which are floating a few millimeters above the pad. Though this method can detect such objects, it tends to report their position as being near the middle of the pad, or simply does not detect floating objects near the edges.

Thus there exists a need in the art for a capacitance-sensing apparatus which does not suffer from poor signal-to-noise ratio and the multiple finger indistinguishability problems of touchpads with long row and column electrodes.

U.S. Pat. No. 5,463,388 to Boie et al. has a capacitive sensing system applicable to either keyboard or mouse input, but does not consider the problem of integrating both types of input simultaneously. Though they mention independent detection of arrayed unit-cell electrodes, their capacitance transduction circuitry appears too complex to be economically reproduced at each electrode. Thus the long lead wires connecting electrodes to remote signal conditioning circuitry can pickup noise and will have significant capacitance compared to the finger-electrode self-capacitance, again limiting signal-to-noise ratio. Also, they do not recognize the importance of independent electrodes for multiple finger tracking, or mention how to track multiple fingers on an independent electrode array.

Lee built an early multi-touch electrode array, with 7 mm by 4 mm metal electrodes arranged in 32 rows and 64 columns. The "Fast Multiple-Touch-Sensitive Input Device (FMTSID)" total active area measured 12" by 16", with a 0.075 mm Mylar dielectric to insulate fingers from electrodes. Each electrode had one diode connected to a row charging line and a second diode connected to a column discharging line. Electrode capacitance changes were measured singly or in rectangular groups by raising the voltage on one or more row lines, selectively charging the electrodes in those rows, and then timing the discharge of selected columns to ground through a discharge resistor. Lee's design required only two diodes per electrode, but the principal disadvantage of Lee's design is that the column diode reverse bias capacitances allowed interference between electrodes in the same column.

All of the related capacitance sensing art cited above utilize interpolation between electrodes to achieve high pointing resolution with economical electrode density. Both Boie et al. and Gillespie et al. discuss compultattion of a centroid from all row and column electrode readings. However, for multiple finger detection, centroid calculation must be carefully limited around local maxima to include only one finger at a time. Lee utilizes a bisective search technique to find local maxima and then interpolates only on the eight nearest neighbor electrodes of each local maximum electrode. This may work fine for small fingertips, but thumb and palm contacts may cover more than nine electrodes. Thus there exists a need in the art for improved means to group exactly those electrodes which are covered by each distinguishable hand contact and to compute a centroid from such potentially irregular groups.

To take maximum advantage of multi-touch surface sensing, complex proximity image processing is necessary to track and identify the parts of the hand contacting the surface at any one time. Compared to passive optical, images, proximity images provide clear indications of where the body contacts the surface, uncluttered by luminosity variation and extraneous objects in the background. Thus proximity image filtering and segmentation stages can be simpler and more reliable than in computer vision approaches to free-space hand tracking such as S. Alimad, "A Usable Real-Time 3D Hand Tracker," Proceedings of the 28th Asilomar Conference on Signals, Systems, and Computers—Part 2, vol. 2, IEEE (1994) or Y. Cui and J. Wang, "Hand Segmentation Using Learning-Based Prediction and Verification for Hand Sign Recognition," Proceedings of the 1996 IEEE Computer Society Conference on Computer Vision and Pattern Recognition, pp. 88-93 (1996). However, parts of the hand such as intermediate finger joints and the center of the palms do not show up in capacitive proximity images at all if the hand is not flattened on the surface. Without these intermediate linkages between fingertips and palms the overall hand structure can only be guessed at, making hand contact identification very difficult. Hence the optical flow and contour tracking techniques which have been applied to free-space hand sign language recognition as in F. Quek, "Unencumbered Gestural Interaction," IEEE Multimedia, vol. 3, pp. 36-47 (1996), do not address the special challenges of proximity image tracking.

Synaptics Corp. has successfully fabricated their electrode array on flexible mylar film rather than stiff circuit board. This is suitable for conforming to the contours of special products, but does not provide significant finger cushioning for large surfaces. Even if a cushion was placed under the film, the lack of stretchability in the film, leads, and electrodes would limit the compliance afforded by the compressible material. Boie et al suggests that placing cornnressihle insulators on top of the electrode array cushions finger impact. However, an insulator more than about one millimeter thick would seriously attenuate the measured finger-electrode capacitances. Thus there exists a need in the art for a method to transfer finger capacitance influences through an arbitrarily thick cushion.

SUMMARY OF THE INVENTION

It is a primary object of the present invention to provide a system and method for integrating different types of manual input such as typing, multiple degree-of-freedom manipulation, and handwriting on a multi-touch surface.

It is also an object of the present invention to provide a system and method for distinguishing different types of manual input such as typing, multiple degree-of-freedom manipulation, and handwriting on a multi-touch surface, via

different hand configurations which are easy for the user to learn and easy for the system to recognize.

It is a further object of the present invention to provide an improved capacitance-transducing apparatus that is cheaply implemented near each electrode so that two-dimensional sensor arrays of arbitrary size and resolution can be built without degradation in signal to noise.

It is a further object of the present invention to provide an electronic system which minimizes the number of sensing electrodes necessary to obtain proximity images with such resolution that a variety of hand configurations can be distinguished.

Yet another object of the present invention is to provide a multi-touch surface apparatus which is compliant and contoured to be comfortable and ergonomic under extended use.

Yet another object of the present invention is to provide tactile key or hand position feedback without impeding hand resting on the surface or smooth, accurate sliding across the surface.

It is a further object of the present invention to provide an electronic system which can provide images of flesh proximity to an array of sensors with such resolution that a variety of hand configurations can be distinguished.

It is another object of the present invention to provide an improved method for invoking cursor motion continuation only when the user wants it by not invoking it when significant deceleration is detected.

Another object of the present invention is to identify different hand parts as they contact the surface so that a variety of hand configurations can be recognized and used to distinguish different kinds of input activity.

Yet another object of the present invention is to reliably extract rotation and scaling as well as translation degrees of freedom from the motion of two or more hand contacts to aid in navigation and manipulation of two-dimensional electronic documents.

It is a further object of the present invention to reliably extract tilt and roll degrees of freedom from hand pressure differences to aid in navigation and manipulation of three-dimensional environments.

Additional objects and advantages of the invention will be set forth in part in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention will be realized and attained by means of the elements and combinations particularly pointed out in the appended claims.

To achieve the objects and in accordance with the purpose of the invention, as embodied and broadly described herein, the invention comprises a sensing device that is sensitive to changes in self-capacitance brought about by changes in proximity of a touch device to the sensing device, the sensing device comprising: two electrical switching means connected together in series having a common node, an input node, and an output node; a dielectric-covered sensing electrode connected to the common node between the two switching means; a power supply providing an approximately constant voltage connected to the input node of the series-connected switching means; an integrating capacitor to accumulate charge transferred during multiple consecutive switchings of the series connected switching means; another switching means connected in parallel across the integrating capacitor to deplete its residual charge; and a voltage-to-voltage translation device connected to the output node of the series-connected switching means which produces a voltage representing the magnitude of the self-capacitance of the sensing device. Alternatively, the sensing device comprises: two electrical switching means connected together in series having a common node, an input node, and an output node; a dielectric-covered sensing electrode connected to the common node between the two switching means; a power supply providing an approximately constant voltage connected to the input node of the series-connected switching means; and an integrating current-to-voltage translation device connected to the output node of the series connected switching means, the current-to-voltage translation device producing a voltage representing the magnitude of the self-capacitance of the sensing device.

To further achieve the objects, the present invention comprises a multi-touch surface apparatus for detecting a spatial arrangement of multiple touch devices on or near the surface of the multi-touch apparatus, comprising: one of a rigid or flexible surface; a plurality of two-dimensional arrays of one of the sensing devices (recited in the previous paragraph) arranged on the surface in groups wherein the sensing devices within a group have their output nodes connected together and share the same integrating capacitor, charge depletion switch, and voltage-to-voltage translation circuitry; control circuitry for enabling a single sensor device from each two-dimensional array; means for selecting the sensor voltage data from each two-dimensional array; voltage measurement circuitry to convert sensor voltage data to a digital code; and circuitry for communicating the digital code to another electronic device. The sensor voltage data selecting means comprises one of a multiplexing circuitry and a plurality of voltage measurement circuits.

To still further achieve the objects, the present invention comprises a multi-touch surface apparatus for sensing diverse configurations and activities of touch devices and generating integrated manual input to one of an electronic or electromechanical device, the apparatus comprising: an array of one of the proximity sensing devices described above; a dielectric cover having symbols printed thereon that represent action-to-be-taken when engaged by the touch devices; scanning means for forming digital proximity images from the array of sensing devices; calibrating means for removing background offsets from the proximity images; recognition means for interpreting the configurations and activities of the touch devices that make up the proximity images; processing means for generating input signals in response to particular touch device configurations and motions; and communication means for sending the input signals to the electronic or electromechanical device.

To even further achieve the objects, the present invention comprises a multi-touch surface apparatus for sensing diverse configurations and activities of fingers and palms of one or more hands near the surface and generating integrated manual input to one of an electronic or electromechanical device, the apparatus comprising: an array of proximity sensing means embedded in the surface; scanning means for forming digital proximity images from the proximities measured by the sensing means; image segmentation means for collecting into groups those proximity image pixels intensified by contact of the same distinguishable part of a hand; contact tracking means for parameterizing hand contact features and trajectories as the contacts move across successive proximity images, contact identification means for determining which hand and which part of the hand is causing each surface contact; synchronization detection means for identifying subsets of identified contacts which touchdown or liftoff the surface at approximately the same time, and for generating command signals in response to synchronous taps of multiple fingers on the surface; typing recognition means for generating intended key symbols from asynchronous finger taps; motion compo-

nent extraction means for compressing multiple degrees of freedom of multiple fingers into degrees of freedom common in two and three dimensional graphical manipulation; chord motion recognition means for generating one of command and cursor manipulation signals in response to motion in one or more extracted degrees of freedom by a selected combination of fingers; pen grip detection means for recognizing contact arrangements which resemble the configuration of the hand when gripping a pen, generating inking signals from motions of the inner fingers, and generating cursor manipulation signals from motions of the palms while the inner fingers are lifted; and communication means for sending the sensed configurations and activities of finger and palms to one of the electronic and electromechanical device.

To further achieve the objects, the present invention comprises a method for tracking and identifying hand contacts in a sequence of proximity images in order to support interpretation of hand configurations and activities related to typing, multiple degree-of-freedom manipulation via chords, and handwriting, the method comprising the steps of: segmenting each proximity image into groups of electrodes which indicate significant proximity, each group representing proximity of a distinguishable hand part or other touch device; extracting total proximity, position, shape, size, and orientation parameters from each group of electrodes; tracking group paths through successive proximity images including detection of path endpoints at contact touchdown and liftoff; computing velocity and filtered position vectors along each path; assigning a hand and finger identity to each contact path by incorporating relative path positions and velocities, individual contact features, and previous estimates of hand and finger positions; and maintaining estimates of hand and finger positions from trajectories of paths currently assigned to the fingers, wherein the estimates provide high level feedback to bias segmentations and identifications in future images.

To still further achieve the objects, the present invention comprises a method for integrally extracting multiple degrees of freedom of hand motion from sliding motions of two or more fingers of a hand across a multi-touch surface, one of the fingers preferably being the opposable thumb, the method comprising the steps of: tracking across successive scans of the proximity sensor array the trajectories of individual hand parts on the surface; finding an innermost and an outermost finger contact from contacts identified as fingers on the given hand; computing a scaling velocity component from a change in a distance between the innermost and outermost finger contacts; computing a rotational velocity component from a change in a vector angle between the innermost and outermost finger contacts; computing a translation weighting for each contacting finger; computing translational velocity components in two dimensions from a translation weighted average of the finger velocities tangential to surface; suppressively filtering components whose speeds are consistently lower than the fastest components; transmitting the filtered velocity components as control signals to an electronic or electromechanical device.

To even further achieve the objects, the present invention comprises a manual input integration method for supporting diverse hand input activities such as resting the hands, typing, multiple degree-of-freedom manipulation, command gesturing and handwriting on a multi-touch surface, the method enabling users to instantaneously switch between the input activities by placing their hands in different configurations comprising distinguishable combinations of relative hand contact timing, proximity, shape, size, position, motion and/or identity across a succession of surface proximity images, the method comprising the steps of: tracking each touching hand part across successive proximity images; measuring the times when each hand part touches down and lifts off the surface; detecting when hand parts touch down or lift off simultaneously; producing discrete key symbols when the user asynchronously taps, holds, or slides a finger on key regions defined on the surface; producing discrete mouse button click commands, key commands, or no signals when the user synchronously taps two or more fingers from the same hand on the surface; producing gesture commands or multiple degree-of-freedom manipulation signals when the user slides two or more fingers across the surface; and sending the produced symbols, commands and manipulation signals as input to an electronic or an electro-mechanical device.

To still even further achieve the objects, the present invention comprises a method for choosing what kinds of input signals will be generated and sent to an electronic or electromechanical device in response to tapping or sliding of fingers on a multi-touch surface, the method comprising the following steps: identifying each contact on the surface as either a thumb, fingertip or palm; measuring the times when each hand part touches down and lifts off the surface; forming a set of those fingers which touch down from the all finger floating state before any one of the fingers lifts back off the surface; choosing the kinds of input signals to be generated by further distinctive motion of the fingers from the combination of finger identities in the set; generating input signals of this kind when further distinctive motions of the fingers occur; forming a subset any two or more fingers which touch down synchronously after at least one finger has lifted back off the surface; choosing a new kinds of input signals to be generated by further distinctive motion of the fingers from the combination of finger identities in the subset; generating input signals of this new kind when further distinctive motions of the fingers occur; and continuing to form new subsets, choose and generate new kinds of input signals in response to liftoff and synchronous touchdowns until all fingers lift off the surface.

To further achieve the objects, the present invention comprises a method for continuing generation of cursor movement or scrolling signals from a tangential motion of a touch device over a touch-sensitive input device surface after touch device liftoff from the surface if the touch device operator indicates that cursor movement continuation is desired by accelerating or failing to decelerate the tangential motion of the touch device before the touch device is lifted, the method comprising the following steps: measuring, storing and transmitting to a computing device two or more representative tangential velocities during touch device manipulation; computing and storing a liftoff velocity from touch device positions immediately prior to the touch device liftoff; comparing the liftoff velocity with the representative tangential velocities, and entering a mode for continuously moving the cursor if a tangential liftoff direction approximately equals the representative tangential directions and a tangential liftoff speed is greater than a predetermined fractional multiple of representative tangential speeds; continuously transmitting cursor movement signals after liftoff to a computing device such that the cursor movement velocity corresponds to one of the representative tangential velocities; and ceasing transmission of the cursor movement signals when the touch device engages the surface again, if comparing means detects significant deceleration before liftoff, or if the computing device replies that the cursor can move no farther or a window can scroll no farther.

It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory only and are not restrictive of the invention as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate several embodiments of the invention and together with the description, serve to explain the principles of the invention. In the drawings:

FIG. **1** is a block diagram of the integrated manual input apparatus;

FIG. **2** is a schematic drawing of the proximity sensor with voltage amplifier;

FIGS. **3**A and **3**B are a schematic drawing of the proximity sensor with integrating current amplifier;

FIGS. **4**A and **4**B are a schematic drawing of the proximity sensor implemented with field effect transistors;

FIGS. **5**A and **5**B are a schematic drawing of the proximity sensor as used to implement 2D arrays of proximity sensors;

FIG. **6** is a block diagram showing a typical architecture for a 2D array of proximity sensors where all sensors share the same amplifier;

FIGS. **7**A and **7**B are a block diagram of circuitry used to convert proximity sensor output to a digital code;

FIG. **8** is a block diagram showing a typical architecture for a 2D array of proximity sensors where sensors within a row share the same amplifier;

FIGS. **9**A and **9**B are a schematic of a circuit useful for enabling the output gates of all proximity sensors within a group (arranged in columns);

FIG. **10** is a side view of a 2D proximity sensor array that is sensitive to the pressure exerted by non-conducting touch objects;

FIG. **11** is a, side view of a 2D proximity sensor array that provides a compliant surface without loss of spatial sensitivity;

FIG. **12** is a side view of a 2D proximity sensor array that is sensitive to both the proximity of conducting touch objects and to the pressure exerted by non-conducting touch objects;

FIG. **13** is an example proximity image of a hand flattened onto the surface with fingers outstretched;

FIG. **14** is an example proximity image of a hand partially closed with fingertips normal to surface;

FIG. **15** is an example proximity image of a hand in the pen grip configuration with thumb and index fingers pinched;

FIG. **16** is a data flow diagram of the hand tracking and contact identification system;

FIG. **17** is a flow chart of hand position estimation:

FIG. **18** is a data flow diagram of proximity image segmentation;

FIG. **19** is a diagram of the boundary search pattern during construction of an electrode group;

FIG. **20**A is a diagram of the segmentation strictness regions with both hands in their neutral, default position on surface;

FIG. **20**B is a diagram of the segmentation strictness regions when the hands are in asymmetric positions on surface;

FIG. **20**C is a diagram of the segmentation strictness regions when the right hand crosses to the left half of the surface and the left hand is off the surface;

FIG. **21** is a flow chart of segmentation edge testing;

FIG. **22** is a flow chart of persistent path tracking;

FIG. **23** is a flow chart of the hand part identification algorithm;

FIG. **24** is a Voronoi cell diagram constructed around hand part attractor points;

FIG. **25**A is a plot of orientation weighting factor for right thumb, right inner palm, and left outer palm versus contact orientation;

FIG. **25**B is a plot of thumb size factor versus contact size;

FIG. **25**C is a plot of palm size factor versus ratio of total contact proximity to contact eccentricity;

FIG. **25**D is a plot of palm separation factor versus distance between a contact and it nearest neighbor contact;

FIG. **26** is a flow chart of the thumb presence verification algorithm;

FIG. **27** is a flow chart of an alternative hand part identification algorithm;

FIG. **28** is a flow chart of the pen grip detection process:

FIG. **29** is a flow chart of the hand identification algorithm:

FIGS. **30**A-C show three different hand partition hypotheses for a fixed arrangement of surface contacts;

FIG. **31**A is a plot of the hand clutching direction factor versus horizontal hand velocity;

FIG. **31**B is a plot of the handedness factor versus vertical position of outermost finger relative to next outermost;

FIG. **31**C is a plot of the palm cohesion factor versus maximum horizontal separation between palm contacts within a hand;

FIG. **32** is a plot of the inner finger angle factor versus the angle between the innermost and next innermost finger contacts;

FIG. **33** is a plot of the inter-hand separation factor versus the estimated distance between the right thumb and left thumb;

FIG. **34** is a flow chart of hand motion component extraction;

FIG. **35** is a diagram of typical finger trajectories when hand is contracting;

FIG. **36** is a flow chart of radial and angular hand velocity extraction;

FIG. **37** is a flow chart showing extraction of translational hand velocity components;

FIG. **38** is a flow chart of differential hand pressure extraction;

FIG. **39**A is a flow chart of the finger synchronization detection loop;

FIG. **39**B is a flow chart of chord tap detection;

FIG. **40**A is a flow chart of the chord motion recognition loop;

FIG. **40**B is a flow chart of chord motion event generation;

FIG. **41** is a flow chart of key layout morphing;

FIG. **42** is a flow chart of the keypress detection loop;

FIG. **43**A is a flow chart of the keypress acceptance and transmission loop; and

FIG. **43**B is a flow chart of typematic emulation.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the present preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings. Wherever possible the same reference numbers will be used throughout the drawings to refer to the same or like parts.

FIG. **1** is a system block diagram of the entire, integrated manual input apparatus. Sensor embedded in the multi-touch surface **2** detect proximity of entire flattened hands **4**, fingertips thumbs, palms, and other conductive touch devices to the surface **2**. In a preferred embodiment, the surface is large enough to comfortably accommodate both hands **4** and is arched to reduce forearm pronation.

In alternative embodiments the multi-touch surface **2** may be large enough to accommodate motion of one hand, but may be flexible so it can be fitted to an armrest or clothing.

Electronic scanning hardware **6** controls and reads from each proximity sensor of a sensor array. A calibration module **8** constructs a raw proximity image from a complete scan of the sensor array and subtracts off any background sensor offsets. The background sensor offsets can simply be a proximity image taken when nothing is touching the surface.

The offset-corrected proximity image is then passed on to the contact tracking and identification module **10**, which segments the image into distinguishable hand-surface contacts, tracks and identifies them as they move through successive images.

The paths of identified contacts are passed on to a typing recognizer module **12**, finger synchronization detection module **14**, motion component extraction module **16**, and pen grip detection module **17**, which contain software algorithms to distinguish hand configurations and respond to detected hand motions.

The typing recognizer module **12** responds to quick presses and releases of fingers which are largely asynchronous with respect to the activity of other fingers on the same hand. It attempts to find the key region nearest to the location of each finger tap and forwards the key symbols or commands associated with the nearest key region to the communication interface module **20**.

The finger synchronization detector **14** checks the finger activity within a hand for simultaneous presses or releases of a subset of fingers. When such simultaneous activity is detected it signals the typing recognizer to ignore or cancel keystroke processing for fingers contained in the synchronous subset. It also passes on the combination of finger identities in the synchronous subset to the chord motion recognizer **18**.

The motion component extraction module **16** computes multiple degrees of freedom of control from individual finger motions during easily performable hand manipulations on the surface **2**, such as hand translations, hand rotation about the wrist, hand scaling by grasping with the fingers, and differential hand tilting.

The chord motion recognizer produces chord tap or motion events dependent upon both the synchronized finger subset identified by the synchronization detector **14** and on the direction and speed of motion extracted in **16**. These events are then posted to the host communication interface **20**.

The pen grip detection module **17** checks for specific arrangements of identified hand contacts which indicate the hand is configured as if gripping a pen. If such an arrangement is, detected, it forwards the movements of the gripping fingers as inking events to the host communication interface **20**. These inking events can either lay digital ink on the host computer display for drawing or signature capture purposes, or they can be further interpreted by handwriting recognition software which is well known in the art. The detailed steps within each of the above modules will be further described later.

The host communication interface keeps events from both the typing recognizer **12** and chord motion recognizer **18** in a single temporally ordered queue and dispatches them to the host computer system **22**. The method of communication between the interface **20** and host computer system **22** can vary widely depending on the function and processing power of the host computer. In a preferred embodiment, the communication would take place over computer cables via industry standard protocols such as Apple Desktop Bus, PS/2 keyboard and mouse protocol for PCs, or Universal Serial Bus (USB). In alternative embodiments the software processing of modules **10-18** would be performed within the host computer **22**. The multi-touch surface apparatus would only contain enough hardware to scan the proximity sensor array **6**, form proximity images **8**, and compress and send them to the host computer over a wireless network. The host communication interface **20** would then play the role of device driver on the host computer, conveying results of the proximity image recognition process as input to other applications residing on the host computer system **22**.

In a preferred embodiment the host computer system outputs to a visual display device **24** so that the hands and fingers **4** can manipulate graphical objects on the display screen. However, in alternative embodiments the host computer might output to an audio display or control a machine such as a robot.

The term "proximity" will only be used in reference to the distance or pressure between a touch device such as a finger and the surface **2**, not in reference to the distance between adjacent fingers. "Horizontal" and "vertical" refer to x and y directional axes within the surface plane. Proximity measurements are then interpreted as pressure in a z axis normal to the surface. The direction "inner" means toward the thumb of a given hand, and the direction "outer" means towards the pinky finger of a given hand. For the purposes of this description, the thumb is considered a finger unless otherwise noted, but it does not count as a fingertip. "Contact" is used as a general term for a hand part when it touches the surface and appears in the current proximity image, and for the group and path data structures which represent it.

FIG. **2** is a schematic diagram of a device that outputs a voltage **58** dependent on the proximity of a touch device **38** to a conductive sense electrode **33**. The proximity sensing device includes two electrical switching means **30** and **31** connected together in series having a common node **48**, an input node **46**, and an output node **45**. A thin dielectric material **32** covers the sensing electrode **33** that is electrically connected to the common node **48**. A power supply **34** providing an approximately constant voltage is connected between reference ground and the input node **46**. The two electrical switches **30** and **31** gate the flow of charge from the power supply **34** to an integrating capacitor **37**. The voltage across the integrating capacitor **37** is translated to another voltage **58** by a high-impedance voltage amplifier **35**. The plates of the integrating capacitor **37** can be discharged by closing electrical switch **36** until the voltage across the integrating capacitor **37** is near zero. The electrical switches **30** and **31** are opened and closed in sequence but are never closed at the same time, although they may be opened at the same time as shown in FIG. **2**. Electrical switch **30** is referred to as the input switch; electrical switch **31** is referred to as the output switch; and, electrical switch **36** is referred to as the shorting switch.

The proximity sensing device shown in FIG. **2** is operated by closing and opening the electrical switches **30**, **31**, and **36** in a particular sequence after which the voltage output from the amplifier **58**, which is dependent on the proximity of a touch device **38**, is recorded. Sensor operation begins with all switches in the open state as shown in FIG. **2**. The shorting switch **36** is then closed for a sufficiently long time to reduce the charge residing on the integrating capacitor **37** to a low level. The shorting switch **37** is then opened. The input switch **30** is then closed thus allowing charge to flow between the power supply and the common node **48** until the voltage across the input switch **30** becomes zero. Charge Q will accumulate on the sensing electrode **33** according to

$$Q=V((e*A))/D \quad (1)$$

where V is the voltage of the power supply **34**, e is the permittivity of the dielectric sensing electrode cover **32** and the air gap between the cover and the touch device **38**, D is the thickness of this dielectric region, and A is the overlap area of the touch device **38** and the sensing electrode **33**. Therefore the amount of charge accumulating on the sensing electrode **33** will depend, among other things, on the area of overlap of the touch device **38** and the sensing electrode **33** and the distance between the touch device **38** and the sensing electrode **33**. The input switch **30** is opened after the voltage across it has become zero, or nearly so. Soon after input switch **30** is opened the output switch **31** is closed until the voltage across it is nearly zero. Closing the output switch **31** allows charge to flow between the sensing electrode **33** and the integrating capacitor **37** resulting in a voltage change across the integrating capacitor **37** according to:

$$\text{delta}V=(V-Vc)/(1+C*D/e*A) \quad (2)$$

where Vc is the voltage across the integrating capacitor **37** before the output switch **31** was closed, C is the capacitance of the integrating capacitor **37**, and A and D are equal to their values when input switch **30** was closed as shown in Equation 1. Multiple switchings of the input **30** and output **31** switches as described above produce a voltage on the integrating capacitor **37** that reflects the proximity of a touch device **38** to the sensing electrode **33**.

FIG. **3**A is a schematic diagram of the proximity sensor in which the shorting transistor **36** and the voltage-to-voltage translation device **35** are replaced by a resistor **40** and a current-to-voltage translation device **41**, respectively. The integrating function of capacitor **37** shown in FIG. **2** is, in this variation of the proximity sensor, carried out by the capacitor **39** shown in FIG. **3**A. Those skilled in the art will see that this variation of the proximity sensor produces a more linear output **58** from multiple switchings of the input and output switches, depending on the relative value of the resistor **40**. Alternatively, the resistor **40** can be replaced by a shorting switch **69** (cf. FIG. **3**B) to improve linearity. Although, the circuits shown in FIG. **3** provide a more linear output than the circuit shown in FIG. **2** the circuits of FIG. **3** generally require dual power supplies while the circuit of FIG. **2** requires only one.

The electrical switches shown in, FIG. **2** can be implemented with various transistor technologies: discrete, integrated, thin film, thick film, polymer, optical, etc. One such implementation is shown in FIG. **4**A where field effect transistors (FETs) are used as the input **30**, output **31**, and shorting **36** switches. The FETs are switched on and off by voltages applied to their gate terminals (**43**, **44**, and **55**). For the purpose of this description we will assume the FET is switched on when its gate voltage is logic 1 and switched off when its gate voltage is logic 0. A controller **42** is used to apply gate voltages as a function of time as shown in FIG. **4**B. In this example, a sequence of three pairs of pulses (**43** and **44**) are applied to the input and output transistor gates. Each pair of pulses **43** and **44** produces a voltage change across the integrating capacitor **37** as shown in Equation 2. The number of pulse pairs applied to input **43** and output **44** gates depends on the desired voltage across integrating capacitor **37**. In typical applications the number is between one and several hundred pulse-pairs.

FIG. **5** shows the proximity sensor circuitry appropriate for use in a system comprising an array of proximity sensors **47** as in a multi-touch surface system. The proximity sensor **47** consists of the input transistor **30**, the output transistor **31**, the sensing electrode **33**, the dielectric cover **32** for the sensing electrode **33**, and conductive traces **43**, **44**, **45**, and **46**. The conductive traces are arranged so as to allow the proximity sensors **47** comprising a 2D array to be closely packed and to share the same conductive traces, thus reducing the number of wires needed in a system. FIG. **6** shows an example of such a system where the input nodes **46** of all proximity sensors are connected together and connected to a power supply **34**. The output nodes **45** of all proximity sensors are connected together and connected to a single integrating capacitor **37**, a single shorting transistor **36**, and a single voltage-to-voltage amplifier **35**. In this implementation, a single proximity sensor **47** is enabled at a time by applying a logic 1 signal first to its input gate **43** and then to its output gate **44**. This gating of a single proximity sensor **47** one at a time is done by input gate controller **50** and output gate controller **51**. For example, to enable the proximity sensor **47** in the lower right corner the input gate controller **50** would output a logic one pulse on conductive trace **43***a*. This is followed by a logic one pulse on conductive trace **44***h* produced by output gate controller **51**. Repetition of this pulse as shown in FIG. **4**B would cause charge to build up on integrating capacitor **37** and a corresponding voltage to appear at the output of the amplifier **58**. The entire array of proximity sensors **47** is thus scanned by enabling a single sensor at a time and recording its output.

FIG. **7**A is a schematic of typical circuitry useful for converting the proximity sensor output **58** to a digital code appropriate for processing by computer. The proximity sensor output **58** is typically non-zero even when there is no touch device (e.g., ref. no. **38** in FIG. **2**) nearby. This non-zero signal is due to parasitic or stray capacitance present at the common node **48** of the proximity sensor and is of relatively constant value. It is desirable to remove this non-zero background signal before converting the sensor output **58** to a digital code. This is done by using a differential amplifier **64** to subtract a stored record of the background signal **68** from the sensor output **58**. The resulting difference signal **65** is then converted to a digital code by an ADC (analog to digital converter) **60** producing a K-bit code **66**. The stored background signal is first recorded by sampling the array of proximity sensors **47** (FIG. **6**) with no touch devices nearby and storing a digital code specific for each proximity sensor **47** in a memory device **63**. The particular code corresponding to the background signal of each proximity sensor is selected by an M-bit address input **70** to the memory device **63** and applied **69** to a DAC (digital to analog converter) **61**.

The 2D array of proximity sensors **47** shown in FIG. **6** can be connected in groups so as to improve the rate at which the entire array is scanned. This is illustrated in FIG. **8** where the groups are arranged as columns of proximity sensors. In this approach, the input nodes of the proximity sensors are connected together and connected to a power supply **34**, as in FIG. **6**. The output gates **44** are also connected in the same way. However, the input gates **43** are now all connected together and the output nodes **45** are connected to only those proximity sensors **47** within a row and to a dedicated voltage amplifier **35**. With this connection method, all of the proximity sensors in a column are enabled at a time, thus reducing the time to scan the array by a factor N, where N is the number of proximity sensors in a group. The outputs **58***a-h* could connect to dedicated converter circuitry as shown in FIG. **7**A or alternatively each output **58***a-h* could be converted one at a time using the circuitry shown in FIG. **7**B. In this figure, the output signals from each group **58***a-h* are selected one at a time by multiplexer **62** and applied to the positive input of the differential amplifier **64**. With this later approach, it is assumed that the ADC **60** conversion time is much faster than the sensor enable time, thus providing the suggested speed up in sensor array scanning.

FIG. **9** shows a typical circuit useful for the control of the proximity sensor's output gate **44**. It consists of three input signals **75**, **76**, **78** and two output signals **44**, **77**. The output gate signal **44** is logic 1 when both inputs to AND gate **79** are logic 1. The AND input signal **77** becomes logic 1 if input signal **76** is logic 1 when input signal **78** transitions from logic 0 to logic 1, otherwise it remains logic 0. A linear array of these circuits **81** can be connected end-to-end to enable the output gates of a single group of proximity sensors at a time as shown in FIG. **8**.

FIG. **10** shows a cover for the multi-touch surface **89** that permits the system to be sensitive to pressure exerted by non-conducting touch objects (e.g., gloved fingers) contacting the multi-touch surface. This cover comprises a deformable dielectric touch layer **85**, a deformable conducting layer **86**, and a compliant dielectric layer **87**. The touch surface **85** would have a symbol set printed on it appropriate for a specific application, and this surface could be removed and replaced with another one having a different symbol set. The conducting layer **86** is electrically connected **88** to the reference ground of the proximity sensor's power supply **34**. When a touch object presses on the top surface **85** it causes the conducting surface **86** under the touch device to move closer to the sensing electrode **33** of the proximity sensor. This results in a change in the amount of charge stored on the sensing electrode **33** and thus the presence of the touch object can be detected. The amount of charge stored will depend on the pressure exerted by the touch object. More pressure results in more charge stored as indicated in Equation 1.

To obtain a softer touch surface on the multi-touch device a thicker and more, compliant dielectric cover could be used. However, as the dielectric thickness increases the effect of the touch device on the sensing electrodes **33** spreads out thus lowering spatial resolution. A compliant anisotropically-conducting material can be used to counter this negative effect while also providing a soft touch surface. FIG. **11** shows a cover in which a compliant anisotropically-conducting material **90** is set between a thin dielectric cover **85** and the sensing electrodes **33**. If the conductivity of the compliant material **90** is oriented mostly in the vertical direction, the image formed by a touch device on the surface **85** will be translated without significant spreading to the sensing electrodes **33**, thus preserving spatial resolution while providing a compliant touch surface.

FIG. **12** shows a cross section of a multi-touch surface that senses both the proximity and pressure of a touch device. The touch layer **85** is a thin dielectric that separates touch devices from the sensing electrodes **33**. Proximity sensing is relative to this surface. The electrodes **33** and associated switches and conductors are fabricated on a compliant material **89** which is attached to a rigid metal base **92**. The metal base **92** is electrically connected **88** to the reference ground of the proximity sensor's power supply **34**. When a touch device presses on the touch surface **85** it causes the sensing electrodes **33** directly below to move closer to the rigid metal base **92**. The distance moved depends on the pressure applied and thus the pressure exerted by a touch device can be detected as described before.

To illustrate typical properties of hand contacts as they appear in proximity images, FIGS. **13-15** contain sample images captured by a prototype array of parallelogram-shaped electrodes. Shading of each electrode darkens to indicate heightened proximity signals as flesh gets closer to the surface, compresses against the surface due to hand pressure, and overlaps the parallelogram more completely. Note that the resolution of these images is in no way intended to limit the scope of the invention, since certain applications such as handwriting recognition will clearly require finer electrode arrays than indicated by the electrode size in these sample images. In the discussion that follows, the proximity data measured at one electrode during a particular scan cycle constitutes one "pixel" of the proximity image captured in that scan cycle.

FIG. **13** shows a right hand flattened against the surface with fingers outstretched. At the far left is the oblong thumb **201** which tends to point off at about 120-degrees. The columnar blobs arranged in an arc across the top of the image are the index finger **202**, middle finger **203**, ring finger **204** and pinky finger **205**. Flesh from the proximal finger joint, or proximal phalanges **209**, will appear below each fingertip if the fingers are fully extended. The inner **207** and outer **206** palm heels cause the pair of very large contacts across the bottom of the image. Forepalm calluses **213** are visible at the center of the hand if the palm is fully flattened. This image shows that all the hand contacts are roughly oval-shaped, but they differ in pressure, size, orientation, eccentricity and spacing relative to one another. This image includes all of the hand parts which can touch the surface from the bottom of one hand but in many instances only a few of these parts will be touching the surface, and the fingertips may roam widely in relation to the palms as fingers are flexed and extended.

FIG. **14** shows another extreme in which the hand is partially closed. The thumb **201** is adducted toward the fingertips **202-208** and the fingers are flexed so the fingertips come down normal instead of tangential to the surface. The height and intensity of fingertip contacts is lessened somewhat because the boney tip rather than fleshy pulp pad is actually touching the surface, but fingertip width remains the same. Adjacent fingertips **202-205** and thumb **201** are so close together as to be distinguishable only by slight proximity valleys **210** between them. The proximal phalange finger joints are suspended well above the surface and do not appear in the image, nor do the forepalm calluses. The palm heels **206**, **207** are somewhat shorter since only the rear of the palm can touch the surface when fingers are flexed, but the separation between them is unchanged. Notice that the proximity images are uncluttered by background objects. Unlike optical images, only conductive objects within a few millimeters of the surface show up at all.

FIG. **15** is a proximity image of a right hand in a pen grip configuration. The thumb **201** and index fingertip **202** are pinched together as if they were holding a pen but in this case they are touching the surface instead. Actually the thumb and index finger appear the same here as in FIG. **14**. However, the middle **203**, ring **204**, and pinky **205** fingers are curled under as if making a fist, so the knuckles from the top of the fingers actually touch the surface instead of the finger tips. The curling under of the knuckles actually places them behind the pinched thumb **201** and index fingertip **202** very close to the palm heels **206**, **207**. The knuckles also appear larger than the curled fingertips of FIG. **14** but the same size as the flattened fingertips in FIG. **13**. These differences in size and arrangement will be measured by the pen grip detector **17** to distinguish this pen grip configuration from the closed and flattened hand configurations.

FIG. **16** represents the data flow within the contact tracking and identification module **10**. The image segmentation process **241** takes the most recently scanned proximity image data **240** and segments it into groups of electrodes **242** corresponding to the distinguishable hand parts of FIG. **13**. The filtering and segmentation rules applied in particular regions of the image are partially determined by feedback of the estimated hand offset data **252**. The image segmentation process **241** outputs a set of electrode group data structures **242**

which are parameterized by fitting an ellipse to the positions and proximity measurements of the electrodes within each group.

The path tracking process **245** matches up the parameterized electrode groups **242** with the predicted continuations of contact path data structures **243** extracted from previous images. Such path tracking ensures continuity of contact representation across proximity images. This makes it possible to measure the velocity of individual hand contacts and determine when a hand part lifts off the surface, disappearing from future images. The path tracking process **245** updates the path positions, velocities, and contact geometry features from the parameters of the current groups **242** and passes them on to the contact identification processes **247** and **248**. For notational purposes, groups and unidentified paths will be referred to by data structure names of the form Gi and Pi respectively, where the indices i are arbitrary except for the null group G0 and null path P0. Particular group and path parameters will be denoted by subscripts to these structure names and image scan cycles will be denoted by bracketed indices, so that, for example, $P2_x[n]$ represents the horizontal position of path 2 in the current proximity image, and $P2_x[n-1]$ represents the position in the previous proximity image. The contact identification system is hierarchically split into a hand identification process **247** and within-hand finger and palm identification process **248**. Given a hand identification for each contact, the finger and palm identification process **248** utilizes combinatorial optimization and fuzzy pattern recognition techniques to identify the part of the hand causing each surface contact. Feedback of the estimated hand offset helps identify hand contacts when so few contacts appear in the image that the overall hand structure is not apparent.

The hand identification process **247** utilizes a separate combinatorial optimization algorithm to find the assignment of left or right hand identity to surface contacts which results in the most biomechanically consistent within-hand identifications. It also receives feedback of the estimated hand and finger offsets **252**, primarily for the purpose of temporarily storing the last measured hand position after fingers in a hand lift off the surface. Then if the fingers soon touch back down in the same region they will more likely receive their previous hand identifications.

The output of the identification processes **247** and **248** is the set of contact paths with non-zero hand and finger indices attached. For notational purposes identified paths will be referred to as F0 for the unidentified or null finger, F1 for the thumb **201**, F2 for the index finger **202**, F3 for the middle finger **203**, F4 for the ring finger **204**, F5 for the pinky finger **205**, F6 for the outer palm heel **206**. F7 for the inner palm heel **207**, and F8 for the forepalm calluses **208**. To denote a particular hand identity this notation can be prefixed with an L for left hand or R for right hand, so that, for example, RF2 denotes the right index finger path. When referring to a particular hand as a whole. LH denotes the left hand and RH denotes the right hand. In the actual algorithms left hand identity is represented by a −1 and right hand by +1, so it is easy to reverse the handedness of measurements taken across the vertical axis of symmetry.

It is also convenient to maintain for each hand a set of bitfield data registers for which each bit represents touchdown, continued contact or liftoff of a particular finger. Bit positions within each bit field correspond to the hand part indices above. Such registers can quickly be tested with a bit mask to determine whether a particular subset of fingers has touched down. Alternatively, they can be fed into a lookup table to find the input events associated with a particular finger chord (combination of fingers). Such finger identity bitfields are needed primarily by the synchronization detector **14** and chord motion recognizer **18**.

The last process within the tracking and identification subsystem is the hand position estimator **251**, which as described above provides biasing feedback to the identification and segmentation processes. The hand position estimator is intended to provide a conservative guess **252** of lateral hand position under all conditions including when the hand is floating above the surface without touching. In this case the estimate represents a best guess of where the hand will touch down again. When parts of a hand are touching the surface, the estimate combines the current position measurements of currently identified hand parts with past estimates which may have been made from more or less reliable identifications.

The simplest but inferior method of obtaining a hand position measurement would be to average the positions of all the hand's contacts regardless of identity. If hand parts **201-207** were all touching the surface as in FIG. **13** the resulting centroid would be a decent estimate, lying somewhere under the center of the palm since the fingers and palm heels typically form a ring around the center of the palm. However, consider when only one hand contact is available for the average. The estimate would assume the hand center is at the position of this lone contact, but if the contact is from the right thumb the hand center would actually be 4-8 cm to the right, or if the contact is from a palm heel the hand center is actually 4-6 cm higher, or if the lone contact is from the middle finger the hand center should actually be actually 4-6 cm lower.

FIG. **17** shows the detailed steps within the hand position estimator **251**. The steps must be repeated for each hand separately. In a preferred embodiment, the process utilizes the within-hand contact identifications (**250**) to compute (step **254**) for each contact an offset between the measured contact position ($Fi_x[n]$, $Fi_y[n]$) and the default position of the particular finger or palm heel (Fi_{defx}, Fi_{defy}) with hand part identity i. The default positions preferably correspond to finger and palm positions when the hand is in a neutral posture with fingers partially closed, as when resting on home row of a keyboard. Step **255** averages the individual contact offsets to obtain a measured hand offset, ($H_{mox}[n]$, $H_{moy}[n]$):

$$H_{mox}[n] = \frac{\sum_{i=1}^{i=7} Fi_{mow}[n](Fi_x[n] - Fi_{defx})}{\sum_{i=1}^{i=7} Fi_{mow}[n]} \tag{3}$$

$$H_{moy}[n] = \frac{\sum_{i=1}^{i=7} Fi_{mow}[n](Fi_y[n] - Fi_{defy})}{\sum_{i=1}^{i=7} Fi_{mow}[n]} \tag{4}$$

Preferably the weighting $Fi_{mow}[n]$ of each finger and palm heel is approximately its measured total proximity, i.e., $Fi_{mow}[n]=Fi_z[n]$. This ensures that lifted fingers, whose proximity is zero, have no influence on the average, and that contacts with lower than normal proximity, whose measured positions and identities are less accurate, have low influence. Furthermore, if palm heels are touching, their large total proximities will dominate the average. This is beneficial because the palm heels, being immobile relative to the hand center compared to the highly flexible fingers, supply a more reliable indication of overall hand position. When a hand is not touching the surface, i.e., when all proximities are zero, the measured

offsets are set to zero. This will cause the filtered hand position estimate below to decay toward the default hand position.

As long as the contact identifications are correct, this hand position measurement method eliminates the large errors caused by assuming lone contacts originate from the center of the hand. Flexing of fingers from their default positions will not perturb the measured centroid more than a couple centimeters. However, this scheme is susceptible to contact misidentification, which can cause centroid measurement errors of up to 8 cm if only one hand part is touching. Therefore, the current measured offsets are not used directly, but are averaged with previous offset estimates ($H_{eox}[n-1]$, $H_{eoy}[n-1]$) using a simple first-order autoregressive filter, forming current offset estimates ($H_{eox}[n]$, $H_{eoy}[n]$).

Step **256** adjusts the filter pole $H_{oa}[n]$ according to confidence in the current contact identifications. Since finger identifications accumulate reliability as more parts of the hand contact the surface one simple measure of identification confidence: is the number of fingers which have touched down from the hand since the hand last left the surface. Contacts with large total proximities also improve identification reliability because they have strong disambiguating features such as size and orientation. Therefore $H_{oa}[n]$ is set roughly proportional to the maximum finger count plus the sum of contact proximities for the hand. $H_{oa}[n]$ must of course be normalized to be between zero and one or the filter will be unstable. Thus when confidence in contact identifications is high, i.e., when many parts of the hand firmly touch the surface, the autoregressive filter favors the current offset measurements. However, when only one or two contacts have reappeared since hand liftoff, the filter emphasizes previous offset estimates in the hope that they were based upon more reliable identifications.

The filtered offsets must also maintain a conservative estimate of hand position while the hand is floating above the surface for optimal segmentation and identification as the hand touches back down. If a hand lifts off the surface in the middle of a complex sequence of operations and must, quickly touch down again, it will probably touch down close to where it lifted off. However, if the operation sequence has ended, the hand is likely to eventually return to the neutral posture, or default position, to rest. Therefore, while a hand is not touching the surface, $H_{oa}[n]$ is made small enough that the estimated offsets gradually decay to zero at about the same rate as a hand lazily returns to default position.

When $H_{oa}[n]$ is made small due to low identification confidence, the filter tracking delay becomes large enough to lag behind a pair of quickly moving fingers by several centimeters. The purpose of the filter is to react slowly to questionable changes in contact identity, not to smooth contact motion. This motion tracking delay can be safely eliminated by adding the contact motion measured between images to the old offset estimate. Step **257** obtains motion from the average, ($H_{nvx}[n]$, $H_{nvy}[n]$) of the current contact velocities:

$$H_{mvx}[n] = \frac{\sum_{i=1}^{i=7} Fi_{mow}[n]Fi_{vx}[n]}{\sum_{i=1}^{i=7} Fi_{mow}[n]} \tag{5}$$

-continued

$$H_{mvy}[n] = \frac{\sum_{i=1}^{i=7} FI_{mow}[n]Fi_{vy}[n]}{\sum_{i=1}^{i=7} Fi_{mow}[n]} \tag{6}$$

The current contact velocities. ($Fi_{vx}[n]$, $Fi_{vy}[n]$), are retrieved from the path tracking process **245**, which measures them independent of finger identity. Step **258** updates the estimated hand offsets ($H_{eox}[n]$, $H_{eoy}[n]$) using the complete filter equations:

$$H_{eox}[n]=H_{oa}[n]H_{mox}[n]+(1-H_{oa}[n])(H_{eox}[n-1]+H_{mox}[n]\Delta t) \tag{7}$$

$$H_{eoy}[n]=H_{oa}[n]H_{moy}[n]+(1-H_{oa}[n])(H_{eoy}[n-1]+H_{moy}[n]\Delta t) \tag{8}$$

Finally, to provide a similarly conservative estimate of the positions of particular fingers step **259** computes individual finger offsets ($Fi_{eox}[n]$, $Fi_{eoy}[n]$) from the distance between identified contacts and their corresponding default finger positions less the estimated hand offsets. For each identifiable contact i, the offsets are computed as:

$$Fi_{eox}[n]=H_{oa}[n](H_{mox}[n]+Fi_x[n]-Fi_{defx})+(1-H_{oa}[n])(Fi_{eox}[n-1]+Fi_{vx}[n]\Delta t) \tag{9}$$

$$FI_{eoy}[n]=H_{oa}[n](H_{moy}[n]+Fi_y[n]-Fi_{defy})+(1-H_{oa}[n])(Fi_{eoy}[n-1]+Fi_{vy}[n]\Delta t) \tag{10}$$

These finger offsets reflect deviations of finger flexion and extension from the neutral posture. If the user places the fingers in an extreme configuration such as the flattened hand configuration, the collective magnitudes of these finger offsets can be used as an indication of user hand size and finger length compared to the average adult.

The parameters ($H_{eox}[n]$, $H_{eoy}[n]$) and ($Fi_{eox}[n]$, $Fi_{eoy}[n]$) for each hand and finger constitute the estimated hand and finger offset data **252**, which is fed back to the segmentation and identification processes during analysis of the next proximity image. If the other processes need the estimate in absolute coordinates, they can simply add (step **260**) the supplied offsets to the default finger positions, but in many cases the relative offset representation is actually more convenient.

It should be clear to those skilled in the art that many improvements can be made to the above hand position estimation procedure which remain well within the scope of this invention, especially in the manner of guessing the position of lifted hands. One improvement is to make the estimated hand offsets decay toward zero at a constant speed when a hand is lifted rather than decay exponentially. Also, the offset computations for each hand have been independent as described so far. It is actually advantageous to impose a minimum horizontal separation between the estimated left hand position and estimated right hand position such that when a hand such as the right hand slides to the opposite side of the board while the other hand is lifted, the estimated position of the other hand is displaced. In this case the estimated position of the lifted left hand would be forced from default to the far left of the surface, possibly off the surface completely. If the right hand is lifted and the left is not, an equation like the following can be applied to force the estimated right hand position out of the way:

$$Rh_{eox}[n]:=\min(RH_{eox}[n],(LF1_{defx}-RF1_{defx})+Lh_{eox}[n]+\text{min_hard_sep} \tag{11}$$

where ($LF1_{defx}$–$RF1_{defx}$) is the default separation between left and right thumbs, is the minimum horizontal separation to be imposed, and $LH_{eox}[n]$ is the current estimated offset of the left hand.

FIG. **18** represents the data flow within the proximity image segmentation process **241**. Step **262** makes a spatially smoothed copy **263** of the current proximity image **240** by passing a two-dimensional diffusion operator or Gaussian kernel over it. Step **264** searches the smoothed image **263** for local maximum pixels **265** whose filtered proximity exceeds a significance threshold and exceeds the filtered proximities of nearest neighbor pixels. The smoothing reduces the chance that an isolated noise spike on a single electrode will result in a local maximum-which exceeds the significance threshold, and consolidates local maxima to about one per distinguishable fleshy contact.

Process **268** then constructs a group of electrodes or pixels which register significant proximity around each local maximum pixel by searching outward from each local maximum for contact edges. Each electrode encountered before reaching a contact boundary is added to the local maximum's group. FIG. **19** shows the basic boundary electrode search pattern for an example contact boundary **274**. In this diagram, an electrode or image pixel lies at the tip of each arrow. The search starts at the local maximum pixel **276**, proceeds to the left pixels **277** until the boundary **274** is detected. The last pixel before the boundary **278** is marked as an edge pixel, and the search resumes to the right **279** of the local maximum pixel **276**. Once the left and right edges of the local maximum's row have been found, the search recurses to the rows above and below, always starting **281** in the column of the pixel in the previous row which had the greatest proximity. As the example illustrates, the resulting set of pixels or electrodes is connected in the mathematical sense but need not be rectangular. This allows groups to closely fit the typical oval-shape of flesh contacts without leaving electrodes out or including those from adjacent contacts.

If contacts were small and always well separated, edges could simply be established wherever proximity readings fell to the background level. But sometimes fingertips are only separated by a slight valley or shallow saddle point **210**. To segment adjacent fingertips the partial minima of these valleys must be detected and used as group boundaries. Large palm heel contacts, on the other hand, may exhibit partial minima due to minor nonuniformities in flesh proximity across the contact. If all electrodes under the contact are to be collected in a single group, such partial minima must be ignored. Given a hand position estimate the segmentation system can apply strict edge detection rules in regions of the image where fingertips and thumb are expected to appear but apply sloppy edge detection rules in regions of the image where palms are expected to, appear. This ensures that adjacent fingertips are not joined into a single group and that each palm heel is not broken into multiple groups.

Step **266** of FIG. **18** defines the positions of these segmentation regions using the hand position estimates **252** derived from analyses of previous images. FIG. **20**A shows the extent of the strict and sloppy segmentation regions while the hands are in their default positions, making estimated offsets for both hands zero. Plus signs in the diagram **252** indicate the estimated position of each finger and palm heel in each hand. Rectangular outlines in the lower corners represent the left **284** and right **286** sloppy segmentation regions where partial minima are largely ignored. The T-shaped region remaining is the strict segmentation region **282**, where proximity saddle points must serve as contact boundaries. As a preferred embodiment the sloppy regions are rectangular, their inner boundaries **285** are placed just inside of the columns where the index fingers **202** are expected to lie, and the upper boundaries **287** are placed at the estimated vertical levels of their respective thumbs **201**. The outer and lower boundaries of the sloppy regions are determined by the outside edges of the surface. Due to the decay in estimated hand offsets after hands leave the surface, the sloppy segmentation regions return to the positions shown after the hands have stayed off the surface a few seconds, regardless of hand position at liftoff. FIG. **20**B shows how the sloppy regions follow the estimated hand positions **252** as the right hand moves toward the upper left and the left hand moves toward the lower left. This ensures that the palms and only the palms fall in the sloppy regions as long as the hand position estimates are correct.

FIG. **20**C shows that the left sloppy region **284** is moved left off the surface entirely when the left hand is lifted off the surface and the right hand slides to the left side of the surface. This prevents the fingers of one hand from entering the sloppy segmentation region of the opposite hand. This effect is implemented by imposing a minimum horizontal separation between the sloppy regions and, should the regions get too close to one another, letting the hand with the most surface contacts override the estimated position of the hand with fewer contacts. FIG. **21** is a detailed flow chart of the edge tests which are applied at each searched electrode depending on whether the electrode is in a strict or sloppy segmentation region. Decision diamond **290** checks whether the unsmoothed proximity of the electrode is greater than the background proximity levels. If not, the electrode is labeled an edge electrode in step **304** regardless of the segmentation region or search direction, and in step **305** the search returns to the row maximum to recurse in another direction. If the unsmoothed proximity is significant farther tests are applied to the smoothed proximity of neighboring electrodes depending on whether decision diamond **292** decides the search electrode is in a sloppy or strict region.

If a strict region search is advancing horizontally within a row, decision diamond **306** passes to decision diamond **308** which tests whether the electrode lies in a horizontal or diagonal partial minimum with respect to its nearest neighbor electrodes. If so, a proximity valley between adjacent fingers has probably been detected, the electrode is labeled as an edge **314** and search resumes in other directions **305**. If not, the search continues on the next electrode in the row **302**. If a strict region search is advancing vertically to the next row, decision diamond **306** passes to decision diamond **310** which tests whether the electrode lies in a vertical partial minimum with respect to the smoothed proximity of its nearest neighbor electrodes. If so, a proximity valley between a finger and the thumb has probably been detected, the electrode is labeled as an edge **312** and search resumes in other directions **305**. If not, the search continues into the next row **302**. If decision diamond **294** determines that a sloppy region search is advancing horizontally within a row, stringent horizontal minimum tests are performed to check for the crease or proximity valley between the inner and outer palm heels. To qualify, the electrode must be more than about 2 cm horizontal distance from the originating local maximum, as checked by decision diamond **296**. Also the electrode must be part of a tall valley or partial horizontal minimum which extends to the rows above and below and the next-nearest neighbors within the row, as checked by decision diamond **298**. If so, the electrode is labeled as an edge **300** and search recurses in other directions **305**. All other partial minima within the sloppy regions are ignored, so the search continues **302** until a background level edge is reached on an upcoming electrode.

In sloppy segmentation regions it is possible for groups to overlap significantly because partial minima between local maxima do not act as boundaries. Typically when this happens the overlapping groups are part of a large fleshy contact such as a palm which, even after smoothing, has multiple local maxima. Two groups are defined to be overlapping if the search originating local maximum electrode of one group is also an element of the other group. In the interest of presenting only one group per distinguishable fleshy contact to the rest of the system, step **270** of FIG. **18** combines overlapping groups into single supergroups before parameter extraction. Those skilled in the art will realize that feedback from high-level analysis of previous images can be applied in various alternative ways to improve the segmentation process and still lie well within the scope of this invention. For example, additional image smoothing in sloppy segmentation regions could consolidate each palm heel contact into a single local maximum which would pass strict segmentation region boundary tests. Care must be taken with this approach however, because too much smoothing can cause finger pairs which unexpectedly enter sloppy palm regions to be joined into one group. Once a finger pair is joined the finger identification process **248** has no way to tell that the fingertips are actually not a single palm heel, so the finger identification process will be unable to correct the hand position estimate or adjust the sloppy regions for proper segmentation of future images.

More detailed forms of feedback than the hand position estimate can be utilized as well. For example, the proximal phalanges (**209** in FIG. **13**) are actually part of the finger but tend to be segmented into separate groups than the fingertips by the vertical minimum test **310**. The vertical minimum test is necessary to separate the thumb group from index fingertip group in the partially closed FIG. **14** and pen grip FIG. **15** hand configurations. However, the proximal phalanges of flattened fingers can be distinguished from a thumb behind a curled fingertip by the fact that it is very difficult to flatten one long finger without flattening the other long fingers. To take, advantage of this constraint, a flattened finger flag **267** is set whenever two or more of the contacts identified as index through pinky in previous images are larger than normal, reliably indicating that fingertips are flattening. Then decision diamond **310** is modified during processing of the current image to ignore the first vertical minimum encountered during search of rows below the originating local minimum **276**. This allows the proximal phalanges to be included in the fingertip group but prevents fingertip groups from merging with thumbs or forepalms. The last step **272** of the segmentation process is to extract shape, size, and position parameters from each electrode group. Group position reflects hand contact position and is necessary to determine finger velocity. The total group proximity, eccentricity, and orientation are used by higher level modules to help distinguish finger, palm, and thumb contacts.

Provided G_e is the set of electrodes in group G, e_z is the unsmoothed proximity of an electrode or pixel e, and e_x and e_y are the coordinates on the surface of the electrode center in centimeters, to give a basic indicator of group position, the proximity-weighted center, or centroid, is computed from positions and proximities of the group's electrodes:

$$G_z = \sum_{e \in G_E} e_z \tag{12}$$

-continued

$$G_x = \sum_{e \in G_E} \frac{e_z e_x}{G_z} \tag{13}$$

$$G_y = \sum_{e \in G_E} \frac{e_z e_y}{G_z} \tag{14}$$

Note that since the total group proximity G_z integrates proximity over each pixel in the group, it depends upon both of the size of a hand part, since large hand parts tend to cause groups with more pixels, and of the proximity to or pressure on the surface of a hand part.

Since most groups are convex, their shape is well approximated by ellipse parameters. The ellipse fitting procedure requires a unitary transformation of the group covariance matrix G_{eov} of second moments Q_{xx}, Q_{xy}, G_{yy}:

$$G_{cov} = \begin{bmatrix} G_{xx} & G_{xy} \\ G_{yz} & G_{yy} \end{bmatrix} \tag{15}$$

$$G_{xx} = \sum_{e \in G_E} e_z (G_x - e_x)^2 \tag{16}$$

$$G_{yx} = G_{xy} = \sum_{e \in G_E} e_z (G_x - e_x)(G_y - e_y) \tag{17}$$

$$G_{yy} = \sum_{e \in G_E} e_x (G_y - e_y)^2 \tag{18}$$

The eigenvalues λ_0 and λ_1 of the covariance matrix G_{eov} determine the ellipse axis lengths and orientation G_θ:

$$G_{major} = \sqrt{\lambda_0} \tag{19}$$

$$G_{minor} = \sqrt{\lambda_1} \tag{20}$$

$$G_\theta = \arctan\left(\frac{\lambda_0 - G_{xx}}{G_{xy}}\right) \tag{21}$$

where G_θ is uniquely wrapped into the range)(0,180°).

For convenience while distinguishing fingertips from palms at higher system levels, the major and minor axis lengths are converted via their ratio into an eccentricity $G_\in$:

$$G_\varepsilon = \frac{G_{major}}{G_{minor}} \tag{22}$$

Note that since the major axis length is always greater than or equal to the minor axis length, the eccentricity will always be greater than or equal to one. Finally, the total group proximity is empirically renormalized so that the typical curled fingertip will have a total proximity around one:

$$G_z := \frac{G_z}{Z_{averageFingertip}} \tag{23}$$

On low resolution electrode arrays, the total group proximity G_z is a more reliable indicator of contact size as well as finger pressure than the fitted ellipse parameters. Therefore, if proximity images have low resolution, the orientation and

eccentricity of small contacts are set to default values rather than their measured values, and total group proximity G_z is used as the primary measure of contact size instead of major and minor axis lengths.

FIG. **22** shows the steps of the path tracking process, which chains together those groups from successive proximity images which correspond to the same physical hand contact. To determine where each hand part has moved since the last proximity image, the tracking process must decide which current groups should be matched with which existing contact paths. As a general rule, a group and path arising from the same contact will be closer to one another than to other groups and paths. Also, biomechanical constraints on lateral finger velocity and acceleration limit how far a finger can travel between images. Therefore a group and path should not be matched unless they are within a distance known as the tracking radius of one another. Since the typical lateral separation between fingers is greater than the tracking radius for reasonable image scan rates touchdown and liftoff are easily detected by the fact that touchdown usually causes a new group to appear outside the tracking radii of existing paths, and liftoff will leave an active path without a group within its tracking radius. To prevent improper breaking of paths at high finger speeds each path's tracking radius P_{rtruck} can be made dependent on its existing speed and proximity.

The first step **320** predicts the current locations of surface contacts along existing trajectories using path positions and velocities measured from previous images. Applying previous velocity to the location prediction improves the prediction except when a finger suddenly starts or stops or changes direction. Since such high acceleration events occur less often than zero acceleration events, the benefits of velocity-based prediction outweigh the potentially bad predictions during finger acceleration. Letting $P_x[n-1]$, $P_y[n-1]$ be the position of path P from time step n−1 and $P_{vx}[n-1]$. $P_{vy}[n-1]$ the last known velocity, the velocity-predicted path continuation is then:

$$P_{predx}[n]=P_x[n-1]+\Delta t P_{vx}[n-1] \tag{24}$$

$$P_{predy}[n]=P_y[n-1]+\Delta t P_{vy}[n-1] \tag{25}$$

Letting the set of paths active in the previous image be PA, and let the set electrode groups constructed in the current image be G, step **322** finds for each group Gk the closest active path and records the distance to it:

$$?????? \tag{26}$$

$$Gk\ \text{closest}Pdist\ 2=\min Pl\ PA\ d\ 2(Gk,Pl)Gk\ G \tag{27}$$

where the squared Euclidean distance is an easily computed distance metric:

$$a^2(Gk,Pl)=(Gk_x-Pl_{predx})^2+(Gk_y-Pl_{predy})^2 \tag{28}$$

Step **324** then finds for each active path Pl, the closest active group and records the distance to it:

$$9\ Pl\ \text{closest}G=\arg\min Gk\ G\ d\ 2(Gk,Pl)Pl\ PA \tag{29}$$

$$Pl\ \text{closest}Gdist\ 2=\min Gk\ G\ d\ 2(Gk,Pl)Pl\ PA \tag{30}$$

In step **326**, an active group Gk and path Pl are only paired with one another if they are closest to one another, i.e., $Gk_{closestP}$ and $Pl_{closestG}$ refer to one another, and the distance between them is less than the tracking radius. All of the following conditions must hold:

$$Gk_{closestP}\equiv Pl \tag{31}$$

$$Pl_{closestG}\equiv Gk \tag{32}$$

$$Pl_{closestGdist2}<Pl_{mack2} \tag{33}$$

To aid in detection of repetitive taps of the same finger, it may be useful to preserve continuity of path assignment between taps over the same location. This is accomplished in step **334** by repeating steps **322-326** using only groups which were left unpaired above and paths which were deactivated within the last second or so due to finger liftoff.

In step **336**, any group which has still not be paired with an active or recently deactivated path is allocated a new path, representing touchdown of a new finger onto the surface. In step **344**, any active path which cannot be so paired with a group is deactivated, representing hand part liftoff from the surface.

Step **346** incorporates the extracted parameters of each group into its assigned path via standard filtering techniques. The equations shown below apply simple autoregressive filters to update the path position ($P_x[n]$, $P_y[n]$, $P_z[n]$), velocity ($P_x[n]$, $P_y[n]$), and shape ($P_\theta[n]$, $P_\in[n]$) parameters from corresponding group parameters, but Kalman or finite impulse response filters would also be appropriate.

If a path P has just been started by group G at time step n, i.e., a hand part has just touched down, its parameters are initialized as follows:

$$P_x[n]=G_x \tag{34}$$

$$P_y[n]=G_y \tag{35}$$

$$P_z[n]=G_z \tag{36}$$

$$P_\theta[n]=G_\theta \tag{37}$$

$$P_\in[n]=G_\in \tag{38}$$

$$P_{vx}[n]=0 \tag{39}$$

$$P_{vy}[n]=0 \tag{40}$$

$$P_x[n]=G_z/\Delta t \tag{41}$$

else if group G is a continuation of active path P [n−1] to time step n:

$$P_x[n]=G_\alpha G_x+(1-G_\alpha)(P_{predx}[n-1]) \tag{42}$$

$$P_y[n]=G_\alpha G_y+(1-G_\alpha)(P_{predy}[n-1]) \tag{43}$$

$$P_z[n]=G_\alpha G_z+(1-G_\alpha)(P_{predz}[n-1]) \tag{44}$$

$$P_\theta[n]=G_\alpha G_\theta+(1-G_\alpha)(P_\theta[n-1]) \tag{45}$$

$$P_\in[n]=G_\alpha G_\in+(1-G_\alpha)(P_\in[n-1]) \tag{46}$$

$$P_{vx}[n]=(P_x[n]-P_x[n-1])/\Delta t \tag{47}$$

$$P_{vy}[n]=(P_y[n]-P_y[n-1])/\Delta t \tag{48}$$

$$P_{vz}[n]=(P_z[n]-P_z[n-1])/\Delta t \tag{49}$$

It is also useful to compute the magnitude P_{speed} and angle P_{dir} from the velocity vector (P_{vx}, P_{vx}). Since the reliability of position measurements increases considerably with total proximity P_z, the low-pass filter pole G_α is decreased for groups with total proximities lower than normal. Thus when signals are weak, the system relies heavily on the previously established path velocity, but when the finger firmly touches the surface causing a strong, reliable signal, the system relies entirely on the current group centroid measurement.

The next process within the tracking module is contact identification. On surfaces large enough for multiple hands, the contacts of each hand tend to form a circular cluster, and the clusters tend to remain separate because users like to avoid entangling the fingers of opposite hands. Because the

arrangement of fingers within a hand cluster is independent of the location of and arrangement within the other hand's cluster, the contact identification system is hierarchically split. The hand identification process **247** first decides to which cluster each contact belongs. Then a within-cluster identification process **248** analyzes for each hand the arrangement of contacts within the hand's cluster, independent of the other hand's cluster. Because within-cluster or finger identification works the same for each hand regardless of how many hands can fit on the surface, it will be described first. The description below is for identification within the right hand. Mirror symmetry must be applied to some parameters before identifying left hand contacts.

FIG. **23** shows the preferred embodiment of the finger identification process **248**. For the contacts assigned to each hand this embodiment attempts to match contacts to a template of hand part attractor points, each attractor point having an identity which corresponds to a particular finger or palm heel. This matching between contact paths and attractors should be basically one to one but in the case that some hand parts are not touching the surface, some attractors will be left unfilled, i.e., assigned to the null path or dummy paths.

Step **350** initializes the locations of the attractor points to the approximate positions of the corresponding fingers and palms when the hand is in a neutral posture with fingers partially curled. Preferably these are the same default finger locations (Fi_{defx},Fi_{defy}) employed in hand offset estimation. Setting the distances and angles between attractor points from a half-closed hand posture allows the matching algorithm to perform well for a wide variety of finger flexions and extensions.

The resulting attractor points tend to lie in a ring as displayed by the crosses in FIG. **24**. The identities of attractor points **371**-**377** correspond to the identities of hand parts **201**-**207**. If the given hand is a left hand, the attractor ring must be mirrored about the vertical axis from that shown. FIG. **24** also includes line segments **380** forming the Voronoi cell around each attractor point. Every point within an attractor's Voronoi cell is closer to that attractor than any other attractor. When there is only one contact in the cluster and its features are not distinguishing, the assignment algorithm effectively assigns the contact to the attractor point of the Voronoi cell which the contact lies within. When there are multiple surface contacts in a hand cluster, they could all lie in the same Voronoi cell, so the assignment algorithm must perform a global optimization which takes into account all of the contact positions at once.

Alternative embodiments can include additional attractors for other hand part or alternative attractor arrangements for atypical hand configurations. For example, attractors for forepalm contacts can be placed at the center of the ring, but since the forepalms typically do not touch the surface unless the rest of the hand is flattened onto the surface as well, forepalm attractors should be weighted such that contacts are assigned to them only when no regular attractors are left unassigned.

For optimal matching accuracy the ring should be kept roughly centered on the hand cluster. Therefore step **352** translates all of the attractor points for a given hand by the hand's estimated position offset. The final attractor positions ($Aj_x[n]$, $Aj_y[n]$) are therefore given by:

$$Aj_x[n]=H_{eox}[n]+Fj_{defx} \tag{50}$$

$$Aj_y[n]=H_{eoy}[n]+Fj_{defy} \tag{51}$$

In alternative embodiments the attractor ring can also be rotated or scaled by estimates of hand rotation and size such as the estimated finger offsets, but care must be taken that wrong finger offset estimates and identification errors do not reinforce one another by severely warping the attractor ring.

Once the attractor template is in place, step **354** constructs a square matrix $[d_{ij}]$ of the distances in the surface plane from each active contact path Pi to each attractor point Aj. If there are fewer surface contacts than attractors, the null path P0, which has zero distance to each attractor, takes place of the missing contacts. Though any distance metric can be used, the squared Euclidean distance,

$$d_{ij}=(Aj_x[n]-Pi_x[n])^2+(Aj_y[n]-Pi_y[n]) \tag{52}$$

is preferred because it specially favors assignments wherein the angle between any pair of contacts is close to the angle between the pair of attractors assigned to those contacts. This corresponds to the biomechanical constraint that fingertips avoid crossing over one another, especially while touching a surface.

In step **356**, the distances from each contact to selected attractors are weighted according to whether the geometrical features of the given contact match those expected from the hand part that the attractor represents. Since the thumb and palm heels exhibit the most distinguishing geometrical features, weighting functions are computed for the thumb and palm heel attractors, and distances to fingertip attractors are unchanged. In a preferred embodiment, each weighting function is composed of several factor versus feature relationships such as those plotted approximately in FIG. **25**. Each factor is designed to take on a default value of 1 when its feature measurement provides no distinguishing information, take on larger values if the measured contact feature uniquely resembles the given thumb or palm hand part, and take on smaller values if the measured feature is inconsistent with the given attractor's hand part. The factor relationships can be variously stored and computed as lookup tables, piecewise linear functions, polynomials, trigonometric functions, rational functions, or any combination of these. Since assignment between a contact and an attractor whose features match is favored as the weighted distance between becomes smaller, the distances are actually weighted (multiplied) with the reciprocals of the factor relationships shown.

FIG. **25**A shows the right thumb and right inner palm heel orientation factor versus orientation of a contact's fitted ellipse. Orientation of these hand parts tends to be about 120°, whereas fingertip and outer palm heel contacts are usually very close to vertical)(90°), and orientation of the left thumb and left inner palm heel averages 60°. The right orientation factor therefore approaches a maximum at 120°. It approaches the default value of 1 at 0°, 90°, and 180° where orientation is inconclusive of identity, and reaches a minimum at 60°, the favored orientation of the opposite thumb or palm heel. The corresponding relationship for the left thumb and inner palm heel orientation factor is flipped about 90°.

FIG. **25**B approximately plots the thumb size factor. Since thumb size as indicated by total proximity tends to peak at two or three times the size of the typical curled fingertip, the thumb size factor peaks at these sizes. Unlike palm heels, thumb contacts can not be much larger than two or three times the default fingertip size, so the thumb factor drops back down for larger sizes. Since any hand part can appear small when touching the surface very lightly or just starting to touchdown, small size is not distinguishing, so the size factor defaults to 1 for very small contacts.

FIG. **25**C approximately plots the palm heel size factor. As more pressure is applied to the palms, the palm heel contacts can grow quite large, remaining fairly round as they do so. Thus the palm heel size factor is much like the thumb size factor except the palm factor is free to increase indefinitely.

However, fingertip contacts can grow by becoming taller as the fingers are flattened. But since finger width is constant, the eccentricity of an ellipse fitted to a growing fingertip contact increases in proportion to the height. To prevent flattened fingers from having a large palm factor, has little effect for palms, whose eccentricity remains near 1, but cancels the high proximities of flattened fingertips. Though directly using fitted ellipse width would be less accurate for low resolution electrode arrays, the above ratio basically captures contact width.

Another important distinguishing feature of the palm heels is that wrist anatomy keeps the centroids of their contacts separated from one other and from the fingers by several centimeters. This is not true of the thumb and fingertips, which can be moved within a centimeter of one another via flexible joints. The inter-palm separation feature is measured by searching for the nearest neighbor contact of a given contact and measuring the distance to the neighbor. As plotted approximately in FIG. **25**D, the palm separation factor quickly decreases as the separation between the contact and its nearest neighbor falls below a few centimeters, indicating that the given contact (and its nearest neighbor) are not palm heels. Unlike the size and orientation factors which only become reliable as the weight of the hands fully compresses the palms, the palm separation factor is especially helpful in distinguishing the palm heels from pairs of adjacent fingertips because it applies equally well to light, small contacts.

Once the thumb and palm weightings have been applied to the distance matrix, step **358** finds the one-to-one assignment between attractors and contacts which minimizes the sum of weighted; distances between each attractor and it's assigned contact. For notational purposes, let a new matrix $[c_{ij}]$ hold the weighted distances:

$$c_{ij}\begin{cases} d_{ij}/(Pi_{thumb_size_fact}Pi_{orient_fact}) & \text{if } j=1 \\ d_{ij} & \text{if } 2 \le j \le 5 \\ d_{ij}/(Pi_{palm_size_fact}Pi_{palm_sep_fact}) & \text{if } j=6 \\ d_{ij}/(Pi_{palm_size_fact}Pi_{palm_sep_fact}) & \text{if } j=7 \end{cases} \tag{53}$$

Mathematically the optimization can then be stated as finding the permutation $\{\pi_1, \ldots, \pi_7\}$ of integer hand part identities $\{1, \ldots, 7\}$ which minimizes:

$$\sum_{i=1}^{7} c_{i\pi_i} \tag{54}$$

where c_{ij} is the weighted distance from contact i to attractor j, and contact i and attractor j are considered assigned to one another when $\pi_i \equiv j$. This combinatorial optimization problem, known more specifically in mathematics as an assignment problem, can be efficiently solved by a variety of well-known mathematical techniques, such as branch and bound, localized combinatorial search, the Hungarian method, or network flow solvers. Those skilled in the art will recognize that this type of combinatorial optimization problem has a mathematically equivalent dual representation in which the optimization is reformulated as a maximization of a sum of dual parameters. Such reformulation of the above hand part identification method as the dual of attractor-contact distance minimization remains well within the scope of this invention.

To avoid unnecessary computation, decision diamond **360** ends the finger identification process at this stage if the hand assignment of the given contact cluster is only a tentative hypothesis being evaluated by the hand identification module **247**. However, if the given hand assignments are the final preferred hypothesis, further processes verify finger identities and compile identity statistics such as finger counts.

The identifications produced by this attractor assignment method are highly reliable when all five fingers are touching the surface or when thumb and palm features are unambiguous. Checking that the horizontal coordinates for identified fingertip contacts are in increasing order easily verifies that fingertip identities are not erroneously swapped. However, when-only two to four fingers are touching, yet no finger strongly exhibits thumb size or orientation features, the assignment of the innermost finger contact may wrongly indicate whether the contact is the thumb. In this case, decision diamond **362** employs a thumb verification process **368** to take further measurements between the innermost finger contact and the other fingers. If these further measurements strongly suggest the innermost finger contact identity is wrong, the thumb verification process changes the assignment of the innermost finger contact. Once the finger assignments are verified, step **364** compiles statistics about the assignments within each hand such as the number of touching fingertips and bitfields of touching finger identities. These statistics provide convenient summaries of identification results for other modules.

FIG. **26** shows the steps within the thumb verification module. The first **400** is to compute several velocity, separation, and angle factors for the innermost contact identified as a finger relative to the other contacts identified as fingers. Since these inter-path measurements presuppose a contact identity ordering, they could not have easily been included as attractor distance weightings because contact identities are not known until the attractor distance minimization is complete. For the factor descriptions below, let FI be the innermost finger contact, FN be the next innermost finger contact, FO be the outermost finger contact.

The separation between thumb and index finger is often larger than the separations between fingertips, but all separations tend to grow as the fingers are outstretched. Therefore an inner separation factor inner_separation_fact is defined as the ratio of the distance between the innermost and next innermost finger contacts to the average of the distances between other adjacent fingertip contacts, avg_separation: 12 inner separation fact min

$$innerseparationfact \approx \min\left(1, \frac{\sqrt{(FI_x - FN_x)^2 + (FI_y - FN_y)^2}}{avgseparation}\right) \tag{55}$$

The factor is clipped to be greater than one since an innermost separation less than the average can occur regardless of whether thumb or index finger is the innermost touching finger. In case there are only two finger contacts, a default average separation of 2-3 cm is used. The factor tends to become larger than one if the innermost contact is actually the thumb but remains near one if the innermost contact is a fingertip.

Since the thumb rarely moves further forward than the fingertips except when the fingers are curled into a fist, the angle between the innermost and next innermost finger contact can help indicate whether the innermost finger contact is the thumb. For the right hand the angle of the vector from the thumb to the index finger is most often 60°, though it ranges to 0° as the thumb moves forward and to 120° as the thumb

adducts under the palm. This is reflected in the approximate plot of the inner angle factor in FIG. **32**, which peaks at 60° and approaches 0 toward 0° and 120°. If the innermost finger contact is actually an index fingertip, the measured angle between innermost and next innermost contact will likely be between 30° and −60°, producing a very small angle factor.

The inner separation and angle factors are highly discriminating of neutral thumb postures, but users often exceed the above cited separation and angle ranges when performing hand scaling or rotation gestures. For instance, during an anti-pinch gesture, the thumb may start pinched against the index or middle fingertip, but then the thumb and fingertip slide away from one another. This causes the inner separation factor to be relatively small at the start of the gesture. Similarly, the thumb-index angle can also exceed the range expected by the inner angle factor at the beginning or end of hand rotation gestures, wherein the fingers rotate as if turning a screw. To compensate, the inner separation and angle factors are fuzzy OR'ed with expansion and rotation factors which are selective for symmetric finger scalings or rotations centered on a point between the thumb and fingertips.

When defined by the following approximate equation, the expansion factor peaks as the innermost and outermost finger contacts slide at approximately the same speed and in opposite directions, parallel to the vector between them:

$$expansionfact \approx -\sqrt{FI_{speed}[n] \times FO_{speed}[n] \times \cos\left(FI_{dir}[n] - \angle\left((FI[n], (FO[n])) \times \cos\left(FO_{dir}[n] - \angle(FI[n], FO[n])\right)\right)\right)} \quad (56)$$

$$\text{expansnsion_fact} := \max(0, \text{expansion_fact}) \quad (57)$$

$$\text{where } \angle(FI[n], FO[n]) \text{ is the angle between the fingers:} \quad (58)$$

$$(FI[n], FO[n]) = \arctan\left(\frac{FI_y[n] - FO_y[n]}{FI_x[n] - FO_x[n]}\right)$$

Translational motions of both fingers in the same direction produce negative factor values which are clipped to zero by the max operation. Computing the geometric rather than arithmetic mean of the innermost and outermost speeds aids selectivity by producing a large expansion factor only when speeds of both contacts are high.

The rotation factor must also be very selective. If the rotation factor was simply proportional to changes in the angle between innermost and outermost finger, it would erroneously grow in response to asymmetries in finger motion such as when the innermost finger starts translating downward while the outermost contact is stationary. To be more selective, the rotation factor must favor symmetric rotation about an imaginary pivot between the thumb and fingertips. The approximate rotation factor equation below peaks as the innermost and outermost finger move in opposite directions, but in this case the contacts should move perpendicular to the vector between them:

$$rotationfact = -\sqrt{FI_{speed}[n]FO_{speed}[n] \times \sin(FI_{dir}[n] - \angle(FI[n], FO[n])) \times \sin(FO_{dir}[n] - \angle(FI[n], FO[n]))} \quad (59)$$

$$\text{rotation_fact} := \max(0, \text{rotation_fact}) \quad (60)$$

Since motions which maximize this rotation factor are easy to perform between the opposable thumb and another finger but difficult to perform between two fingertips the rotation factor is a robust indicator of thumb presence.

Finally, a fuzzy logic expression (step **402**) combines these inter-contact factors with the thumb feature factors for the innermost and next innermost finger contacts. In a preferred embodiment, this fuzzy logic expression for the combined_thumb_fact takes the form:

$$\text{combined_thumb_fact} \approx (\text{inner_separation_fact} \times \text{angle_fact} + \text{expansion_fact} + \text{rotation_fact}) \times (FI_{orient_fact}/FN_{orient_fact}) \times (FI_{thumb_size_fact}/FN_{thumb_size_fact}) \quad (61)$$

The feature factor ratios of this expression attempt to compare the features of the innermost contact to current features of the next innermost contact, which is already known to be a fingertip. If the innermost contact is also a fingertip its features should be similar to the next innermost, causing the ratios to remain near one. However, thumb-like features on the innermost contact will cause the ratios to be large. Therefore if the combined thumb factor exceeds a high threshold, diamond **404** decides the innermost finger contact is definitely a thumb. If decision diamond **412** determines the contact is not already assigned to the thumb attractor **412**, step **414** shifts the contact assignment inward on the attractor ring to the thumb attractor. Otherwise, if decision diamond **406** determines that the combined thumb factor is less than a low threshold, the innermost contact is most definitely not the thumb. Therefore if decision diamond **408** finds the contact assigned to the thumb attractor, step **410** shifts the innermost contact assignment and any adjacent finger contacts outward on the attractor ring to unfill the thumb attractor. If the combined_thumb_fact is between the high and low threshold or if the existing assignments agree with the threshold decisions, step **413** makes no assignment changes.

The hand contact features and interrelationships introduced here to aid identification can be measured and combined in various alternative ways yet remain well within the scope of the invention. In alternative embodiments of the multi-touch surface apparatus which include raised, touch-insensitive palm rests, palm identification and its requisite attractors and factors may be eliminated. Geometrical parameters can be optimally adapted to measurements of individual user hand size taken while the hand is flattened. However, the attractor-based identification method already tolerates variations in a single person's finger positions due to finger flexion and extension which are as great or greater than the variations in hand size across adult persons. Therefore adaptation of the thumb and palm size factors to a person's average finger and palm heel proximities is more important than adaptation of attractor positions to individual finger lengths, which will only add marginal performance improvements.

As another example of an alternative method for incorporating these features and relationships into a hand contact identifier, FIG. **27** diagrams an alternative finger identification embodiment which does not include an attractor template. To order the paths from finger and palm contacts within a given hand **430**, step **432** constructs a two-dimensional matrix of the distances from each contact to the other contacts. In step **434**, a shortest path algorithm well known from the theory of network flow optimization then finds the shortest graph cycle connecting all the contact paths and passing through each once **434**. Since hand contacts tend to lie in a ring this shortest graph cycle will tend to connect adjacent contacts, thus establishing a sensible ordering for them.

The next step **438** is to pick a contact at an extreme position in the ring such as the innermost or outermost and test

whether it is a thumb (decision diamond **440**) or palm (decision diamond **442**). This can be done using contact features and fuzzy logic expressions analogous to those utilized in the thumb verification process and the, attractor weightings. If the innermost path is a thumb, step **444** concludes that contacts above are most likely fingertips, and contacts in the ring below the thumb are most likely palms. If (**442**) the innermost path is a palm heel, step **446** concludes the paths significantly above the innermost must be fingers while paths at the same vertical level should be palms. The thumb and palm tests are then repeated for the contacts adjacent in the ring to the innermost until any other thumb or palm contacts are found. Once any thumb and palm contacts are identified, step **448** identifies remaining fingertip contacts by their respective ordering in the ring and their relatively high vertical position.

Since this alternative algorithm does not include an attractor template to impose constraints on relative positions, the fuzzy verification functions for each contact may need to include measurements of the vertical position of the contact relative to other contacts in the ring and relative to the estimated hand offset. The attractor template embodiment is preferred over this alternative embodiment because the attractor embodiment more elegantly incorporates expected angles between contacts and the estimated hand offset into the finger identification process.

Hand identification is needed for multi-touch surfaces which are large enough to accomodate both hands simultaneously and which have the left and right halves of the surface joined such that a hand can roam freely across the middle to either half of the surface. The simplest method of hand identification would be to assign hand identity to each contact according to whether the contact initially touched down in the left or right half of the surface. However, if a hand touched down in the middle, straddling the left and right halves, some of the hand's contacts would end up assigned to the left hand and others to the right hand. Therefore more sophisticated methods which take into account the clustering properties of hand contacts must be applied to ensure all contacts from the same hand get the same identity. Once all surface contacts are initially identified, the path tracking module can reliably retain existing identifications as a hand slides from one side of the surface to the other.

The thumb and inner palm contact orientations and the relative thumb placement are the only contact features independent of cluster position which distinguish a lone cluster of right hand contacts from a cluster of left hand contacts. If the thumb is lifted off the surface, a right hand contact cluster appears nearly indistinguishable from a left hand cluster. In this case cluster identification must still depend heavily on which side of the board the cluster starts on, but the identity of contacts which recently lifted off nearby also proves helpful. For example, if the right hand moves from the right side to the middle of the surface and lifts off, the next contacts which appear in the middle will most likely be from the right hand touching back down, not from the left hand moving to the middle and displacing the right hand. The division between left and right halves of the surface should therefore be dynamic, shifting toward the right or left according to which hand was most recently near the middle. Since the hand offset estimates temporarily retain the last known hand positions after liftoff, such a dynamic division is implemented by tying the positions of left hand and right hand attractor templates to the estimated hard positions.

Though cases remain in which the user can fool the hand identification system with sudden placements of a hand in unexpected locations, the user may actually wish to fool the system in these cases. For example, users with only one hand free to use the surface may intentionally place the hand far onto the opposite half of the surface to access the chord input operations of the opposite hand. Therefore, when a hand cluster suddenly touches down well into the opposite half of the surface, it can safely be given the opposite halfs identity, regardless of its true identity. Arching the surface across the middle can also discourage users from sliding a hand to the opposite side by causing awkward forearm pronation should users do so.

FIG. **29** shows process details within the hand identification module **247**. Decision diamond **450** first determines whether the hand identification algorithm actually needs to be executed by checking whether all path proximities have stabilized. To maximize stability of the identifications, hand and finger identities need only be reevaluated when a new hand part touches down or disambiguating features of existing contacts become stronger. The contact size and orientation features are unreliable until the flesh fully compresses against the surface a few dozen milliseconds after initial surface contact. Therefore decision diamond **450** executes the hand identification algorithm for each proximity image in which a new contact appears and for subsequent proximity images in which the total proximity of any new contacts continues to increase. For images in which proximities of existing contacts have stabilized and no new contacts appear, path continuation as performed by the path tracking process **245** is sufficient to retain and extend (step **452**) the contact identifications computed from previous images.

Should the hand identification algorithm be invoked for the current image, the first step **453** is to define and position left and right hand attractor templates. These should be basically the same as the attractor templates (FIG. **24**, step **352**) used in within-hand identification, except that both left and right rings must now be utilized at once. The default placement of the rings relative to one another should correspond to the default left and right hand contact positions shown in FIG. **20**A. Each ring translates to follow the estimated position of its hand, just like the sloppy segmentation regions follow the hands in FIG. **20**B. Individual attractor points can safely be translated by their corresponding estimated finger offsets. Therefore the final attractor positions ($Aj_x[n]$, $Aj_y[n]$) for the left hand L and right hand H attractor rings are:

$$Laj_x[n]=Lh_{eox}[n]+LFj_{eox}[n]+Lfj_{defx} \tag{62}$$

$$Laj_y[n]=Lh_{eoy}[n]+LFj_{eoy}[n]+Lfj_{defy} \tag{63}$$

$$Raj_x[n]=Rh_{eox}[n]+RFj_{eox}[n]+Rfj_{defx} \tag{64}$$

$$Raj_y[n]=Rh_{eoy}[n]+RFj_{eoy}[n]+Rfj_{defy} \tag{65}$$

Basically the hand identification algorithm will compare the cost of assigning contacts to attractors in one ring versus the other, the cost depending on the sum of weighted distances between each contact and its assigned attractor. Adjusting the attractor ring with the estimated hand and finger offsets lowers the relative costs for assignment hypotheses which resemble recent hand assignments, helping to stabilize identifications across successive proximity images even when hands temporarily lift off.

Next a set of assignment hypotheses must be generated and compared. The most efficient way to generate sensible hypotheses is to define a set of roughly vertical contour lines, one between each horizontally adjacent contact. Step **454** does this by ordering all surface contacts by their horizontal coordinates and establishing a vertical contour halfway between each pair of adjacent horizontal coordinates. FIGS. **30**A-C show examples of three different contours **475** and

their associated assignment hypotheses for a fixed set of contacts. Each contour corresponds to a separate hypothesis, known also as a partition, in which all contacts to the left **476** of the contour are from the left hand, and all contacts to the right **477** of the contour are from the right hand. Contours are also necessary at the left and right ends of the surface to handle the hypotheses that all contacts on the surface are from the same hand. Contours which hypothesize more contacts on a given hand than can be caused by a single hand are immediately eliminated.

Generating partitions via vertical contours avoids all hypotheses in which contacts of one hand horizontally overlap or cross over contacts of the opposite hand. Considering that each hand can cause seven or more distinct contacts, this reduces the number of hand identity permutations to examine from thousands to at most a dozen. With fewer hypotheses to examine, the evaluation of each partition can be much more sophisticated, and if necessary, computationally costly.

The optimization search loop follows. Its goal is to determine which of the contours divides the contacts into a partition of two contact clusters such that the cluster positions and arrangement of contacts within each cluster best satisfy known anatomical and biomechanical constraints. The optimization begins by picking (step **456**) a first contour divider such as the leftmost and tentatively assigning (step **458**) any contacts to the left of the contour to the left hand and the rest to the right hand. Step **460** invokes the finger identification algorithm of FIG. **23**, which attempts to assign finger and palm identities to contacts within each hand. Decision diamond **360** avoids the computational expense of thumb verification **368** and statistics gathering **364** for this tentative assignment hypothesis.

Returning to FIG. **29**, step **462** computes a cost for the partition. This cost is meant to evaluate how well the tentatively identified contacts fit their assigned attractor ring and how well the partition meets between-hand separation constraints. This is done by computing for each hand the sum of weighted distances from each tentatively identified contact to its assigned attractor point as in Equation 54 of finger identification, including size and orientation feature factors for thumb and palm attractors. This sum represents the basic template fitting cost for a hand. Each hand cost is then weighted as a whole with the reciprocals of its clutching velocity, handedness, and palm cohesion factors. These factors, to be described below, represent additional constraints which are underemphasized by the weighted attractor distances. Finally, the weighted left and right hand costs are added together and scaled by the reciprocal of a hand separation factor to obtain a total cost for the partition.

If decision diamond **464** determines this total cost is lower than the total costs of the partitions evaluated so far **464**, step **466** records the partition cost as the lowest and records the dividing contour. Decision diamond **472** repeats this process for each contour **470** until the costs of all partitions have been evaluated. Step **473** chooses the partition which has the lowest cost overall as the actual hand partitioning **473**, and the hand identities of all contact paths are updated accordingly. Then step **474** reinvokes the within-hand finger contact identification process so that the thumb verification and statistics gathering processes are performed using the actual hand assignments.

Users often perform clutching motions in which the right hand, for example, lifts off from a slide at the right side of the surface, touches backdown in the middle of the surface, and resumes sliding toward the right. Therefore when a hand is detected touching down in the middle of the surface and sliding toward one side, it probably came from the at side. A hand velocity factor, plotted approximately in FIG. **31**A, captures this phenomenon by slightly increasing in value when a hand cluster's contacts are moving toward the cluster's assigned side of the board, thus decreasing the basic cost of the hand. The factor is a function of the average of the contacts' horizontal velocities the side of the surface the given cluster is assigned. Since high speeds do not necessarily give a stronger indication of user intent the factor saturates at moderate speeds.

Though the thumb orientation factors help identify which hand a thumb is from when the thumb lies in the ambiguous middle region of the surface, the vertical position of the thumb relative to other fingers in the same hand also gives a strong indication of handedness. The thumb tends to be positioned much lower than the fingertips, but the pinky tends to be only slightly lower than the other fingertips. The handedness factor plotted approximately in FIG. **31**B, takes advantage of this constraint by boosting the hand cost when the contact identified as the outermost fingertip is more than a couple centimeters lower than the next outermost fingertip contact. In such cases the tentative hand assignment for all contacts in the cluster is probably wrong. Since this causes the within-hand identification algorithm to fit the contacts to the wrong attractor ring, finger identities become reversed such that the supposedly lowered pinky is truly a lowered thumb of the opposite hand. Unfortunately, limited confidence can be placed in the handedness factor. Though the pinky should not appear lowered as much as the thumb the outer palm heel can, creating an ambiguity in which the thumb and fingertips of one hand have the same contact arrangement as the fingertips and outer palm heel of the opposite hand. This ambiguity can cause the handedness factor to be erroneously low for an accurately identified hand cluster, so the handedness factor is only used on clusters in the middle of the surface where hand position is ambiguous.

Distinguishing contact clusters is challenging because a cluster can become quite sparse and large when the fingers outstretched, with the pinky and thumb of the same hand spanning up to 20 cm. However, the palm can stretch very little in comparison, placing useful constraints on how far apart palm heel contacts and forepalms from the same hand can be. The entire palm region of an outstretched adult hand is about 10 cm square, so palm contact centroids should not be scattered over a region larger than about 8 cm. When a partition wrongly includes fingers from the opposite hand in a cluster, the within-cluster identification algorithm tends to assign the extra fingers from the opposite hand to palm heel and forepalm attractors. This usually causes the contacts assigned to the cluster's palm attractors to be scattered across the surface wider than is plausible for true palm contacts from a single hand. To punish such partitions, the palm cohesion factor quickly drops below one for a tentative hand cluster in which the supposed palm contacts are scattered over a region larger than 8 cm. Therefore its reciprocal will greatly increase the hand's basic cost. FIG. **31**C shows the value of the palm cohesion factor versus horizontal separation between palm contacts. The horizontal spread can be efficiently measured by finding the maximum and minimum horizontal coordinates of all contacts identified as palm heels or forepalms and taking the difference between the maximum and minimum. The measurement and factor value lookup are repeated for the vertical separation, and the horizontal and vertical factors are multiplicatively combined to obtain the final palm cohesion factor.

FIG. **33** is an approximate plot of the inter-hand separation factor. This factor increases the total costs of partitions in which the estimated or actual horizontal positions of the

thumbs from each hand approach or overlap. It is measured by finding the minimum of the horizontal offsets of right hand contacts with respect to their corresponding default finger positions. Similarly the maximum of the horizontal offsets of the left hand contacts with respect to their corresponding default finger positions is found. If the difference between these hand offset extremes is small enough to suggest the thumbs are overlapping the same columnar region of the surface while either touching the surface or floating above it, the separation factor becomes very small. Such overlap corresponds to a negative thumb separation in the plot. To encourage assignment of contacts which are within a couple centimeters of one another to the same cluster, the separation factor gradually begins to drop starting with positive separations of a few centimeters or less. The inter-hand separation factor is not applicable to partitions in which all surface contacts are assigned to the same hand, and takes on the default value of one in this case.

Alternative embodiments of this hand identification process can include additional constraint factors and remain well within the scope of this invention. For example, a velocity coherence factor could be computed to favor partitions in which all fingers within a cluster slide at approximately the same speed and direction, though each cluster as a whole has a different average speed and direction.

Sometimes irreversible decisions made by the chord motion recognizer or typing recognized on the basis of existing hand identifications prevent late changes in the identifications of hand contacts even when new proximity image information suggests existing identifications are wrong. This might be the case for a chord slide which generates input events that can not be undone, yet well into the slide new image information indicates some fingers in the chord should have been attributed to the opposite hand. In this case the user can be warned to stop the slide and check for possible input errors but in the meantime it is best to retain the existing identifications even if wrong, rather than switch to correct assignments which could have further unpredictable effects when added to the erroneous input events. Therefore once a chord slide has generated input events, the identifications of their existing paths may be locked so the hand identification algorithm can only swap identifications of subsequent new contacts.

This hand identification process can be modified for differently configured multi-touch surfaces and remain well within the scope of this invention. For surfaces which are so narrow that thumbs invade one another's space or so tall that one hand can lie above another, the contours need not be straight vertical lines. Additional contours could weave around candidate overlapping thumbs, or they could be perpendicular to the vector between the estimated hand positions. If the surface was large enough for more than one user, additional attractor rings would have to be provided for each additional hand, and multiple partitioning contours would be necessary per hypothesis to partition the surface into more than two portions. On a surface large enough for only one hand it might still be necessary to determine which hand was touching the surface. Then instead of hypothesizing different contours, the hand identification module would evaluate the hypotheses that either the left hand attractor ring or the right hand attractor ring was centered on the surface. If the surface was mounted on a pedestal to allow access from all sides, the hand identification module would also hypothesize various rotations of each attractor ring.

The attractor-based finger identification system **248** will successfully identify the individual hand contacts which comprise the pen grip hand configuration (FIG. **15**). However, additional steps are needed to distinguish the unique finger arrangement within the pen grip from the normal arrangement within the closed hand configuration (FIG. **14**). In this pen grip arrangement the outer fingers curl under toward the palms so their knuckles touch the surface and the index, finger juts out ahead of them. The pen grip detection module **17** employs a fuzzy pattern recognition process similar to the thumb verification process to detect this unique arrangement

An additional problem with handwriting recognition via the pen grip hand configuration is that the inner gripping fingers and sometimes the whole hand will be picked up between strokes, causing the distinguishing finger arrangement to temporarily disappear. Therefore the pen grip recognition process must have hysteresis to stay in handwriting mode between gripping finger lifts. In the preferred embodiment, hysteresis is obtained by temporal filtering of the combined fuzzy decision factors and by using the estimated finger positions in measurements of finger arrangement while the actual fingers are lifted off the surface. The estimated finger positions provide effective hysteresis because they temporarily retain the unique jutting arrangement before decaying back toward the normal arched fingertip positions a few seconds after liftoff.

FIG. **28** shows the steps within the pen grip detection module **17**. Decision diamond **485** determines whether all pen grip hand parts are touching the surface. If not decision diamond **486** causes the estimated finger and palm positions to be retrieved for any lifted parts in step **487** only if pen grip or handwriting mode is already active. Otherwise the process exits for lack of enough surface contacts. Thus the estimated finger positions cannot be used to start handwriting mode, but they can continue it. Step **488** retrieves the measured positions and sizes of fingers and palm heels which are touching the surface.

Step **489** computes a knuckle factor from the outer finger sizes and their vertical distance from the palm heels which peaks as the outer finger contacts become larger than normal fingertips and close to the palm heels. Step **490** computes a jutting factor from the difference between the vertical coordinates of the inner and outer fingers which peaks as the index fingertip juts further out in front of the knuckles. Step **491** combines the knuckle and jutting factors in a fuzzy logic expression and averages the result with previous results via an autoregressive or moving average filter. Decision diamond **492** continues or starts pen grip mode if the filtered expression result is above a threshold which may itself be variable to provide additional hysteresis. While in pen grip mode, typing **12** and chord motion recognition **18** are disabled for the pen gripping hand.

In pen grip mode, decision diamond **493** determines whether the inner gripping fingers are actually touching the surface. If so, step **495** generates inking events from the path parameters of the inner fingers and appends them to the outgoing event queue of the host communication interface. These inking events can either cause "digital ink" to be laved on the display **24** for drawing or signature capture purposes, or they can be intercepted by a handwriting recognition system and interpreted as gestures or language symbols. Handwriting recognition systems are well known in the art.

If the inner fingers are lifted, step **494** sends stylus raised events to the host communication interface to instruct the handwriting recognition system of a break between symbols. In some applications the user may need to indicate where the "digital ink" or interpreted symbols are to be inserted on the display by positioning a cursor. Though on a multi-touch surface a user could move the cursor by leaving the pen grip

configuration and sliding a finger chord, it is preferable to allow cursor positioning without leaving the pen grip configuration. This can be supported by generating cursor positioning events from slides of the palm heels and outer knuckles. Since normal writing motions will also include slides of the palm heels and outer knuckles, palm motions should be ignored until the inner fingers have been lifted for a few hundred milliseconds.

Should the user actually pick up a conductive stylus and attempt to write with it, the hand configuration will change slightly because the inner gripping fingers will be directing the stylus from above the surface rather than touching the surface during strokes. Since the forearm tends to supinate more when actually holding a stylus, the inner palm heel may also stay off the surface while the hand rests on the sides of the pinky, ring finger and the outer palm heel. Though the outer palm heel may lie further outward than normal with respect to the pinky, the ring and pinky fingers will still appear as large knuckle contacts curled close to the outer palm. The tip of the stylus essentially takes the place of the index fingertip for identification purposes, remaining at or above the vertical level of the knuckles. Thus the pen grip detector can function in essentially the same way when the user writes with a stylus, except that the index fingertip path sent to the host communication interface will in actuality be caused by the stylus.

Technically, each hand has 24 degrees of freedom of movement in all finger joints combined, but as a practical matter, tendon linkage limitations make it difficult to move all of the joints independently. Measurements of finger contacts on a surface yield ten degrees of freedom in motion lateral to the surface, five degrees of freedom in individual fingertip pressure or proximity to the surface, and one degree of freedom of thumb orientation. However, many of these degrees of freedom have limited ranges and would require unreasonable twisting and dexterity from the average user to access independently.

The purpose of the motion component extraction module **16** is to extract from the 16 observable degrees of freedom enough degrees of freedom for common graphical manipulation tasks in two and three dimensions. In two dimensions the most common tasks are horizontal and vertical panning, rotating, and zooming or resizing. In three dimensions, two additional rotational degrees of freedom are available around the horizontal and vertical axes. The motion component extractor attempts to extract these 4-6 degrees of freedom from those basic hand motions which can be performed easily and at the same time without interfering with one another. When multiple degrees of freedom can be accessed at the same time they are said to be integral rather than separable, and integral input devices are usually faster because they allow diagonal motions rather than restricting motions to be along a single axis or degree of freedom at one time.

When only four degrees of freedom are needed, the basic motions can be whole hand translation, hand scaling by uniformly flexing or extending the fingers, and hand rotation either about the wrist as when unscrewing ajar lid or between the fingers as when unscrewing a nut. Not only are these hand motions easy to perform because they utilize motions which intuitively include the opposable thumb, they correspond cognitively to the graphical manipulation tasks of object rotation and sizing. Their only drawback is that the translational motions of all the fingers during these hand rotations and scalings do not cancel perfectly and can instead add up to a net translation in some direction in addition to the desired rotation or scaling. To allow all motions to be performed simultaneously so that the degrees of freedom are integral yet to prevent unintended translations from imperfectly performed scalings and rotations, the motion extractor preferentially weights the fingers whose translations cancel best and nonlinearly scales velocity components depending on their speeds relative to one another.

The processes within the motion component extractor **16** are shown in FIG. **34**. Step **500** first fetches the identified contact paths **250** for the given hand. These paths contain the lateral velocities and proximities to be used in the motion calculations, and the identifications are needed so that motion of certain fingers or palm heels which would degrade particular motion component calculations can be deemphasized.

The next step **502** applies additional filtering to the lateral contact velocities when finger proximity is changing rapidly. This is necessary because during finger liftoff and touch down on the surface, the front part of the fingertip often touches down before and lifts off after the back of the fingertip, causing a net downward or upward lateral translation in the finger centroid. Such proximity-dependent translations can be put to good use when slowly rolling the fingertip for fine positioning control, but they can also annoy the user if they cause the cursor to jump away from a selected position during finger liftoff. This is prevented by temporarily downscaling a finger's lateral velocity in proportion to large changes in the finger's proximity. Since other fingers within a hand tend to shift slightly as one finger lifts off, additional downscaling of each finger velocity is done in response to the maximum percent change in proximity among contacting fingers. Alternatively, more precise suppression can be obtained by subtracting from the lateral finger speed an amount proportional to the instantaneous change in finger contact height. This assumes that the perturbation in lateral finger velocity caused by finger liftoff is proportional to the change in contact height due to the back of the fingertip lifting off first or touching down last.

Process **504**, whose detailed steps are shown in FIG. **36**, measures the polar velocity components from radial (scaling) and rotational motion. Unless rotation is extracted from thumb orientation changes, at least two contacting fingers are necessary to compute a radial or angular velocity of the hand. Since thumb motion is much more independent of the other fingers than they are of one another, scalings and rotations are easier for the user to perform if one of these fingers is the opposable thumb, but the measurement method will work without the thumb. If decision diamond **522** determines that less than two fingers are touching the surface, step **524** sets the radial and rotational velocities of the hand to zero. FIG. **35** shows trajectories of each finger during a contractive hand scaling. The thumb **201** and pinky **205** travel in nearly opposite directions at roughly the same speed, so that the sum of their motions cancels for zero net translation, but the difference in their motions is maximized for a large net scaling. The central fingers **202-204** also move toward a central point but the palm heels remain stationary, failing to complement the flexing of the central fingers. Therefore the difference between motion of a central finger and any other finger is usually less than the difference between the pinky and thumb motions, and the sum of central finger velocities during a hand scaling adds up to a net vertical translation. Similar phenomena occur during hand rotations, except that if the rotation is centered at the wrist with forearm fixed rather than centered at the forepalms, a net horizontal translation will appear in the sum of motions from any combination of fingers.

Since the differences in finger motion are usually greatest between thumb and pinky, step **526** only retrieves the current and previous positions of the innermost and outermost touching fingers for the hand scaling and rotation measurements.

Step **528** then computes the hand scaling velocity H_{xx} from the change in distance between the innermost finger FI and outermost finger FO with approximately the following equation:

$$Hvs[n] = \frac{d(FI[n], FO[n]) - d(fi[n-1], FO[n-1])}{\Delta t} \tag{66}$$

where d(FI[n],FO[n]) is the squared Euclidean distance between the fingers:

$$d\Big(FI[n], FO[n] = \sqrt{(FI_x[n] - FO_x[n])^2 + (FI_y[n] - FO_y[n])^2} \tag{67}$$

If one of the innermost or outermost fingers was not touching during the previous proximity image, the change in separation is assumed to be zero. Similarly, step **530** computes the hand rotational velocity H_{xx} from the change in angle between the innermost and outermost finger with approximately the following equation:

$$H_{vr}[n] = \left(\frac{\angle(FI[n], FO[n]) - \angle(FI[n-1], FO[n-1])}{\Delta t}\right) \times \left(\frac{d(FI[n], FO[n]}{\pi}\right) \tag{68}$$

The change in angle is multiplied by the current separation to convert it to the same units as the translation and scaling components. These equations capture any rotation and scaling components of hand motion even if the hand is also translating as a whole, thus making the rotation and scaling degrees of freedom integral with translation.

Another reason the computations above are restricted to the thumb and pinky or innermost and outermost fingers is that users may want to make fine translating manipulations with the central fingers, i.e., index, middle, and ring, while the thumb and pinky remain stationary. If changes in distances or angles between the central fingers and the thumb were averaged with Equations 66-68, this would not be possible because central finger translations would cause the appearance of rotation or scaling with respect to the stationary thumb or pinky. However, Equations 56-60 applied in the thumb verification process are only sensitive to symmetric rotation and scaling about a fixed point between the fingers. They approach zero if any significant whole hand translation is occurring or the finger motions are not complementary. In case the user fails to properly move the outermost finger during a rotation or scaling gesture, step **531** uses equations of the approximate form of Equations 56-60 to compute rotation and scaling velocities between the thumb and any touching fingers other than the outermost. The resulting velocities are preferably combined with the results of Equations 66-68 via a maximum operation rather than an average in case translational motion causes the fixed point rotations or scalings to be zero. Finally, decision diamond **532** orders a check for radial or rotational deceleration **534** during motions prior to finger liftoff. The method for detecting radial or rotational deceleration is the same as that detailed in the description of translation extraction.

FIG. **37** shows the details of hand translational velocity measurements referred to in process **506** of FIG. **34**. The simplest way to compute a hand translation velocity would be to simply average the lateral velocities of each finger. However, the user expects the motion or control to display gain to be constant regardless of how many fingers are being moved, even if some are resting stationary. Furthermore, if the user is simultaneously scaling or rotating the hand, a simple average is sensitive to spurious net translations caused: by uncanceled central finger motions.

Therefore, in a preferred embodiment the translational component extractor carefully assigns weightings for each finger before computing the average translation. Step **540** initializes the translation weighting Fi_{vw} of each finger to its total contact proximity, i.e., $Fi_{vw}[n]=F_{iz}[n]$. This ensures that fingers not touching the surface do not dilute the average with their zero velocities and that fingers which only touch lightly have less influence since their position and velocity measurements may be less reliable. The next step **544** decreases the weightings of fingers which are relatively stationary so that the control to display gain of intentionally moving fingers is not diluted. This can be done by finding the fastest moving finger, recording its speed as a maximum finger speed and scaling each finger's translation weighting in proportion to its speed divided by the maximum of the finger speeds, as shown approximately in the formula below:

$$Fi_{vw}[n] := FI_{vw}[n] \times \left(\frac{Fi_{speed}[n]}{\max_j Fi_{speed}[n]}\right)^{ptw} \tag{69}$$

where the power ptw adjusts the strength of the speed dependence. Note that step **544** can be skipped for applications such as computer-aided-design in which users desire both a normal cursor motion gain mode and a low gain mode. Lower cursor motion gain is useful for fine, short range positioning, and would be accessed by moving only one or two fingers while keeping the rest stationary.

Step **546** decreases the translation weightings for the central fingers during hand scalings and rotations, though it does not prevent the central fingers from making fine translational manipulations while the thumb and pinky are stationary. The formulas below accomplish this seamlessly by downscaling the central translation weightings as the magnitudes of the rotation and scaling velocities become significant compared to $K_{polarthresh}$:

$$Fi_{vwx}[n] \approx \frac{Fi_{vw}[n] \times K_{polarthresh}}{K_{polarthresh} + |H_{vr}[n]|} \tag{70}$$

$$Fi_{vwy}[n] \approx \frac{Fi_{vw}[n] \times K_{polarthresh}}{K_{polarthresh} + |H_{vr}[n]| + |H_{vs}[n]|} \tag{71}$$

where these equations are applied only to the central fingers whose identities i are between the innermost and outermost. Note that since hand scaling does not cause much horizontal translation bias, the horizontal translation weighting $Fi_{vwx}[n]$ need not be affected by hand scaling velocity $H_{vs}[n]$, as indicated by the lack of a hand scaling term in Equation 70. The translation weightings of the innermost and outermost fingers are unchanged by the polar component speeds, i.e., $FI_{vwx}[n]=FI_{vwx}[n]=FI_{vw}[n]$ and $FO_{vwx}[n]=FO_{vwx}[n]=FO_{vw}[n]$. Step **548** finally computes the hand translation velocity vector ($H_{vx}[n]$, $H_{vy}[n]$) from the weighted average of the finger velocities:

$$H_{vx}[n] = \frac{\sum_{i-1}^{5} Fi_{vwx} Fi_{vx}}{\sum_{i-1}^{5} Fi_{vwx}} \quad (72)$$

$$H_{vy}[n] = \frac{\sum_{i-1}^{5} Fi_{vwy} Fi_{vy}}{\sum_{i-1}^{5} Fi_{vwy}} \quad (73)$$

The last part of the translation calculations is to test for the lateral deceleration of the fingers before liftoff, which reliably indicates whether the user wishes cursor motion to stop at liftoff. If deceleration is not detected prior to liftoff, the user may intend cursor motion to continue after liftoff, or the user may intend a special "one-shot" command to be invoked. Decision diamond **550** only invokes the deceleration tests while finger proximities are not dropping too quickly, to prevent the perturbations in finger centroids which can accompany finger liftoff from interfering with the deceleration measurements. Step **551** computes the percentage acceleration or ratio of current translation speed $|H_{vx}[n], H_{vy}[n])|$ to a past average translation speed preferably computed by a moving window average or autoregressive filter. Decision diamond **552** causes the translation deceleration flag to be set **556** if the acceleration ratio is less than a threshold. If this threshold is set greater than one, the user will have to be accelerating the fingers just prior to liftoff for cursor motion to continue. If the threshold is set just below one, cursor motion will reliably be continued as long as the user maintains a constant lateral speed prior to liftoff, but if the user begins to slow the cursor on approach to a target area of the display the deceleration flag will be set. Decision diamond **554** can also cause the deceleration flag to be set if the current translation direction is substantially different from an average of past directions. Such change in direction indicates the hand motion trajectory is curving, in which case cursor motion should not be continued after liftoff because accurately determining the direction to the user's intended target becomes very difficult. If neither deceleration nor curved trajectories are detected, step **558** clears the translation deceleration flag. This will enable cursor motion continuation should the fingers subsequently begin liftoff. Note that decision diamond **550** prevents the state of the translation deceleration flags from changing during liftoff so that the decision after liftoff to continue cursor motion depends on the state of the deceleration flag before liftoff began. The final step **560** updates the autoregressive or moving window average of the hand translation velocity vector, which can become the velocity of continued cursor motion after liftoff. Actual generation of the continued cursor motion signals occurs in the chord motion recognizer **18** as will be discussed with FIG. **40**.

Note that this cursor motion continuation method has several advantages over motion continuation methods in related art. Since the decision to continue motion depends on a percentage acceleration which inherently normalizes to any speed range, the user can intentionally invoke motion continuation from a wide range of speeds including very low speeds. Thus the user can directly invoke slow motion continuation to auto scroll a document at readable speeds. This is not true of Watanabe's method in U.S. Pat. No. 4,734,685, which only continues motion when the user's motion exceeds a high speed threshold, nor of Logan et al.'s method in U.S. Pat. No. 5,327,161, which if enabled for low finger speeds will undesirably continue motion when a user decelerates on approach to a large target but fails to stop completely before lifting off. Percentage acceleration also captures user intent more clearly than position of a finger in a border area. Position of a finger in a border area as used in U.S. Pat. No. 5,543,591 to Gillespie et al. is ambiguous because the cursor can reach its desired target on the display just as the finger enters the border, yet the touchpad device will continue cursor motion past the target because it thinks the finger has run out of space to move. In the present invention, on the other hand, the acceleration ratio will remain near one if the fingers can slide off the edge of the sensing array without hitting a physical barrier, sensibly invoking motion continuation. But if the fingers decelerate before crossing or stop on the edge of the sensing array, the cursor will stop as desired.

The details of the differential hand pressure extraction process **508** are shown in FIG. **38**. Fingertip proximity, quickly saturates when pressure is applied through the bony tip normal to a hard surface. Unless the surface itself is highly compliant, the best dynamic range of fingertip pressure is obtained with the fingers outstretched and hand nearly flattened so that the compressible soft pulp underneath the fingertips rests on the surface. Decision diamond **562** therefore causes the tilt and roll hand pressure components to be set to zero in step **564** and pressure extraction to abort unless the hand is nearly flattened. Inherent in the test for hand flattening **562** is a finger count to ensure that most of the five fingers and both palm heels are touching the surface to maximize the precision of the hand pressure measurements, though technically only three non-collinear hand contacts arranged like a tripod are necessary to establish tilt and roll pressures. Decision diamond **562** can also require the user to explicitly enable three-dimensional manipulation with an intuitive gesture such as placing all five fingers on the surface briefly tapping the palm heels on the surface, and finally resting the palm heels on the surface. Decision diamond **566** causes step **568** to capture and store reference proximities for each contact path when the proximity of all contacts have stabilized at the end of this initiation sequence. The tilt and roll pressure components are again zeroed **564** for the sensor array scan cycle during which this calibration is performed.

However, during subsequent scan cycles the user can tilt the hand forward applying more pressure to the fingertips or backward applying more pressure to the palm heels or the user can roll the hand outward onto the pinky and outer palm heel or inward applying more pressure to the thumb, index finger and inner palm heel. Step **5170** will proceed to calculate an unweighted average of the current contact positions. Step **572** computes for each hand part still touching the surface the ratio of current proximity to the reference proximity previously stored. To make these ratios less sensitive to accidental lifting of hand parts, step **574** clips them to be greater or equal to one so only increases in proximity and pressure register in, the tilt and roll measurements. Another average contact path position is computed in step **576**, but this one is weighted by the above computed proximity ratios for each path. The difference between these weighted and unweighted contact position averages taken in step **578** produces a vector whose direction can indicate the direction of roll or tilt and whose magnitude can control the rate of roll or tilt about x and y axes.

Since the weighted and unweighted position averages are only influenced by positions of currently contacting fingers and increases in contact pressure or proximity, the method is insensitive to finger liftoffs. Computation of reference-normalized proximity ratios in step **572** rather than absolute

changes in proximity prevents the large palm heel contacts from having undue influence on the weighted average position.

Since only the current contact positions are used in the average position computations, the roll and tilt vector is independent of lateral motions such as hand translation or rotation as long as the lateral motions do not disturb finger pressure, thus once again achieving integrality. However, hand scaling and differential hand pressure are difficult to use at the same time because flexing the fingers generally causes significant decreases in fingertip contact area and thus interferes with inference of fingertip pressure changes. When this becomes a serious problem, a total hand pressure component can be used as a sixth degree of freedom in place of the hand scaling component. This total pressure component causes cursor velocity along a z-axis in proportion to deviations of the average of the contact proximity ratios from one. Alternative embodiments may include further enhancements such as adapting the reference proximities to slow variations in resting hand pressure and applying a dead zone filter to ignore pressure difference vectors with small magnitudes

Despite the care taken to measure the polar velocity, translation velocity, and hand pressure components in such a way that the resultant vectors are independent of one another, uneven finger motion during hand scaling, rotation, or translation can still cause minor perturbations in measurements of one degree of freedom while primarily attempting to move in another. Non-linear filtering applied in steps **510** and **512** of FIG. **34** removes the remaining motion leakage between dominant components and nearly stationary components. In steps **510** each component velocity is downscaled by the ratio of its average speed to the maximum of all the component speeds, the dominant component speed:

$$H_{vx}[n] := H_{vx}[n] \times \left(\frac{H_{xyspeed}[n]}{dominantspeed}\right)^{pds} \tag{74}$$

$$H_{vy}[n] := H_{vy}[n] \times \left(\frac{H_{xyspeed}[n]}{dominantspeed}\right)^{pds} \tag{75}$$

$$H_{vs}[n] := H_{vs}[n] \times \left(\frac{H_{sspeed}[n]}{dominantspeed}\right)^{pds} \tag{76}$$

$$H_{vr}[n] := H_{vr}[n] \times \left(\frac{H_{rspeed}[n]}{dominantspeed}\right)^{pds} \tag{77}$$

where $H_{xyspeed}[n]$, $H_{sspeed}[n]$, and $H_{rspeed}[n]$ are autoregressive averages over time of the translation speed, scaling speed, and rotational speed, where:

$$\text{dominant_speed} = \max(H_{xyspeed}[n], H_{sspeed}[n], H_{rspeed}[n]) \tag{78}$$

where pds controls the strength of the filter. As pdy is adjusted towards infinity the dominant component is picked out and all components less than the dominant tend toward zero producing the orthogonal cursor effect well-known in drawing applications. As pds is adjusted towards zero the filters have no effect. Preferably, pds is set in between so that components significantly slower than the dominant are slowed further, but components close to the dominant in speed are barely affected, preserving the possibility of diagonal motion in multiple degrees of freedom at once. The autoregressive averaging helps to pick out the component or components which are dominant over the long term and suppress the others even while the dominant components are slowing to a stop.

Step **512** takes a second pass with a related filter known as a dead-zone filter. A dead-zone filter produces zero output velocity for input velocities less than a speed threshold but produces output speeds in proportion to the difference between the input speed and the threshold for input velocities that exceed the threshold. Preferably the speed threshold or width of the dead zone is set to a fraction of the maximum of current component speeds. All velocity components are filtered using this same dead zone width. The final extracted component velocities are forwarded to the chord motion recognizer module **18** which will determine what if any input events should be generated from the motions.

FIG. **39**A shows the details of the finger synchronization detector module **14**. The synchronization detection process described below is repeated for each hand independently. Step **600** fetches proximity markers and identifications for the hand's current paths. The identifications will be necessary to ignore palm paths and identify combinations of synchronized fingers, while the proximity markers record the time at which each contact path first exceeds a press proximity threshold and the time at which each contact path drops below a release proximity threshold prior to total liftoff. Setting these proximity thresholds somewhat higher than the minimum proximity considered significant by the segmentation search process **264**, produces more precise finger press and release times.

Step **603** searches for subsets of fingers which touch down at about the same time and for subsets of fingers which lift off at about the same time. This can be done by recording each finger path along with its press time in a temporally ordered list as it crosses the press proximity threshold. Since the primary function of the palms is to support the forearms while the hands are resting, palm activity is ignored by the typing **12** and chord motion recognizers **18** except during differential hand pressure extraction and palm heel presses can be excluded from this list and most other synchronization tests. To check for synchronization between the two most recent finger presses, the press times of the two most recent entries in the list are compared. If the difference between their press times is less than a temporal threshold, the two finger presses are considered synchronized. If not, the most recent finger press is considered asynchronous. Synchronization among three or more fingers up to five is found by comparing press times of the three, four, or five most recent list entries. If the press time of the most recent entry is within a temporal threshold of the nth most recent entry, synchronization among the n most recent finger presses is indicated. To accommodate imprecision in touchdown across the hand, the magnitude of the temporal threshold should increase slightly in proportion to the number of fingers being tested for synchronization. The largest set of recent finger presses found to be synchronized is recorded as the synchronized subset, and the combination of finger identities comprising this subset is stored conveniently as a finger identity bitfield. The term subset is used because the synchronized press subset may not include all fingers currently touching the surface, as happens when a finger touches down much earlier than the other fingers yet remains touching as they simultaneously touch down. An ordered list of finger release times is similarly maintained and searched separately. Alternative embodiments may require that a finger still be touching the surface to be included in the synchronized press subset.

Decision diamond **602** checks whether a synchronization marker is pending from a previous image scan cycle. If not, decision diamond **604** checks whether the search **603** found a newly synchronized press subset in the current proximity image. If so, step **606** sets the temporal synchronization

marker to the oldest press within the new synchronized subset. Additional finger presses may be added to the subset during future scan cycles without affecting the value of this temporal synchronization marker. If there is currently no finger press synchronization, decision diamond **605** determines whether three or more fingers have just been released simultaneously. Simultaneous release of three or more fingers should not occur while typing with a set of fingers but does occur when lifting fingers off the surface from rest. Therefore simultaneous release of three or more fingers reliably indicates that the released fingers are not intended as keypresses and should be deleted from the keypress queue **605**, regardless of whether these same fingers touched down synchronously. Release synchronization of two fingers is not by itself a reliable indicator of typing intent and has no effect on the keypress queue. The keypress queue is described later with FIGS. **42**-**43**B.

Once a press synchronization marker for the hand is pending, further processing checks the number of finger presses which are synchronized and waits for release of the synchronized fingers. If decision diamond **608** finds three or more fingers in the synchronized press subset the user cannot possibly be typing with these fingers. Therefore step **612** immediately deletes the three or more synchronized presses from the keypress queue. This way they cannot cause key symbol transmission to the host, and transmission of key symbols from subsequent asynchronous presses is not blocked waiting for the synchronized fingers to be released.

However, when the synchronization only involves two finger presses **608**, it is difficult to know whether the user intended to tap a finger pair chord or intended to type two adjacent keys and accidentally let the key presses occur simultaneously. Since such accidental simultaneous presses are usually followed by asynchronous releases of the two fingers, but finger pair chords are usually released synchronously, the decision whether the presses are asynchronous key taps or chord taps must be delayed until finger release can be checked for synchronization. In the meantime, step **610** places a hold on the keypress queue to prevent transmission of key symbols from the possible finger chord or any subsequent finger presses. To prevent long backups in key transmission, decision diamond **614** will eventually release the queue hold by having step **615** delete the synchronized presses from the keypress queue if both fingers remain touching a long time. Though this aborts the hypothesis that the presses were intended as key taps, the presses are also less likely to be key taps if the fingers are not lifted soon after touchdown.

If the synchronized fingers are not lifting, decision diamond **616** leaves the synchronization marker pending so synchronization checks can be continued with updated path parameters **600** after the next scan cycle. If the synchronized fingers are lifting, but decision diamond **618** finds with the help of the synchronization release search **603** that they are doing so asynchronously **618**, step **622** releases any holds on the keypress queue assuming any synchronized finger pair was intended to be two keypresses. Though the synchronized finger presses are not deleted from the keypress queue at this point, they may have already been deleted in step **612** if the pressed subset contained more than two. Also, step **624** clears the temporal synchronization marker, indicating that no further synchronization tests need be done for this subset.

Continuing to FIG. **39**B, if the fingers synchronized during touchdown also lift simultaneously, step **618** removes them and any holds from the keypress queue in case they were a pair awaiting a positive release synchronization test. Further tests ensue to determine whether the synchronized fingers meet additional chord tap conditions. As with single finger taps, the synchronized fingers cannot be held on the surface more than about half a second if they are to qualify, as a chord tap. Decision diamond **626** tests this by thresholding the time between the release of the last remaining synchronized finger and the temporal press synchronization marker. A chord tap should also exhibit a limited amount of lateral finger motion, measured either as an average of peak finger speeds or distance traveled since touchdown in decision diamond **628**. If the quick release and limited lateral motion conditions are not met, step **624** clears the synchronization marker with the conclusion that the synchronized fingers were either just resting fingers or part of a chord slide.

If the chord tap conditions are met, step **630** looks up, using the synchronized subset bitfield, any input events such as mouse clicks or keyboard commands assigned to the combination of fingers in the chord tap. Some chords such as those including all four fingertips may be reserved as resting chords **634**, in which case decision diamond **632** will find they have no associated input events. If the chord does have tap input events, step **636** appends these to the main outgoing event queue of the host communication interface **20**. Finally step **624** clears the synchronization marker in readiness for future finger synchronizations on the given hand.

As a further precaution against accidental generation of chord taps while typing, it is also useful for decision diamond **632** to ignore through step **634** the first chord tap which comes soon after a valid keypress without a chord slide in between. Usually after typing the user will need to reposition the mouse cursor before clicking, requiring an intervening chord slide. If the mouse cursor happens to already be in place after typing, the user may have to tap the finger chord a second time for the click to be sent, but this is less risky than having an accidental chord tap cause an unintended mouse button click in the middle of a typing session.

FIG. **40**A shows the detailed steps of the chord motion recognizer module **18**. The chord motion recognition process described below is repeated for each hand independently. Step **650** retrieves the parameters of the hand's identified paths **250** and the hand's extracted motion components from the motion extraction module **16**. If a slide of a finger chord has not already started, decision diamond **652** orders slide initiation tests **654** and **656**. To distinguish slides from glancing finger taps during typing, decision diamond **654** requires at least two fingers from a hand to be touching the surface for slide mode to start. There may be some exceptions to this rule, such as allowing a single finger to resume a previous slide within a second or so after the previous slide chord lifts off the surface.

In a preferred embodiment, the user can start a slide and specify its chord in either of two ways. In the first way, the user starts with the hand floating above the surface, places some fingers on the surface possibly asynchronously, and begins moving all of these fingers laterally. Decision diamond **656** initiates the slide mode only when significant motion is detected in all the touching fingers. Step **658** selects the chord from the combination of fingers touching when significant motion is detected, regardless of touchdown synchronization. In this case coherent initiation of motion in all the touching fingers is sufficient to distinguish the slide from resting fingers, so synchronization of touchdown is not necessary. Also, novice users may erroneously try to start a slide by placing and sliding only one finger on the surface, forgetting that multiple fingers are necessary. Tolerance of asynchronous touchdown allows them to seamlessly correct this by subsequently placing and sliding the rest of the fingers desired for

the chord. The slide chord will then initiate without forcing the user to pick up all fingers and start over with synchronized finger touchdowns.

In the second way, the user starts with multiple fingers resting on the surface, lifts a subset of these fingers, touches a subset back down on the surface synchronously to select the chord, and begins moving the subset laterally to initiate the slide. Decision diamond **656** actually initiates the slide mode when it detects significant motion in all the fingers of the synchronized subset. Whether the fingers which remained resting on the surface during this sequence begin to move does not matter since in this case the selected chord is determined in step **658** by the combination of fingers in the synchronized press subset, not from the set of all touching fingers. This second way has the advantage that the user does not have to lift the whole hand from the surface before starting the slide, but can instead leave most of the weight of the hands resting on the surface and only lift and press the two or three fingers necessary to identify the most common finger chords.

To provide greater tolerance for accidental shifts in resting finger positions, decision diamond **656** requires both that all relevant fingers are moving at significant speed and that they are moving about the same speed. This is checked either by thresholding the geometric mean of the finger speeds or by thresholding the fastest finger's speed and verifying that the slowest finger's speed is at least a minimum fraction of the fastest finger's speed. Once a chord slide is initiated, step **660** disables recognition of key or chord taps by the hand at least until either the touching fingers or the synced subset lifts off.

Once the slide initiates, the chord motion recognizer could simply begin sending raw component velocities paired with the selected combination of finger identities to the host. However, in the interest of backward compatibility with the mouse and key event formats of conventional input devices, the motion event generation steps in FIG. **40**B convert motion in any of the extracted degrees of freedom into standard mouse and key command events which depend on the identity of the selected chord. To support such motion conversion, step **658** finds a chord activity structure in a lookup table using a bitfield of the identities of either the touching fingers or the fingers in the synchronized, subset. Different finger identity combinations can refer to the same chord activity structure. In the preferred embodiment, all finger combinations with the same number of non-thumb fingertips refer to the same chord activity structure, so slide chord activities are distinguished by whether the thumb is touching and how many non-thumb fingers are touching. Basing chord action on the number of fingertips rather than their combination still provides up to seven chords per hand yet makes chords easier for the user to memorize and perform. The user has the freedom to choose and vary which fingertips are used in chords requiring only one; two or three fingertips. Given this freedom, users naturally tend to pick combinations in which all touching fingertips are adjacent rather than combinations in which a finger such as the ring finger is lifted but the surrounding fingers such as the middle and pinky must touch. One chord typing study found that users can tap these finger chords in which all pressed fingertips are adjacent twice as fast as other chords.

The events in each chord activity structure are organized into slices. Each slice contains events to be generated in response to motion in a particular range of speeds and directions within the extracted degrees of freedom. For example, a mouse cursor slice could be allocated any translational speed and direction. However, text cursor manipulation requires four slices, one for each arrow key, and each arrow's slice integrates motion in a narrow direction range of translation. Each slice can also include motion sensitivity and so-called cursor acceleration parameters for each degree of freedom. These will be used to discretize motion into the units such as arrow key clicks or mouse clicks expected by existing host computer systems.

Step **675** of chord motion conversion simply picks the first slice in the given chord activity structure for processing. Step **676** scales the current values of the extracted velocity components by the slice's motion sensitivity and acceleration parameters. Step **677** geometrically projects or clips the scaled velocity components into the slice's defined speed and direction range. For the example mouse cursor slice, this might only involve clipping the rotation and scaling components to zero. But for an arrow key slice, the translation velocity vector is projected onto the unit vector pointing in the same direction as the arrow. Step **678** integrates each scaled and projected component velocity over time in the slice's accumulators until decision diamond **680** determines at least one unit of motion has been accumulated. Step **682** looks up the slice's preferred mouse, key, or three-dimensional input event format, attaches the number of accumulated motion units to the event; and step **684** dispatches the event to the outgoing queue of the host communication interface **20**. Step **686** subtracts the sent motion events from the accumulators, and step **688** optionally clears the accumulators of other slices. If the slice is intended to generate a single key command per hand motion, decision diamond **689** will determine that it is a one-shot slice so that step **690** can disable further event generation from it until a slice with a different direction intervenes. If the given slice is the last slice, decision diamond **692** returns to step **650** to await the next scan of the sensor array. Otherwise step **694** continues to integrate and convert the current motion for other slices.

Returning to FIG. **40**A, for some applications it may be desirable to change the selected chord whenever an additional finger touches down or one of the fingers in the chord lifts off. However, in the preferred embodiment, the selected chord cannot be changed after slide initiation by asynchronous finger touch activity. This gives the user freedom to rest or lift addition fingers as may be necessary to get the best precision in a desired degree of freedom. For example, even though the finger pair chord does not include the thumb, the thumb can be set down shortly after slide initiation to access the full dynamic range of the rotation and scaling degrees of freedom. In fact, all remaining lifted fingers can always be set down after initiation of any chord to allow manipulation by the whole hand. Likewise, all fingers but one can be lifted, yet translation will continue.

Though asynchronous finger touch activity is ignored, synchronized lifting and pressing of multiple fingers subsequent to slide initiation can create a new synchronized subset and change the selected chord. Preferably this is only allowed while the hand has paused but its fingers are still resting on the surface. Decision diamond **670** will detect the new subset and commence motion testing in decision diamond **673** which is analogous to decision diamond **656**. If significant motion is found in all fingers of the newly synchronized subset, step **674** will select the new subset as the slide chord and lookup a new chord activity structure in analogy to step **658**. Thus finger synchronization again allows the user to switch to a different activity without forcing the user to lift the whole hand from the surface. Integration of velocity components resumes but the events generated from the new chord activity structure will presumably be different.

It is advantageous to provide visual or auditory feedback to the user about which chord activity structure has been selected. This can be accomplished visually by placing a row of five light emitting diodes across the top of the multi-touch

surface, with one row per hand to be used on the surface. When entering slide mode, step **658** would turn on a combination of these lights corresponding to the combination of fingers in the selected chord. Step **674** would change the combination of active lights to match the new chord activity structure should the user select a new, chord, and step **668** would turn them off. Similar lights could be emulated on the host computer display **24**. The lights could also be flashed to indicate the finger combination detected during chord taps in step **636**. The implementation for auditory feedback would be similar, except light combinations would be replaced with tone or tone burst combinations.

The accumulation and event generation process repeats for all array scan cycles until decision diamond **664** detects liftoff by all the fingers from the initiating combination. Decision diamond **666** then checks the pre-liftoff deceleration flag of the dominant motion, component. The state of this flag is determined by step **556** or **558** of translation extraction (FIG. **37**) if translation is dominant, or by corresponding flags in step **534** of polar extraction. If there has been significant deceleration, step **668** simply exits the chord slide mode, setting the selected chord to null. If the flag indicates no significant finger deceleration prior to liftoff, decision diamond **666** enables motion continuation mode for the selected chord. While in this mode, step **667** applies the pre-liftoff weighted average (**560**) of dominant component velocity to the motion accumulators (**678**) in place of the current velocities, which are presumably zero since no fingers touch the surface. Motion continuation mode does not stop until any of the remaining fingers not in the synchronized subset are lifted or more fingers newly touch down. This causes decision diamond **664** to become false and normal slide activity with the currently selected chord to resume. Though the cursor or scrolling velocity does not decay during motion continuation mode, the host computer can send a signal instructing motion continuation mode to be canceled if the cursor reaches the edge of the screen or end of a document. Similarly, if any fingers remain on the surface during motion continuation, their translations can adjust the cursor or scrolling velocity.

In the preferred embodiment, the chord motion recognizers for each hand function independently and the input events for each chord can be configured independently. This allows the system to allocate tasks between hands in many different ways and to support a variety of bimanual manipulations. For example, mouse cursor motion can be allocated to the fingertip pair chord on both hands and mouse button drag to a triple fingertip chord on both hands. This way the mouse pointer can be moved and drug with either hand on either half of the surface. Primary mouse clicks would be generated by a tap of a fingertip pair on either half of the surface, and double-clicks could be ergonomically generated by a single tap of three fingertips on the surface. Window scrolling could be allocated to slides of four fingers on either hand.

Alternatively, mouse cursor manipulations could be allocated as discussed above to the right hand and right half of the surface, while corresponding text cursor manipulations are allocated to chords on the left hand. For instance, left fingertip pair movement would generate arrow key commands corresponding to the direction of motion, and three fingertips would generate shift arrow combinations for selection of text.

For host computer systems supporting manipulations in three or more degrees of freedom, a left hand chord could be selected to pan, zoom, and rotate the display background while a corresponding chord in the right hand could translate, resize and rotate a foreground object. These chords would not have to include the thumb since the thumb can touch down anytime after initiating chord motion without changing the selected chord. The user then need add the thumb to the surface when attempting rotation or scaling.

Finger chords which initially include the thumb can be reserved for one-shot command gestures, which only generate input events once for each slide of a chord rather than repeating transmission each time an additional unit of motion is detected. For example, the common editing commands cut, copy and paste can be intuitively allocated to a pinch hand scaling, chord tap, and anti-pinch hand scaling of the thumb and an opposing fingertip.

FIG. **41** shows the steps within the key layout definition and morphing process, which is part of the typing recognition module **12**. Step **700** retrieves at system startup a key layout which has been pre-specified by the user or manufacturer. The key layout consists of a set of key region data structures. Each region has associated with it the symbol or commands which should be sent to the host computer when the region is pressed and coordinates representing the location of the center of the region on the surface. In the preferred embodiment, arrangement of those key regions containing alphanumeric and punctuation symbols roughly corresponds to either the QWERTY or the Dvorak key layouts common on mechanical keyboards.

In some embodiments of the multi-touch surface apparatus it is advantageous to be able to snap or morph the key layout to the resting positions of the hands. This is especially helpful for multi-touch surfaces which are several times larger than the standard keyboard or key layout, such as one covering an entire desk. Fixing the key layout in one small fixed area of such a surface would be inconvenient and discourage use of the whole available surface area. To provide feedback to the user about changes in the position of the key layout, the position of the key symbols in these embodiments of the multi-touch surface would not be printed permanently on the surface. Instead, the position of the key symbols would be reprogrammably displayed on the surface by light emitting polymers, liquid crystal, or other dynamic visual display means embedded in the multi-touch surface apparatus along with the proximity sensor arrays.

Given such an apparatus, step **702** retrieves the current paths from both hands and awaits what will be known as a layout homing gesture. If decision diamond **704** decides with the help of, a hand's synchronization detector that all five of the hand's fingers have just been placed on the surface synchronously, step **706** will attempt to snap the key layout to the hand such that the hand's home row keys lie under the synchronized fingertips, wherever the hand is on the surface. Step **706** retrieves the measured hand offsets from the hand position estimator and translates all key regions which are normally typed by the given hand in proportion to the measured hand offsets. Note the currently measured rather than filtered estimates of offsets can be used because when all five fingers are down there is no danger of finger misidentification corrupting the measured offsets. This procedure assumes that the untranslated locations of the home row keys are the same as the default finger locations for the hand.

Decision diamond **708** checks whether the fingers appear to be in a neutral, partially closed posture, rather closed than outstretched or pinched together. If the posture is close to neutral, step **710** may further offset the keys normally typed by each finger, which for the most part are the keys in the same column of the finger by the measured finger offsets. Temporal filtering of these finger offsets over several layout homing gestures will tend to scale the spacing between columns of keys to the user's hand size. Spacing between rows is scaled down in proportion to the scaling between columns.

With the key layout for the hand's keys morphed to fit the size and current position of the resting hand, step **712** updates

the displayed position of the symbols on the surface, so that the user will see that the key layout has snapped to the position of his hand. From this stage the user can begin to type and the typing recognizer **718** will use the morphed key region locations to decide what key regions are being pressed. The layout will remain morphed this way until either the user performs another homing gesture to move it somewhere else on the surface, or until the user takes both hands off the surface for a while. Decision diamond **714** will eventually time out so that step **716** can reset the layout to its default position in readiness for another user or usage session.

For smaller multi-touch surfaces in which the key layout is permanently printed on the surface, it is advantageous to give the user tactile feedback about the positions of key regions. However, any tactile indicators placed on the surface must be carefully designed so as not to impede smooth sliding across the surface. For example, shallow depressions made in the surface near the center of each key mimicking the shallow depressions common on mechanical keyboard keycaps would cause a vibratory washboard effect as the hand slides across the surface. To minimize such washboard effects, in the preferred embodiment the multi-touch surface provides for the fingertips of each hand a single, continuous depression running from the default index fingertip location to the default pinky fingertip location. This corresponds on the QWERTY key layout to shallow, slightly arched channels along home row from the "J" key to the ";" key for the right hand, and from the "A" key to the "F" key for the left hand. Similarly, the thumbs can each be provided with a single oval-shaped depression at their default locations, slanted slightly from vertical to match the default thumb orientation. These would preferably correspond to "Space" and "BackSpace" key regions for the right and left thumbs, respectively. Such minimal depressions can tactilely guide users' hands back to home row of the key layout without requiring users to look down at the surface and without seriously disrupting finger chord slides and manipulations on the surface.

The positions of key regions off home row can be marked by other types of tactile indicators. Simply roughening the surface at key regions does not work well. Though humans easily differentiate textures when sliding fingers over them, most textures cannot be noticed during quick taps on a textured region. Only relatively abrupt edges or protrusions can be sensed by the users' fingertips under typing conditions. Therefore, a small raised dot like a Braille dot is formed on top of the surface at the center of each key region. The user receives feedback on the accuracy of their typing strokes from where on the fingertip a dot is felt. This feedback can be used to correct finger aim during future keypresses. Since single finger slides are ignored by the chord motion recognizer, the user can also slide a finger around the surface in tactile search of a particular key region's dot and then tap the key region when the dot is found, all without looking at the surface. Each dot should be just: large enough to be felt during tapping but not so large as to impede chord slides across the surface. Even if the dots are not large enough to impede sliding, they can still corrupt proximity and fingertip centroid measurements by raising the fingertip flesh near the dot off the surface thus locally separating the flesh from the underlying proximity sensing electrode. Therefore, in the preferred embodiment, the portion of each dot above the surface dielectric is made of a conductive material. This improves capacitive coupling between the raised fingertip flesh and the underlying electrodes.

FIG. **42** shows the steps within the keypress detection loop. Step **750** retrieves from the current identified path data **250** any paths which were recently created due to hand part touchdown or the surface. Decision diamond **752** checks whether the path proximity reached a keypress proximity thresh for the first time during the current sensor array scan. If the proximity has not reached the threshold yet or has already exceeded it previously, control returns to step **750** to try keypress detection on the next recent path. If the path just crossed the keypress proximity threshold decision diamond **754** checks whether the contact path has been identified as a finger rather than a palm. To give the users the freedom rest the palms anywhere on the surface, palm presses should not normally cause keypresses, and are therefore ignored. Assuming the path is a finger, decision diamond **756** checks whether the hand the identified finger comes from is currently performing a chord slide gesture or writing via the pen grip hand configuration. Asynchronous finger presses are ignored once these activities have started, as also indicated in step **660** of FIG. **40**A. Assuming such hand activities are not ongoing, decision diamond **757** proceeds with debounce tests which check that the finger has touched the surface for at least two sensor array scan cycles and that it had been off the surface for several scan cycles before touching down. The path tracking module (FIG. **22**) facilitates such liftoff debouncing by reactivating in step **334** a finger's old path if the finger lifts off and quickly touches back down over the same spot. Upon reactivation the time stamp of the last liftoff by the old path must be preserved for comparison with the time stamp of the new touchdown.

If all of these tests are passed, step **758** looks up the current path position ($P_x[n],P_y[n]$), and step **760** finds the key region whose reference position is closest to the fingertip centroid. Decision diamond **762** checks that the nearest region is within a reasonable distance of the finger, and if not causes the finger press to be ignored. Assuming a key region is close to the finger, step **764** creates a keypress element data structure containing the path, index identifier and finger identity, the closest key region, and a time stamp indicating when the finger crossed the keypress proximity threshold. Step **766** then appends this element data structure to the tail of a FIFO keypress queue. This accomplished, processing returns to step **750** to process or wait for touchdowns by other fingers.

The keypress queue effectively orders finger touchdowns by when they pass the keypress transmitted to the host. However, an element's key symbol is not assured transmission of the host once in the keypress queue. Any of a number of conditions such as being part of a synchronized subset of pressing fingers can cause it to be deleted from the queue before being transmitted to the host. In this sense the keypress queue should be considered a keypress candidate queue. Unlike the ordered lists of finger touchdowns and releases maintained for each hand separately in the synchronization detector, the keypress queue includes and orders the finger touchdowns from both hands.

FIG. **43**A shows the steps within the keypress acceptance and transmission loop. Step **770** picks the element at the head of the keypress queue, which represents the oldest finger touchdown which has neither been deleted from the queue as an invalid keypress candidate nor transmitted its associated key symbol. Decision diamond **772** checks whether the path is still identified as a finger. While waiting in the queue path proximity could have increased so much that the identification system decides the path is actually from a palm heel, in which case step **778** deletes the keypress element without transmitting to the host and step **770** advances processing to the next element. Decision diamond **774** also invalidates the element if its press happened synchronously with other fingers of the same hand. Thus decision diamond **774** follows through on deletion command steps **601**, **612**, **615**, **620** of the

synchronization detection process (FIG. **39**). Decision diamond **776** invalidates the keypress if too much lateral finger motion has occurred since touchdown, even if that lateral finger motion has not yet caused a chord slide to start. Because users may be touch typing on the surface, several millimeters of lateral motion are allowed to accommodate glancing fingertip motions which often occur when quickly reaching for keys. This is much more glancing tap motion than is tolerated by touchpads which employ a single finger slide for mouse cursor manipulation and a single finger tap for key or mouse button click emulation.

Decision diamond **780** checks whether the finger whose touchdown created the keypress element has since lifted off the surface. If so, decision diamond **782** checks whether it was lifted off soon enough to qualify as a normal key tap. If so, step **784** transmits the associated key symbol to the host and step **778** deletes it from the head of the queue. Note that a keypress is always deleted from the queue upon liftoff, but even though it may have stayed on the surface for a time exceeding the tap timeout, it may have still caused transmission as a modifier key, as an impulsive press with hand resting, or as a typematic press, as described below.

When a keypress is transmitted to the host it is advantageous for a sound generation device on the multi-touch surface apparatus or host computer to emit an audible click or beep as feedback to the user. Generation of audible click and beep feedback in response to keypresses is well known in commercial touchscreens, kiosks, appliance control panels and mechanical keyboards in which the keyswitch action is nearly silent and does not have a make force threshold which feels distinctive to the user. Feedback can also be provided as a light on the multi-touch surface apparatus which flashes each time a keypress is sent. Keypresses accompanied by modifier keypresses should cause longer flashes or tones to acknowledge that the key symbol includes modifiers.

If the finger has not yet lifted, decision diamond **786** checks whether its associated key region is a modifier such as <shift>, <ctrl>, or <alt>. If so, step **788** advances to the next element in the queue without deleting the head. Processing will continue at step **772** to see if the next element is a valid key tap. If the next element successfully reaches the transmission stage, step **784** will scan back toward the head of the queue for any modifier regions which are still pressed. Then step **784** can send the next element's key symbol along with the modifying symbols of any preceding modifier regions.

Decision diamond **782** requires that users touch the finger on the surface and lift back off within a few hundred milliseconds for a key to be sent. This liftoff timing requirement substitutes for the force activation threshold of mechanical keyswitches Like the force threshold of mechanical keyswitches, the timing constraint provides a way for the user to rest the finger on the key surface without invoking a keypress. The synchronization detector **14** provides another way forefingers to rest on the surface without generating key symbols: they must touch down at the same time as at least one other finger. However, sometimes users will start resting by simultaneously placing the central fingertips on the surface, but then they follow asynchronously with the pinky a second later and the thumb a second after that. These latter presses are essentially asynchronous and will not be invalidated by the synchronization detector, but as long as they are not lifted within a couple hundred milliseconds, decision diamond **782** will delete them without transmission. But, while decision diamond **782** provides tolerance of asynchronous finger resting, its requirement that fingers quickly lift off, i.e., crisply tap, the surface to cause key generation makes it very difficult to keep most of the fingers resting on the surface to support the hands while tapping long sequences of symbols. This causes users to raise their hands off the surface and float them above the surface during fast typing sequences. This is acceptable typing posture except that the users arms will eventually tire if the user fails to rest the hands back on the surface between sequences.

To provide an alternative typing posture which does not encourage suspension of the hands above the surface, decision diamond **790** enables a second key acceptance mode which does not require quick finger liftoff after each press. Instead, the user must start with all five fingers of a hand resting on the surface. Then each time a finger is asynchronously raised off the surface and pressed on a key region, that key region will be transmitted regardless of subsequent liftoff timing. If the surface is hard such that fingertip proximity quickly saturates as force is applied, decision diamond **792** checks the impulsivity of the proximity profile for how quickly the finger proximity peaks. If the proximity profile increases to its peak very slowly over time, no key will be generated. This allows the user to gently set down a raised finger without generating a key in case the user lifts the finger with the intention of generating a key but then changes his mind. If the touch surface is compressible, decision diamond **792** can more directly infer finger force from the ratio of measured fingertip proximity to ellipse axis lengths. Then it can threshold the inferred force to distinguish deliberate key presses from gentle finger rests. Since when intending to generate a key the user will normally press down on the new key region quickly after lifting off the old key region, the impulsivity and force thresholds should increase with the time since the finger lifted off the surface.

Emulating typematic on a multi-touch surface presents special problems if finger resting force cannot be distinguished reliably from sustained holding force on a key region. In this case, the special touch timing sequence detected by the steps of FIG. **43**B supports reliable typematic emulation. Assuming decision diamond **798** finds that typematic has not started yet, decision diamond **794** checks whether the keypress queue element being processed represents the most recent finger touchdown on the surface. If any finger touchdowns have followed the touchdown represented by this element, typematic can never start from this queue element. Instead, decision diamond **796** checks whether the element's finger has been touching longer than the normal tap timeout. If the finger has been touching too long, step **778** should delete its keypress element because decision diamond **786** has determined it is not a modifier and decision diamond **794** has determined it can never start typematic. If decision diamond **794** determines that the keypress element does not represent the most recent touchdown, yet decision diamond **796** indicates the element has not exceeded the tap timeout, processing returns to step **770** to await either liftoff or timeout in a future sensor array scan. This allows finger taps to overlap in the sense that a new key region can be pressed by a finger before another finger lifts off the previous key region. However, either the press times or release times of such a pair of overlapping finger taps must be asynchronous to prevent the pair from being considered a chord tap.

Assuming the finger touchdown is the most recent, decision diamond **800** checks whether the finger has been touching for a typematic hold setup interval of between about half a second and a second. If not, processing returns to **770** to await either finger liftoff or the hold setup condition to be met during future scans of the sensor array. When the hold setup condition is met, decision diamond **802** checks whether all other fingers on the hand of the given finger keypress lifted off the surface more than a half second ago. If they did, step **804**

will initialize typematic for the given keypress element. The combination of decision diamonds **800** and **802** allow the user to have other fingers of the hand to be resting on the surface when a finger intended for typematic touches down. But typematic will not start unless the other fingers lift off the surface within half a second of the desired typematic finger's touchdown, and typematic will also not start until the typematic finger has a continued to touch the surface for at least half a second after the others lifted off the surface. If these stringent conditions are not met, the keypress element will not start typematic and will eventually be deleted through either tap timeout **782** when the finger lifts off or through tap timeout **796**) if another touches down after it.

Step **804** simply sets a flag which will indicate to decision diamond **798** during future scan cycles that typematic has already started for the element. Upon typematic initialization, step **810** sends out the key symbol for the first time to the host interface communication queue, along with any modifier symbols being held down by the opposite hand. Step **812** records the time the key symbol is sent for future reference by decision diamond **808**. Processing then returns to step **770** to await the next proximity image scan.

Until the finger lifts off or another taps asynchronously, processing will pass through decision diamond **798** to check whether the key symbol should be sent again. Step **806** computes the symbol repeat interval dynamically to be inversely proportional to finger proximity. Thus the key will repeat faster as the finger is pressed on the surface harder or a larger part of the fingertip touches the surface. This also reduces the chance that the user will cause more repeats than intended since as finger proximity begins to drop during liftoff the repeat interval becomes much longer. Decision diamond **808** checks whether the dynamic repeat interval since the last typematic symbol send has elapsed, and if necessary sends the symbol again in **810** and updates the typematic send time stamp **812**.

It is desirable to let the users rest the other fingers back onto the surface after typematic has initiated **804** and while typematic continues, but the user must do so without tapping. Decision diamond **805** causes typematic to be canceled and the typematic element deleted **778** if the user asynchronously taps another finger on the surface as if trying to hit another key. If this does not occur, decision diamond **182** will eventually cause deletion of the typematic element when its finger lifts off.

The typing recognition process described above thus allows the multi-touch surface to ergonomically emulate both the typing and hand resting capabilities of a standard mechanical keyboard. Crisp taps or impulsive presses on the surface generate key symbols as soon as the finger is released or decision diamond **792** verifies the impulse has peaked, ensuring prompt feedback to the user. Fingers intended to rest on the surface generate no keys as long as they are members of a synchronized finger press or release subset or are placed on the surface gently and remain there along with other fingers for a second or two. Once resting, fingers can be lifted and tapped or impulsively pressed on the surface to generate key symbols without having to lift other resting fingers. Typematic is initiated ether by impulsively pressing and maintaining distinguishable force on a key, or by holding a finger on a key while other fingers on the hand are lifted. Glancing motions of single fingers as they tap key regions are easily tolerated since most cursor manipulation must be initiated by synchronized slides of two or more fingers.

Other embodiments of the invention will be apparent to those skilled in the art from consideration of the specification and practice of the invention disclosed herein. It is intended that the specification and examples be considered as exemplary only, with a true scope and spirit of the invention being indicated by the following claims.

What is claimed is:

1. A method of selecting input of a computing system including a touch sensing surface, the method comprising:

detecting a set of multiple contacts touched down on the surface;

determining a number of the contacts;

determining whether the contacts are in motion across the surface;

determining whether the contacts are decelerating across the surface, based on a change in average speed of the contacts across the surface; and

selecting an input based on the number of contacts, whether the contacts are in motion across the surface, and whether the contacts are decelerating across the surface.

2. The method of claim **1**, the method further comprising:

detecting a liftoff of a first subset of one or more contacts of the set, wherein a second subset of one or more contacts of the set remains touched down; and

determining a motion of the first subset prior to the liftoff;

wherein selecting the input includes selecting, while the first subset remains lifted off from the surface after the liftoff, one of a plurality of a post-liftoff states, wherein the selection is determined by first information including the motion of the first subset prior to the liftoff.

3. The method of claim **2**, wherein the input is selected prior to the liftoff, the method further comprising:

generating the input based on the motion of the first subset prior to the liftoff.

4. The method of claim **3**, wherein generating the input is based on the set of contacts.

5. The method of claim **3**, further comprising:

determining whether the input is a currently-selected input at the time of the liftoff, wherein the first information includes the determination that the input is currently-selected at the time of the liftoff.

6. The method of claim **3**, wherein one of the post-liftoff states includes terminating the input, wherein terminating the input is selected based on determining whether the one or more contacts are decelerating.

7. The method of claim **6**, wherein terminating the input is selected if the motion of the first subset is determined to be paused prior to the liftoff.

8. The method of claim **6**, wherein terminating the input is selected if the motion of the first subset is determined to be decelerating prior to the liftoff.

9. The method of claim **3**, wherein one of the post-liftoff states includes continuing a motion of the input.

10. The method of claim **9**, further comprising:

adjusting the continued motion of the input based on the second subset.

11. The method of claim **10**, wherein adjusting the continued motion includes adjusting the continued motion based on a motion of the second subset.

12. The method of claim **11**, wherein adjusting the continued motion based on the motion of the second subset includes adjusting the continued motion based on a translation motion of the second subset.

13. The method of claim **10**, further comprising:

detecting one or more liftoffs of the one or more contacts in the second subset, wherein adjusting the continued motion includes terminating the continued motion in response to detecting that all of the one or more contacts in the second subset have lifted off.

14. The method of claim **9**, further comprising:

detecting a touchdown of one or more contacts after the liftoff of the first subset; and

terminating the input in response to detecting the touchdown of the one or more contacts after the liftoff of the first subset.

15. The method of claim **9**, wherein continuing the motion of the input is selected if the motion of the first subset is determined to be moving at a constant speed prior to the liftoff.

16. The method of claim **9**, wherein continuing the motion of the input is selected if the motion of the first subset is determined to be greater than a predetermined acceleration prior to the liftoff.

17. The method of claim **9**, wherein a speed of the continuing motion of the input is based on the motion of the first subset prior to the liftoff.

18. The method of claim **17**, wherein the speed of the continuing motion of the input is set to a same speed as the motion of the first subset prior to the liftoff.

19. The method of claim **3**, wherein the input includes one of a cursor motion, a scroll motion, and a drag motion.

20. The method of claim **3**, wherein generating the input includes initiating the input based on one of a synchronized motion of the first subset and a synchronized touchdown of the first subset.

21. The method of claim **20**, wherein generating the input includes generating a motion of the input while the first subset remains touched down after the initiating of the input, and the motion of the input while the first subset remains touched down is based on a combination of motions of contacts in the first and second subsets.

22. The method of claim **2**, wherein the motion of the first subset prior to the liftoff of the first subset is an amount of change in direction of the first subset.

23. The method of claim **22**, wherein selecting the one of the plurality of post-liftoff states includes selecting termination of the input in response to a determination that the amount of change in direction is greater than a predetermined curve threshold.

24. A non-transitory computer-readable storage medium storing computer-readable program instructions executable to perform a method of selecting input of a computing system including a touch sensing surface, the method comprising:

detecting a set of multiple contacts touched down on the surface;

determining a number of the contacts;

determining whether the contacts are in motion across the surface;

determining whether the contacts are decelerating across the surface, based on a change in average speed of the contacts across the surface; and

selecting an input based on the number of contacts, whether the contacts are in motion across the surface, and whether the contacts are decelerating across the surface.

25. An apparatus comprising:

a touch sensing surface; and

an input system that

detects a set of multiple contacts touched down on the surface;

determines a number of the contacts;

determines whether the contacts are in motion across the surface;

determines whether the contacts are decelerating across the surface, based on a change in average speed of the contacts across the surface; and

selects an input based on the number of contacts, whether the contacts are in motion across the surface, and whether the contacts are decelerating across the surface.

26. The non-transitory computer-readable storage medium of claim **24**, the method further comprising:

detecting a liftoff of a first subset of one or more contacts of the set, wherein a second subset of one or more contacts of the set remains touched down; and

determining a motion of the first subset prior to the liftoff;

wherein selecting the input includes selecting, while the first subset remains lifted off from the surface after the liftoff, one of a plurality of a post-liftoff states, wherein the selection is determined by first information including the motion of the first subset prior to the liftoff.

27. The non-transitory computer-readable storage medium of claim **26**, wherein the input is selected prior to the liftoff, the method further comprising:

generating the input based on the motion of the first subset prior to the liftoff.

28. The non-transitory computer-readable storage medium of claim **27**, further comprising:

determining whether the input is a currently-selected input at the time of the liftoff, wherein the first information includes the determination that the input is currently-selected at the time of the liftoff.

29. The non-transitory computer-readable storage medium of claim **27**, wherein one of the post-liftoff states includes terminating the input, wherein terminating the input is selected based on determining whether the one or more contacts are decelerating.

30. The apparatus of claim **25**, the method further comprising:

detecting a liftoff of a first subset of one or more contacts of the set, wherein a second subset of one or more contacts of the set remains touched down; and

determining a motion of the first subset prior to the liftoff;

wherein selecting the input includes selecting, while the first subset remains lifted off from the surface after the liftoff, one of a plurality of a post-liftoff states, wherein the selection is determined by first information including the motion of the first subset prior to the liftoff.

31. The apparatus of claim **30**, wherein the input is selected prior to the liftoff, the method further comprising:

generating the input based on the motion of the first subset prior to the liftoff.

32. The apparatus of claim **31**, further comprising:

determining whether the input is a currently-selected input at the time of the liftoff, wherein the first information includes the determination that the input is currently-selected at the time of the liftoff.

33. The apparatus of claim **31**, wherein one of the post-liftoff states includes terminating the input, wherein terminating the input is selected based on determining whether the one or more contacts are decelerating.

* * * * *